



Altronix WP4 Weatherproof Enclosure Installation Guide

[Home](#) » [Altronix](#) » Altronix WP4 Weatherproof Enclosure Installation Guide 

Contents

- [1 Altronix WP4 Weatherproof Enclosure](#)
- [2 Overview:](#)
- [3 Specifications:](#)
- [4 Installation Instructions:](#)
- [5 Wall Mount Installation](#)
- [6 Pole Mounting Using Optional Pole Mount Kit PMK1 \(not included\):](#)
- [7 Enclosure Dimensions](#)
- [8 ABOUT COMPANY](#)
- [9 Documents / Resources](#)
 - [9.1 References](#)
- [10 Related Posts](#)



Altronix WP4 Weatherproof Enclosure



Overview:

Altronix WP4 is a UL Listed, NEMA 4/IP 66 Rated outdoor power supply/battery and accessory enclosure with a metal back plane. It can accommodate a wide variety of Altronix power supplies, sub-assemblies, and other accessories.


Specifications:

- NEMA 4/4X, IP66-11 Rated enclosure for outdoor use.
- Lightweight molded fiberglass reinforced polyester enclosure is corrosion-resistant and does not contain halogens.
- Lockable stainless steel latches.
- Includes metal back plane for mounting power supplies and accessories.
- Integral flanges simplify wall or pole mounting.
- **Applications:** Power Supplies, Batteries and Auxiliary modules.
- **Product weight:** 1.8 lb. (0.8 kg).
- **Shipping weight:** 2.6 lbs (1.17 kg).

Installation Instructions:

1. Remove back plane inside enclosure by removing the four (4) mounting screws (do not discard hardware).
2. Mark and drill desired inlets on the enclosure to facilitate wiring (Fig. 1, pg. 2).
3. Enclosure can be wall or pole mounted. See the detailed instructions below.
4. Mount circuit boards to back plane.
5. Secure back plane inside the enclosure with the four (4) mounting screws.
6. Mount unit in desired location with the appropriate fasteners utilizing the holes provided on the flanges (Enclosure Dimensions, pg. 4).
7. To facilitate wire entry utilize weather tight NEMA 4 rated connectors, bushings and cable.


Fig. 1



Wall Mount Installation

1. Place unit at desired location and secure with mounting screws (not included) (Fig. 2, pg. 3).

Fig. 2



Pole Mounting Using Optional Pole Mount Kit PMK1 (not included):

This installation should be made by qualified service personnel. This product contains no serviceable parts. PMK1 is intended for use with Altronix outdoor rated power supplies or accessories housed in WP1, WP2, WP3 and WP4 enclosures. Brackets are designed for use with the Wormgear Quick Release Straps (two included).

1. Thread one (1) wormgear quick release strap through the slots on the back of a mounting bracket (Fig. 3, pg. 3).
2. Once the desired height of the top Pole Mount bracket is achieved, tighten the straps down by sliding open end of the strap through the locking mechanism on the strap, then tighten the screw with flat head screwdriver or 5/16" hex socket driver (Fig. 4, pg. 3 and Fig. 6, pg. 3).

Fig. 3




Fig. 4






Fig. 5




3. Attach the bottom bracket to the enclosure by inserting bolts through the flange of the enclosure and into the bracket, tightening bolts with a 7/16" hex socket (Fig. 5, pg. 3).
4. Thread the second worm gear quick release strap through the slots on the back of the bottom mounting bracket (Fig. 3, pg. 3).
5. Mount enclosure onto the top bracket by inserting bolts through flange of the enclosure and into the bracket, tightening bolts with a 7/16" hex socket (Fig. 5, pg. 3).

6. Tighten the straps of the bottom bracket down by sliding the open end of the strap through the locking mechanism on the strap, then tighten screw with flat head screwdriver or 5/16" hex socket driver (Fig. 6, pg. 3).
7. lip excess straps.



Enclosure Dimensions

(H x W x D approximate): 9.32" x 7.32" x 4.92" (236.7mm x 185.9mm x 125mm)



ABOUT COMPANY

- Altronix is not responsible for any typographical errors.
- 140 58th Street, Brooklyn, New York 11220 USA
- **phone:** 718-567-8181
- **fax:** 718-567-9056
- **website:** www.altronix.com
- **e-mail:** info@altronix.com IIWP4

Documents / Resources

<div><div>WP4</div><div>Weatherproof Enclosure</div><div>Installation Guide</div><div><div><div>Alttronix</div></div></div></div>	<div><div>Alttronix WP4 Weatherproof Enclosure [pdf] Installation Guide</div><div>WP4, Weatherproof Enclosure, WP4 Weatherproof Enclosure</div></div>
<div><div>WP4</div><div>Weatherproof Enclosure</div><div>Installation Guide</div><div><div><div>Alttronix</div></div></div></div>	<div><div>Alttronix WP4 Weatherproof Enclosure [pdf] Installation Guide</div><div>WP4, Weatherproof Enclosure, Enclosure, WP4</div></div>

References

-  [Alttronix Home](#)