

Quoizel HC9011IB

Quoizel Hillcrest HC9011IB Outdoor Post Lantern User Manual

Model: HC9011IB

[Overview](#)

[Safety](#)

[Contents](#)

[Setup](#)

[Operation](#)

[Maintenance](#)

[Troubleshooting](#)

[Specifications](#)

[Warranty](#)

[Support](#)

1. PRODUCT OVERVIEW

The Quoizel Hillcrest HC9011IB Outdoor Post Lantern is designed to enhance outdoor spaces with its classic Arts & Crafts style. Featuring an imperial bronze finish and white linen textured glass, this fixture provides a soft, inviting glow, reducing glare and hot spots. Constructed from durable aluminum, it is built to withstand various outdoor conditions, ensuring lasting performance and aesthetic appeal.

This versatile post light is suitable for patios, porches, gardens, pools, entryways, or driveways, complementing both traditional and contemporary home exteriors.



Figure 1.1: The Quoizel Hillcrest HC90111B Outdoor Post Lantern installed on a post in front of a residential garage and entryway. The lantern features an imperial bronze finish and white linen textured glass, providing ambient outdoor lighting.

2. IMPORTANT SAFETY INFORMATION

Please read all instructions carefully before installation and use. Retain this manual for future reference.

- **Electrical Safety:** Always disconnect power at the circuit breaker or fuse box before installing, servicing, or cleaning the fixture. Ensure all electrical connections comply with local codes and ordinances. If you are unsure about wiring, consult a qualified electrician.
- **Grounding:** The fixture must be properly grounded to prevent potential electrical shock.
- **Bulb Requirements:** Use only bulbs of the specified type and wattage. Exceeding the maximum wattage can cause overheating and damage to the fixture or create a fire hazard.
- **Outdoor Use:** This fixture is designed for outdoor use and is waterproof. However, ensure all seals and connections are secure during installation to maintain its weather resistance.
- **Handling Glass:** Handle the glass components with care to avoid breakage and injury.
- **Proposition 65 Warning:** This product may contain chemicals known to the State of California to cause cancer and birth defects or other reproductive harm. Wash hands after handling.

3. PACKAGE CONTENTS

Verify that all components are present and undamaged before beginning installation. If any parts are missing or damaged, do not proceed with installation and contact customer support.

- Quoizel Hillcrest HC90111B Post Lantern Fixture (1)
- White Linen Textured Glass Panels (Quantity as required for assembly)
- Mounting Hardware Kit (Screws, wire nuts, etc.)

- Installation Template (if applicable)
- Instruction Manual (This document)

4. INSTALLATION INSTRUCTIONS

This post lantern is designed for upward-mount installation to a junction box. Professional installation is recommended if you are not familiar with electrical wiring.

1. Prepare for Installation:

- Turn off power at the main circuit breaker or fuse box to avoid electrical shock.
- Ensure the mounting surface (post or pedestal) is stable and capable of supporting the fixture's weight.
- Unpack all components and lay them out on a clean, flat surface.

2. Mount the Fixture:

- Attach the mounting bracket (if separate) to the junction box on your post using the provided screws.
- Carefully pull the electrical wires from the junction box through the center hole of the mounting bracket.

3. Make Electrical Connections:

- Connect the **black** wire from the fixture to the **black** (hot) wire from the junction box using a wire nut.
- Connect the **white** wire from the fixture to the **white** (neutral) wire from the junction box using a wire nut.
- Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box and to the mounting bracket using a ground screw.
- Ensure all connections are secure and tuck them neatly into the junction box.

4. Secure the Fixture:

- Align the fixture base with the mounting bracket and secure it using the provided screws or nuts.
- Ensure the fixture is flush against the mounting surface and stable.

5. Install Glass Panels and Bulb:

- Carefully insert the white linen textured glass panels into the fixture frame according to the design.
- Screw in one E26 base bulb (not included) into the socket. Do not exceed the maximum wattage of 150 watts.

6. Restore Power:

- Turn the power back on at the circuit breaker.
- Test the light fixture to ensure proper operation.



Figure 4.1: A detailed view of the top section of the Quoizel Hillcrest HC9011IB lantern, highlighting the imperial bronze finish and the texture of the white linen glass panels.

5. OPERATING INSTRUCTIONS

The Quoizel Hillcrest HC9011IB Outdoor Post Lantern operates via a standard wall switch or an external control system connected to its power source.

- **Turning On/Off:** Use the connected wall switch to turn the light fixture on or off.
- **Dimming Functionality:** This fixture supports full-range dimming when used with compatible dimmable bulbs and a suitable dimmer switch (sold separately). Consult your dimmer switch's instructions for proper operation.
- **Remote Control:** The product specifications mention "Remote" as a control method and "Bluetooth" for connectivity. If your specific model includes these features, refer to the separate remote control or smart home integration guide for pairing and operation.

6. CARE AND MAINTENANCE

Regular care will help maintain the appearance and functionality of your outdoor post lantern.

- **Cleaning:**
 - Ensure power is off before cleaning.
 - Wipe the fixture with a soft, damp cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
 - For glass panels, use a mild glass cleaner if necessary, applied to a cloth, not directly to the fixture.
- **Bulb Replacement:**

- Turn off power at the circuit breaker.
 - Allow the bulb to cool completely before attempting to replace it.
 - Unscrew the old bulb and screw in a new E26 base bulb. Ensure the replacement bulb does not exceed 150 watts.
 - Restore power and test the light.
- **Inspection:** Periodically inspect the fixture for any signs of wear, loose connections, or damage. Address any issues promptly to ensure safety and performance.

7. TROUBLESHOOTING GUIDE

If you encounter issues with your Quoizel Hillcrest HC9011IB Outdoor Post Lantern, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	<ul style="list-style-type: none"> ◦ No power to the fixture. ◦ Bulb is faulty or loose. ◦ Incorrect wiring. 	<ul style="list-style-type: none"> ◦ Check circuit breaker/fuse. ◦ Ensure wall switch is ON. ◦ Replace bulb or tighten it. ◦ Verify wiring connections (consult electrician if unsure).
Light flickers or is dim.	<ul style="list-style-type: none"> ◦ Loose bulb connection. ◦ Incorrect bulb wattage. ◦ Faulty dimmer switch (if applicable). 	<ul style="list-style-type: none"> ◦ Tighten bulb. ◦ Ensure bulb wattage is within limits. ◦ Check dimmer switch compatibility and wiring.
Glass panels are loose or rattling.	<ul style="list-style-type: none"> ◦ Panels not seated correctly. ◦ Retaining clips/screws loose. 	<ul style="list-style-type: none"> ◦ Gently re-seat glass panels. ◦ Tighten any retaining clips or screws.

If the problem persists after attempting these solutions, please contact customer support.

8. PRODUCT SPECIFICATIONS

Brand	Quoizel
Model Number	HC9011IB
Material	Aluminum (Fixture), Glass (Shade)
Finish	Imperial Bronze
Shade Color	White Linen Textured Glass
Dimensions (L x W x H)	11"L x 11"W x 18.75"H
Item Weight	8.6 Pounds
Number of Lights	1
Light Source	Socketed (Bulb not included)
Bulb Base	E26
Max Wattage	150 watts
Voltage	120 Volts
Indoor/Outdoor Usage	Outdoor

Water Resistance Level	Waterproof
Mounting Type	Post Mount, upward-mount-to-junction-box
Control Method	Remote, Push Button (via external switch/dimmer)
Connectivity Protocol	Bluetooth (if applicable to specific model variant)
Special Features	Arts & Crafts design, warm opaque linen glass, full range dimming capability
Certification	ETL Listed

9. WARRANTY INFORMATION

The Quoizel Hillcrest HC9011IB Outdoor Post Lantern comes with a **3-year limited manufacturer's warranty**. This warranty covers defects in materials and workmanship under normal use and service. Please retain your proof of purchase for warranty claims. For full details regarding warranty coverage and limitations, please contact Quoizel customer support.

10. CUSTOMER SUPPORT

For technical assistance, missing parts, or warranty inquiries, please contact Quoizel customer support:

- **Website:** Visit the official Quoizel website for FAQs and support resources.
- **Phone:** Refer to the contact information provided on the Quoizel website or product packaging.
- **Email:** Use the contact form or email address available on the Quoizel website.

When contacting support, please have your model number (HC9011IB) and proof of purchase readily available.