

CASIO LK-201TV

CASIO LK-201TV Electronic Keyboard User Manual

Model: LK-201TV

1. INTRODUCTION

Thank you for purchasing the CASIO LK-201TV Electronic Keyboard. This instrument is designed to provide a comprehensive musical experience, combining keyboard performance with interactive karaoke features. Its intuitive design, including light-up keys and a TV connection, makes it suitable for both beginners and experienced users.

This manual provides essential information on setting up, operating, and maintaining your LK-201TV keyboard. Please read it thoroughly before use to ensure proper operation and to maximize your enjoyment of the product.



Image: The CASIO LK-201TV electronic keyboard, featuring 61 keys, a central LCD display, control buttons, built-in speakers on either side, and a microphone connected to the top left. Several keys on the keyboard are illuminated in red, indicating the light-up key function.

2. SETUP

2.1 Power Supply

Connect the included AC adapter to the DC 9V terminal on the rear of the keyboard and plug it into a standard wall outlet. Ensure the power switch is in the OFF position before connecting.

2.2 TV Connection

To utilize the karaoke and lesson display features, connect the keyboard to your television using a standard video cable (not included). Locate the VIDEO OUT terminal on the rear of the keyboard and connect it to the video input

(usually yellow RCA jack) on your TV. Select the appropriate video input channel on your TV.

2.3 Microphone Connection

Insert the plug of the included microphone into the MIC IN jack on the keyboard. Adjust the microphone volume using the dedicated MIC VOLUME knob.

2.4 USB Connection

The USB terminal allows for data transfer between the keyboard and a computer. Use a standard USB cable (Type B) to connect the keyboard to your PC. This enables transferring MIDI data or songs downloaded from the internet.

3. OPERATING INSTRUCTIONS

3.1 Basic Playback

Turn on the power. Select a tone using the TONE buttons. The large LCD display will show the selected tone name. The keyboard features 61 standard keys with touch response, allowing for dynamic expression based on how hard you press the keys. This can be toggled On/Off.

3.2 Light-Up Keys Function

When using the lesson function or playing built-in songs, the 'light-up keys' feature will illuminate the next key to be played in red. Up to 10 keys can light up simultaneously. This visual guide assists in learning and practicing.

3.3 3-Step Lesson System

The 'Advanced 3-Step Lesson' system allows you to practice at your own pace:

1. **Step 1: Listen** - Listen to the song.
2. **Step 2: Watch** - Follow the light-up keys.
3. **Step 3: Play** - Play along with the accompaniment.

The system includes a scoring function, providing feedback on your performance and allowing for competitive play with others.

3.4 Karaoke Function

With the TV connected, you can display lyrics for built-in songs on your television screen. Sing along using the microphone, and the keyboard will provide a performance score, visible on the TV. Adjust the microphone volume as needed.

3.5 Tones and Rhythms

The LK-201TV offers 264 diverse tones, including keyboard instruments, string instruments, and synth sounds. It also features 100 rich rhythms covering various genres such as pop, rock, jazz, and Latin. Use the dedicated buttons to select your desired tone and rhythm.

3.6 Automatic Accompaniment

Engage the automatic accompaniment function to add a full band sound to your playing. Simply specify chords, and the keyboard will generate appropriate backing tracks.

3.7 Song Memory Function

The song memory function allows you to record and easily review your own performances. This is useful for tracking

progress and identifying areas for improvement.

4. MAINTENANCE

To ensure the longevity and optimal performance of your CASIO LK-201TV, follow these maintenance guidelines:

- **Cleaning:** Wipe the keyboard with a soft, dry cloth. For stubborn dirt, use a cloth lightly dampened with water and a mild detergent, then wipe dry immediately. Avoid abrasive cleaners, solvents, or polishes.
- **Storage:** Store the keyboard in a cool, dry place away from direct sunlight, extreme temperatures, and high humidity.
- **Handling:** Avoid dropping the keyboard or subjecting it to strong impacts. Do not place heavy objects on top of it.
- **Power:** Disconnect the AC adapter from the wall outlet when the keyboard will not be used for an extended period.

5. TROUBLESHOOTING

If you encounter issues with your LK-201TV, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
No sound	Power off; Volume too low; Headphones connected.	Turn power on; Increase Master Volume; Disconnect headphones.
Light-up keys not working	Function disabled; Not in lesson/song mode.	Ensure light-up key function is enabled; Select a lesson or built-in song.
No display on TV	Incorrect TV input; Loose cable connection.	Select correct video input on TV; Check video cable connection.
Microphone not working	Microphone not connected; MIC VOLUME too low.	Ensure microphone is fully inserted; Increase MIC VOLUME.

If the problem persists after trying these solutions, please contact CASIO customer support.

6. SPECIFICATIONS

Feature	Description
Model Number	LK-201TV
Keys	61 standard keys, 5 octaves

Feature	Description
Light-up Keys	Maximum 10 keys simultaneous illumination
Touch Response	Yes (On/Off selectable)
Number of Tones	264 tones (128 panel tones + 128 GM + 8 drum), Layer/Split function
Number of Rhythms	100 types
Built-in Songs	100 songs
Display	Large LCD display (shows tone name, chord name, fingering)
Connectivity	USB, MIC IN, VIDEO OUT
Dimensions (approx.)	97 x 37 x 15 cm
Weight (approx.)	5.5 kg



7. WARRANTY AND SUPPORT

For warranty information, please refer to the warranty card included with your product or visit the official CASIO website. Keep your purchase receipt as proof of purchase.

For technical support, service, or inquiries, please contact CASIO customer service through their official channels. Contact information can typically be found on the CASIO website or in the product packaging.

© 2023 CASIO Computer Co., Ltd. All rights reserved.

Related Documents - LK-201TV

	<p>Casio LK-S250 Casiotone User's Guide</p> <p>A comprehensive user's guide for the Casio LK-S250 Casiotone keyboard, covering setup, basic operations, sound control, rhythm backing, and connectivity.</p>
	<p>CASIO LK-S250 Casiotone Quick Start Guide</p> <p>Quick start guide for the CASIO LK-S250 Casiotone portable keyboard, covering setup, basic operation, song playback, rhythm playing, and DJ mode. Learn how to connect power, use controls, and explore musical features.</p>

	<p>Casio LAW-21 Модуль 2789: Руководство пользователя и характеристики</p> <p>Полное руководство пользователя для часов Casio LAW-21 (Модуль 2789). Содержит инструкции по эксплуатации, уходу, описания режимов работы (текущее время, мировое время, таймер, секундомер, будильник) и технические характеристики.</p>
	<p>Casio LK-280 Digital Keyboard User's Guide: Learn to Play</p> <p>Explore the features and functions of the Casio LK-280 digital keyboard with this comprehensive user's guide. Learn about setup, playing techniques, built-in songs, and advanced features for an enhanced musical experience.</p>
	<p>Руководство пользователя Casio BG-1220, MSG-172, MTG-910 Модуль 3006</p> <p>Подробное руководство пользователя для часов Casio BG-1220, MSG-172, MTG-910 с модулем 3006, охватывающее водостойкость, уход, мировое время, секундомер, таймер, будильник и технические характеристики.</p>
	<p>CASIO LK-S450 Casiotone Digital Keyboard User's Guide</p> <p>Comprehensive user's guide for the CASIO LK-S450 Casiotone digital keyboard, covering setup, operations, features, and troubleshooting for musicians of all levels.</p>