Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

SentrySafe X055

SentrySafe X055 Digital Keypad Safe Instruction Manual

Model: X055

1. Product Overview

The SentrySafe X055 is a digital keypad safe designed for securing valuables such as money, jewelry, electronics, and documents. It features solid steel construction, two live-locking bolts, and a programmable digital lock with override keys for reliable access.



Image: SentrySafe X055 Digital Keypad Safe with door open, showing interior.



Image: SentrySafe X055 safe with door open, showing the two live-locking bolts.



Image: SentrySafe X055 safe with door open, highlighting the carpeted interior.

2. Setup Instructions

2.1 Battery Installation

The safe requires four (4) high-quality, name-brand alkaline AA batteries with an expiration date 8-10 years from the current year for optimal performance. Generic and rechargeable batteries are not recommended.

1. Locate the battery compartment on the inside of the safe door.
2. Open the battery compartment cover.
3. Insert four AA batteries, ensuring correct polarity (+/-).
4. Replace the battery compartment cover.

2.2 Setting Your Personal Combination

Your safe comes with a factory-set code. It is crucial to change this to a personal combination immediately after battery

installation.

1. With the safe door open, press the red program button located on the inside of the door near the hinge. The yellow light on the keypad will illuminate.
2. Enter your new 3-8 digit personal combination on the keypad.
3. Press the '#' button to confirm. The green light will flash, indicating successful programming.
4. Test your new combination with the door open before closing it.



Image: Close-up of the SentrySafe X055 digital keypad.

2.3 Securing the Safe (Bolt-Down Kit)

For enhanced security, the safe includes a bolt-down kit to anchor it to a floor or shelf.

1. Choose a suitable location for your safe.
2. Mark the drilling points through the pre-drilled holes inside the safe.
3. Drill pilot holes according to the instructions provided with the bolt-down kit.
4. Secure the safe using the provided hardware.



Image: SentrySafe X055 safe with bolt-down kit.

3. Operating Instructions

3.1 Opening the Safe with Your Combination

1. Enter your personal 3-8 digit combination.
2. Press the '#' button. The green light will illuminate.
3. Within 5 seconds, turn the handle clockwise to open the safe door.

3.2 Using the Override Keys

Two override keys are provided for emergency access or if the digital keypad is not functioning.

1. Locate the keyhole cover on the keypad panel.
2. Remove the keyhole cover.

3. Insert one of the override keys into the keyhole and turn it clockwise.
4. Simultaneously turn the handle clockwise to open the safe door.

3.3 Closing and Locking the Safe

1. Close the safe door firmly.
2. Turn the handle counter-clockwise until the door is securely latched.

Your browser does not support the video tag.

Video: Official SentrySafe Security Safe overview, demonstrating key features and operation.

4. Maintenance

4.1 Battery Replacement

When the batteries are low, the red light on the keypad may flash or the safe may not open. Replace all four AA batteries promptly.

1. Open the safe using either your combination or the override key.
2. Follow the battery installation steps in Section 2.1.
3. Always replace all four batteries at once with new, high-quality alkaline batteries.

4.2 General Care

To maintain your safe's appearance and functionality:

- Wipe the exterior with a soft, damp cloth. Avoid abrasive cleaners.
- Keep the keypad clean and free of debris.
- Do not store override keys inside the safe. Keep them in a secure, separate location.

5. Troubleshooting

5.1 Safe Does Not Open with Combination

- **Check Batteries:** Ensure batteries are new, high-quality alkaline, and correctly installed. Low batteries are a common cause.
- **Incorrect Combination:** Verify you are entering the correct personal combination. If forgotten, use the override keys.
- **Keypad Error:** If the red light flashes rapidly after entering a code, it indicates an incorrect entry. Wait 20 seconds and try again.

5.2 Override Key Does Not Work

- **Correct Key:** Ensure you are using the correct override key for your safe.
- **Full Insertion:** Make sure the key is fully inserted into the keyhole before turning.

5.3 Door Does Not Close Properly

- **Obstructions:** Check for any items blocking the door or the locking bolts.
- **Handle Alignment:** Ensure the handle is in the correct position before closing the door.

6. Specifications



Image: SentrySafe X055 Digital Keypad Safe Dimensions.

Feature	Detail
Brand	SentrySafe
Model Number	X055
Product Dimensions	9.7"D x 13.8"W x 8.7"H
Interior Dimensions (Chamber)	8.5"H x 13.6"W x 8.7"D
Lock Type	Electronic Combination Lock
Color	Black
Capacity	0.6 cubic feet (0.58 cubic feet)
Material	Alloy Steel

Feature	Detail
Item Weight	10 pounds
Mounting Type	Floor Mount
Special Feature	Removable
Included Components	SentrySafe X055 Security Safe
Water Resistance Level	Water Resistant
Control Type	Touchpad Control

7. Warranty and Support

This product is covered by the Manufacturer's Limited Warranty. For detailed warranty information and customer support, please refer to the official SentrySafe resources.

- **User Manual (PDF):** For a comprehensive guide, download the official PDF manual:Download PDF Manual
- **Manufacturer's Website:** Visit the SentrySafe store for additional product information and support:SentrySafe Store

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B000Z8P5Z2

More documents and user manuals: **https://manuals.plus/**