



[Manuals.plus](#) /

› [Powell](#) /

› Powell Rustica Full Over Twin All in One Bunk Bed with Chair Instruction Manual

Powell 836-944

Powell Rustica Full Over Twin All in One Bunk Bed with Chair Instruction Manual

Model: 836-944

INTRODUCTION

This manual provides detailed instructions for the assembly, operation, and maintenance of your Powell Rustica Full Over Twin All in One Bunk Bed with Chair, Model 836-944. Please read all instructions carefully before beginning assembly and retain this manual for future reference.

The Powell Rustica bunk bed system offers a comprehensive youth bedroom solution, combining a full-size upper bunk, a twin-size trundle bed, a desk unit, and integrated storage. This unit is designed for efficient space utilization and functionality.

SAFETY INFORMATION

WARNING: Failure to follow these warnings and instructions could result in serious injury or death.

- Always use the recommended mattress size for both the upper bunk and trundle bed.
- Ensure all hardware is securely tightened before use and periodically check for loose connections.
- The upper bunk is not suitable for children under six years of age.
- Prohibit more than one person on the upper bunk.
- Prohibit horseplay on or under the bed.
- Always use the ladder for entering and leaving the upper bunk.
- Do not attach or hang items to any part of the bunk bed that are not designed for use with the bed; for example, but not limited to, hooks, belts, and jump ropes.
- Keep these instructions for future reference.

SETUP AND ASSEMBLY

Some assembly is required for this product. It is recommended that two adults assemble the unit. Clear a large area for assembly and lay out all components and hardware before starting.

Required Tools (Not Included):

- Phillips Head Screwdriver
- Hammer
- Allen Wrench (often included with hardware, but a set is useful)

Assembly Steps:

1. **Unpack Components:** Carefully remove all parts from the packaging. Verify that all components and hardware listed in the packing list are present.
2. **Assemble Base Structure:** Begin by assembling the main frame of the bunk bed, including the vertical supports and lower bed frame. Ensure all connections are finger-tightened initially.
3. **Install Desk Unit and Storage:** Attach the desk unit, including the pull-out keyboard tray and shelves, to the main frame. Secure the storage drawers into their designated compartments.
4. **Assemble Upper Bunk:** Construct the upper bunk frame. With assistance, carefully lift and secure the upper bunk onto the main support structure. Ensure all safety rails are properly installed and secured.
5. **Assemble Trundle Bed:** Assemble the trundle bed frame and install the wheels. Slide the trundle bed into its position under the main structure.
6. **Assemble Chair:** Follow the separate instructions for assembling the accompanying desk chair.
7. **Final Tightening:** Once all components are in place, systematically tighten all hardware connections using the appropriate tools. Do not overtighten.
8. **Safety Check:** Before first use, thoroughly inspect the entire bunk bed system to ensure all parts are correctly assembled and securely fastened.



Image 1: Fully assembled Powell Rustica Full Over Twin All in One Bunk Bed with Chair, showcasing the upper bunk, desk area, storage drawers, wardrobe, and pull-out trundle bed.



Image 2: Close-up view of the integrated desk unit with a pull-out keyboard tray, shelving, and multiple storage drawers, part of the Powell Rustica Bunk Bed system.

OPERATING INSTRUCTIONS

Using the Upper Bunk:

- Access the upper bunk using the integrated ladder only.
- Ensure the mattress fits snugly within the bed frame and does not exceed the maximum recommended thickness (refer to safety labels on the bed).

Using the Trundle Bed:

- To deploy the trundle bed, gently pull it out from under the main bed structure using the handles or designated pull points.
- To store, push the trundle bed back into its compartment until it is fully recessed.

Using the Desk Unit:

- The desk features a pull-out keyboard tray for ergonomic computer use.
- Utilize the integrated shelves for books, stationery, or electronic devices.

Using Storage Drawers and Wardrobe:

- The unit includes six large storage drawers for clothing or personal items.
- The built-in wardrobe provides hanging storage space. Open the doors carefully.

MAINTENANCE

- **Cleaning:** Wipe surfaces with a soft, damp cloth. Avoid harsh chemicals or abrasive cleaners that may damage the finish.

- **Hardware Inspection:** Periodically (every 3-6 months) check all bolts, screws, and fasteners to ensure they are tight. Retighten as necessary to maintain structural integrity and safety.
- **Moving the Unit:** If moving the bunk bed, disassemble it partially or entirely to prevent damage to the structure and connections. Do not drag the assembled unit.
- **Wood Care:** Protect the wood finish from direct sunlight and extreme temperature changes to prevent warping or fading.

TROUBLESHOOTING

Squeaking Noises:

- Check all hardware connections. Loose bolts are a common cause of squeaking. Tighten any loose fasteners.
- Ensure the bed is on a level surface. Uneven floors can cause stress on the frame, leading to noise.

Drawers Sticking or Not Sliding Smoothly:

- Inspect drawer glides for obstructions or damage.
- Ensure drawers are not overloaded.
- Apply a small amount of silicone lubricant to the drawer glides if they are wooden.

Bed Feels Unstable:

- Immediately cease use.
- Re-check all assembly steps and ensure all hardware is fully tightened.
- Verify that the bed is placed on a flat, stable surface.

SPECIFICATIONS

Model Number:	836-944
Item Weight:	479 pounds
Product Dimensions (Overall):	78 x 16.75 x 73.25 inches (Length x Depth x Height)
Assembled Height:	73 inches
Assembled Width:	78 inches
Upper Bunk Dimensions:	78 x 56.75 inches (Full Size)
Trundle Bed Dimensions:	78 x 45.75 inches (Twin Size)
Desk Chair Dimensions:	17.75 x 19.375 x 40.375 inches (Width x Depth x Height)
Desk Chair Seat Height:	17.375 inches

WARRANTY AND SUPPORT

For warranty information or assistance with parts and assembly, please contact Powell customer support. Refer to your purchase documentation or the manufacturer's website for specific contact details and warranty terms. When contacting support, please have your model number (836-944) and purchase date available.

