

[Manuals.plus](#) /

› [Minka Lavery](#) /

› Minka Lavery 6461-273 One Light Bath Fixture User Manual

Minka Lavery 6461-273

Minka Lavery 6461-273 One Light Bath Fixture User Manual

Model: 6461-273

[Introduction](#) [Safety Information](#) [What's Included](#) [Setup & Installation](#) [Operating](#)
[Instructions](#) [Maintenance](#) [Troubleshooting](#) [Specifications](#) [Warranty & Support](#)

1. INTRODUCTION

This manual provides essential instructions for the safe installation, operation, and maintenance of your Minka Lavery 6461-273 One Light Bath Fixture. Please read this manual thoroughly before installation and retain it for future reference. This fixture is designed for indoor use in bathrooms and features a transitional style with an Aged Patina Iron finish and a white glass shade.

2. IMPORTANT SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.

- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC).
- Consult a qualified electrician if you are unfamiliar with electrical wiring.
- This fixture is designed for 120V AC power supply.
- Do not install this fixture in areas where it may be directly exposed to water spray or submersion. It is **NOT water resistant**.
- Ensure the mounting surface can support the weight of the fixture.
- Use only the specified bulb type and wattage to avoid overheating.
- Do not attempt to modify the fixture.
- Keep flammable materials away from the light source.

3. WHAT'S INCLUDED

Carefully unpack your fixture and check that all parts are present. If any parts are missing or damaged, do not attempt to assemble or install the fixture. Contact customer support for assistance.

- Minka Lavery 6461-273 Fixture Body (Aged Patina Iron)
- White Glass Shade

- Mounting Hardware (screws, wire nuts, mounting plate)
- One (1) T4 Halogen Bulb (75W, E11 base)
- Instruction Manual



Image 1: Front view of the Minka Lavery 6461-273 One Light Bath Fixture, showcasing the Aged Patina Iron finish and white glass shade.

4. SETUP & INSTALLATION

This fixture is designed for semi-flush mount installation. Professional installation is recommended.

4.1 Tools Required (Not Included)

- Phillips Head Screwdriver
- Flathead Screwdriver
- Wire Strippers
- Electrical Tape
- Safety Glasses
- Ladder (if necessary)

4.2 Installation Steps

1. **Turn Off Power:** Locate the circuit breaker or fuse box and turn off the power to the junction box where you will be

installing the fixture. Verify power is off using a voltage tester.

2. **Prepare Mounting Plate:** Attach the mounting plate to the junction box using the provided screws. Ensure it is securely fastened.
3. **Electrical Connections:**
 - Connect the **black** wire from the fixture to the **black** (hot) wire from the junction box.
 - Connect the **white** wire from the fixture to the **white** (neutral) wire from the junction box.
 - Connect the **green** or **bare copper** ground wire from the fixture to the ground wire from the junction box.
 - Secure all connections with wire nuts and wrap with electrical tape for added safety.
4. **Mount Fixture Body:** Carefully align the fixture body with the mounting plate and secure it using the provided screws.
5. **Install Bulb:** Insert the provided T4 Halogen bulb into the E11 base socket. Handle the bulb with a clean cloth to avoid oil transfer from fingers, which can shorten bulb life.
6. **Attach Glass Shade:** Secure the white glass shade to the fixture body according to the design.
7. **Restore Power:** Turn the power back on at the circuit breaker or fuse box.
8. **Test Fixture:** Turn on the light switch to ensure the fixture is working correctly.



Image 2: Angled view of the Minka Lavery 6461-273 fixture, showing the structural details and the glass shade.

5. OPERATING INSTRUCTIONS

The Minka Lavery 6461-273 Bath Fixture operates via a standard wall switch (toggle type, as per specifications). Once installed and power is restored, simply use the wall switch to turn the light on or off.

- **Turning On/Off:** Flip the connected wall switch to the "ON" position to illuminate the fixture, and to the "OFF" position to turn it off.
- **Light Output:** The fixture provides 1100 lumens of white light from its 75-watt T4 Halogen bulb.

6. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your light fixture.

6.1 Cleaning

- **Always turn off power** at the circuit breaker before cleaning.
- Wipe the fixture with a soft, dry cloth.
- Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
- For the glass shade, a mild glass cleaner applied to a cloth (not directly to the fixture) can be used.

6.2 Bulb Replacement

- **Turn off power** at the circuit breaker and allow the bulb to cool completely before attempting replacement.
- Carefully remove the glass shade.
- Unscrew the old T4 Halogen bulb from the E11 base socket.
- Insert a new T4 Halogen bulb (max 75W, E11 base). Avoid touching the new bulb with bare hands; use a clean cloth or gloves.
- Reattach the glass shade.
- Restore power and test the fixture.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	Power is off at the circuit breaker. Loose wire connections. Defective bulb. Faulty wall switch.	Check circuit breaker/fuse. Verify all wire connections are secure (with power off). Replace bulb. Test wall switch or consult an electrician.
Light flickers.	Loose bulb. Incorrect bulb type/wattage. Loose wire connections.	Tighten bulb. Ensure correct bulb (T4 Halogen, max 75W, E11 base). Check wire connections (with power off).
Bulb burns out quickly.	Touching bulb with bare hands during installation. Over-wattage bulb. Voltage fluctuations.	Always use a clean cloth when handling halogen bulbs. Use only 75W T4 Halogen bulb. Consult an electrician to check household voltage.

8. SPECIFICATIONS

Feature	Detail
Model Number	6461-273
Brand	Minka Lavery
Dimensions (L x W x H)	5.5" x 5.5" x 5.5"
Weight	2.49 Pounds
Finish	Aged Patina Iron
Shade Material	Glass (White)
Input Voltage	120 Volts
Number of Lights	1
Bulb Type	T4 Halogen (Included)
Bulb Base	E11
Max Wattage	75 Watts
Brightness	1100 Lumens
Installation Type	Semi Flush Mount
Indoor/Outdoor Use	Indoor Only
Water Resistance	Not Water Resistant
Required Assembly	No

9. WARRANTY & SUPPORT

9.1 Limited Warranty

Minka Lavery provides a **Limited 1-Year Warranty** on this product from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or normal wear and tear. For warranty claims, please retain your proof of purchase.

9.2 Customer Support

If you have any questions regarding the installation, operation, or maintenance of your Minka Lavery 6461-273 fixture, or if you require assistance with warranty claims, please contact Minka Lavery customer support. Refer to the official Minka Lavery website or product packaging for the most current contact information. For more information, visit the [Minka Lavery Store on Amazon](#).

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question

and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question