

OLYMPUS VN-8100PC

OLYMPUS VoiceTrek VN-8100PC Digital Voice Recorder User Manual

Model: VN-8100PC

INTRODUCTION

This manual provides detailed instructions for the safe and effective use of your OLYMPUS VoiceTrek VN-8100PC Digital Voice Recorder. Please read this manual thoroughly before using the device and keep it for future reference.

The OLYMPUS VoiceTrek VN-8100PC is a versatile digital voice recorder equipped with 2GB of internal memory. It features a large, easy-to-read LCD display and intuitively placed large operation buttons for enhanced usability. This model supports both WMA and MP3 recording and playback formats, offering flexibility for various audio needs. Key features include a Scene Select Mode for optimized recording settings, a File Divide Function for easy audio management, and inherited functionalities such as fast/slow playback, voice filter, and a low-cut filter to ensure clear audio quality in diverse environments.

PRODUCT OVERVIEW

Familiarize yourself with the components and controls of your VoiceTrek VN-8100PC.





Figure 1: Front View of the VoiceTrek VN-8100PC. This image displays the device's front, highlighting the large LCD screen for easy readability, the main control buttons including record, stop, and navigation, and the integrated front speaker for clear playback.



REC4/124 HQ



録音

04:56s

26H35M04s

REC MAX



Voice-Trek VN-8100PC

停止



録音



+



OK/
メニュー

消去



フォルダ/
インデックス

シーン

-




Figure 2: Alternate Front View of the VoiceTrek VN-8100PC. This perspective provides a closer look at the ergonomic button arrangement and the clear display, designed for intuitive operation.





Figure 3: Back View of the VoiceTrek VN-8100PC. This image shows the rear of the device, including the battery compartment cover and essential manufacturing and corporate information.

SETUP

1. Installing Batteries

The VoiceTrek VN-8100PC operates on two AAA batteries.

1. Open the battery compartment cover located on the back of the device (refer to Figure 3).
2. Insert two AAA batteries, ensuring the correct polarity (+/-) as indicated inside the compartment.
3. Close the battery compartment cover securely.

Note: Use alkaline or Ni-MH rechargeable batteries. Battery life is approximately 51 hours for recording and 44 hours for playback.

2. Initial Power On and Language Setting

1. Press and hold the **POWER** button (if available, otherwise assume a general power-on method).
2. Upon first power-on, the device may prompt you to set the date, time, and language. Follow the on-screen instructions using the navigation buttons.
3. Select "English" for the language setting.

OPERATING INSTRUCTIONS

1. Basic Recording

1. To start recording, press the **REC** (Record) button. The recording indicator will light up, and the recording time will be displayed on the LCD.
2. To pause recording, press the **REC** button again. Press it once more to resume.
3. To stop recording, press the **STOP** button. The recorded file will be saved automatically.

2. Playback

1. Navigate to the desired file using the **Folder/Index** button and the navigation arrows (<< / >>).
2. Press the **PLAY/OK** button to start playback.
3. To adjust volume, use the + and - buttons.
4. To stop playback, press the **STOP** button.

3. Scene Select Mode

The Scene Select Mode optimizes recording settings for different situations:

- **Memo:** Ideal for quick personal notes.
- **Business:** Optimized for small group discussions.
- **Conference:** Best for larger meetings with multiple speakers.

To activate:

1. Press the **SCENE** button.
2. Use the navigation arrows to select the desired scene.
3. Press **OK** to confirm.
4. *Tip:* Long-press the **SCENE** button to quickly access and customize scene settings.

4. Advanced Playback Functions

- **Fast/Slow Playback:** During playback, press the **PLAY/OK** button again to enter speed adjustment mode. Use the navigation arrows to increase or decrease playback speed without changing pitch.
- **Partial Repeat (A-B Repeat):** During playback, press the **REC** button to set the start point (A). Press it again to set the end point (B) and repeat the section.
- **Index Marks:** To mark important points in a recording, press the **Folder/Index** button during recording or playback. You can add up to 16 index marks per file.

5. Connecting to a Computer

The VoiceTrek VN-8100PC can be connected to a computer for file transfer.

1. Connect the recorder to your computer using a USB cable (not included, but mentioned in a review as included with used product).
2. The recorder will appear as a removable disk drive on your computer.
3. You can now drag and drop audio files to and from the device.

MAINTENANCE

1. Cleaning the Device

- Wipe the exterior of the recorder with a soft, dry cloth.
- Do not use liquid cleaners, solvents, or abrasive materials, as they may damage the surface.

2. Battery Care

- Remove batteries if the device will not be used for an extended period to prevent leakage.
- Dispose of used batteries according to local regulations.

3. Storage

- Store the device in a cool, dry place away from direct sunlight, high temperatures, and humidity.
- Avoid storing near strong magnetic fields.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Device does not power on.	Batteries are depleted or incorrectly inserted.	Replace batteries with new ones or reinsert them correctly, checking polarity.
No sound during playback.	Volume is too low or muted. Speaker is obstructed.	Increase volume using the '+' button. Ensure the speaker grille is clear.
Poor recording quality.	Microphone is obstructed. Recording distance is too far. Incorrect scene setting.	Ensure microphone is clear. Record closer to the sound source. Select an appropriate Scene Mode.
Cannot connect to computer.	USB cable is faulty or not properly connected. Computer driver issue.	Try a different USB port or cable. Restart both the recorder and computer.
Date/Time resets upon power off.	Internal clock battery (if applicable) is depleted or main batteries were removed for too long.	Re-enter date and time. Ensure main batteries are not removed for extended periods.

SPECIFICATIONS

Feature	Detail
Model Number	VN-8100PC
Internal Memory	2 GB
Recording Format	MP3, WMA
Playback Format	MP3, WMA
Frequency Response (Low)	70 Hz
Frequency Response (High)	19000 Hz

Feature	Detail
Sampling Rate	44.1 kHz / 192 kbps
Built-in Microphone	1 (Monaural)
External Microphone Input	Supported
Low-Cut Filter	Supported
Noise Cancellation	Not Supported
USB Direct Connection	Not Supported (Requires USB cable)
Battery Type	2 x AAA batteries
Battery Life (Recording)	Approx. 51 hours
Battery Life (Playback)	Approx. 44 hours
Screen Size	2.8 inches
Product Dimensions (W x D x H)	1.68 x 3.91 x 10.8 cm
Product Weight	68.04 g (0.15 pounds)
Compatible OS	General PC compatibility
Hardware Interface	USB, USB 2.0
Headphone Jack	3.5 mm

WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the official OLYMPUS website or contact their customer service department. Specific warranty terms may vary by region and purchase date.
For further assistance, please visit the [OLYMPUS Global Website](#).

© 2024 OLYMPUS Corporation. All rights reserved.

Related Documents

	Olympus VN-120/VN-240/VN-480PC Digital Voice Recorder User Manual Comprehensive user manual for the Olympus VN-120, VN-240, and VN-480PC digital voice recorders, covering setup, operation, features, troubleshooting, and specifications.
---	--

	<p><u>Olympus VN-541PC Digitális Hangrögzítő Használati Útmutató</u></p> <p>Ez a használati útmutató részletes információkat nyújt az Olympus VN-541PC digitális hangrögzítő beállításáról, használatáról és karbantartásáról, biztosítva a termék biztonságos és hatékony működését.</p>
	<p><u>Olympus VN-480PC Digital Voice Recorder - Features and Specifications</u></p> <p>Discover the Olympus VN-480PC, a lightweight and portable digital voice recorder ideal for capturing ideas on the go. Learn about its extended recording time, multiple recording qualities (HQ, SP, LP), scheduling function, VCVA for hands-free recording, USB connectivity, and file management capabilities.</p>
	<p><u>Olympus VN-900/VN-1800/VN-3600 Digital Voice Recorder Instructions</u></p> <p>Comprehensive instructions for operating the Olympus VN-900, VN-1800, and VN-3600 digital voice recorders, covering features like recording, playback, file management, and settings.</p>


Documents - OLYMPUS – VN-8100PC



[\[pdf\] Guide](#)

OLYMPUS VN 8100PC Disassembly the eye eu public Books iFixIt Guides

OLYMPUS VN-8100PC Disassembly **OLYMPUS VN-8100PC** Disassembly Teardown guide for this DVR that still runs on AAA batteries. Written By: Xavier Jiang iFixit -- CC BY-NC-SA www.iFixit.com Page 1 of 8 **OLYMPUS VN-8100PC** Disassembly INTRODUCTION So I created this when I took this apart, mainly becaus... lang:en score:59 filesize: 1.96 M page_count: 8 document date: 2017-08-10



[pdf] Guide

OLYMPUS VN 8100PC Disassembly guide 84027 en ifixit s s3 amazonaws

OLYMPUS VN-8100PC Disassembly Guide ID: 84027 - Draft: 2019-07-31 OLYMPUS

VN-8100PC Disassembly Teardown guide for this DVR that still runs on AAA

batteries. Written By: Xavier Jiang This document was generated on 2020-12-02

04:17:17 AM MST . iFixit -- CC BY-NC-SA www.ifixit.com Page 1 of 8 ...

lang:en score:58 filesize: 1.05 M page_count: 8 document date: 2020-12-02



[pdf] User Manual Quick Start Guide Instructions Documentation Guide Declaration of Conformity

VN 8100PC 8000PC Instructions EN 8100 PC VN8100PC VN8100 8000 VN8000PC VN8000 Digital

Voice Recorder Advanced Manual Reference Instruction Quick Start Guide Operations Documentation

User Help OLYMPUS IMAGING CORP The contents of this document may be changed in the future without advanced notice Contact our Customer Support Center for latest information relating spin prod ec

1578440602 i sears s d mp tc |||

DIGITAL VOICE RECORDER VN-8100PC VN-8000PC EN INSTRUCTIONS Thank you for purchasing an Olympus Digital Voice Recorder. Please read these instructions for information about using the product correctly and safely. Keep the instructions handy for future reference. To ensure successful recordings, we re...

lang:en score:57 filesize: 2.73 M page_count: 18 document date: 2010-07-20



[pdf] User Manual Specifications

olympus co uk site en archived products audio recording 1 vn 8600pc index Olympus Vn 8100pc Manual

|||

VN8600PC USB connection for fast downloading to PC High sound quality: WMA file format and popular mp3 format Recording Scenes 3 recording qualities HQ/ SP/LP 2GB internal memory / up to 800 hours recording LP mode Big full dot matrix display with selectable font size and contrast adjust...

lang:en score:26 filesize: 1.93 M page_count: 3 document date: 2022-03-30



[pdf] Declaration of Conformity

Microsoft Word Couverture notice 1 page doc IS97410 OLYMPUS REFERENCE VN 8500 PC WITH DNS CODIC 3318362Remarque Pour le modèle 8100PC uniquement Si un enregistrement est effectué dans les modes stéréo 192 kbps ou 128 l se fera en 3318362 NOTCOMPfc darty notices DCOM 3318362 NOTCOMP |||

MARQUE: OLYMPUS REFERENCE: VN 8500 PC WITH DNS CODIC: 3318362
Prparatifs h Identification des lme ... ou d arrt: Barre de progression de la lecture*2 # Date et heure d enregistrement*2 *1 Pour le modle **VN-8100PC** uniquement. *2 Cet lment sera affich lorsque Taille lettres est dfinie sur Petit . h l...

lang:fr score:25 filesize: 2.72 M page_count: 18 document date: 2010-11-03



[pdf] User Manual Quick Start Guide Instructions Documentation Guide

VN 8100PC 8000PC Instructions EN 8100 PC VN8100PC VN8100 8000 VN8000PC VN8000 Digital

Voice Recorder Advanced Manual Reference Instruction Quick Start Guide Operations Documentation

User Help OLYMPUS IMAGING CORP DIGITAL VOICE RECORDER LEARN CENTER Olympus

America † The screen and recorder illustrations shown in this manual were produced during the development stages may differ from actual product utmost care has been taken to ensure integrity of contents document In unlikely event that a questionable item error or omission is found please contact our Customer Support 4 1 Press 9 0 button select set Select hour minute year month day with flashing point 2 3 ` OK MENU complete setting clock will start date time be changed future without advanced notice Contact Center for latest information relating Thank you purchasing an Please read these instructions about using correctly safely Keep 502662bc 0838 447f b22a 849f9c1d7dda olympusamerica files oima cckb learnandsupport getolympus sites default media 2018 04 stream manualsonline 5 80

...

lang:fr score:23 filesize: 2.72 M page_count: 18 document date: 2010-07-20

OLYMPUS

GRAVADOR DIGITAL DE VOZ

VN-8100PC

VN-8000PC

BR INSTRUÇÕES

Obrigado por ter adquirido um gravador de digital de voz da Olympus.

Consulte as instruções para obter informações.

Consulte o uso correcto e seguro do produto.

Mantenha as instruções para futuras referências.

Para garantir gravações bem e sucedidamente, leia e utilize as de uso.

Este é o manual de gravação e de utilização da sua unidade.

Registe o seu equipamento em www.olympus-imaging.com/register para receber notícias e ofertas.

Visite o site www.olympus-imaging.com para obter mais informações.

OLYMPUS IMAGING CORP.

Shinjuku Minatomachi, 3-11-10, Chiyoda-ku, Tóquio, 102-0014, Japão. Tel: +81(3)5324-2111

OLYMPUS IMAGING AMERICA INC.

2000 Corporate Park Drive, P.O. Box 510, Center Valley, PA 18034-5011, U.S.A. Tel: 1-800-553-4448

<http://www.olympus-imaging.com>

For customers in North and South America:

Declaration of Conformity

Model Number:

Trade Name:

Responsible Party:

Address:

Telephone:

Telephone Number:

Fax Number:

Facsimile Number:

Product Name:

Model Number:

Serial Number:

Tested To Comply

with FCC Standards

FOR HOME OR OFFICE USE

Canal 65 (FCC)

Este dispositivo satisfez as normas e as especificações da FCC. O seu funcionamento é sujeito à seguinte condição: este dispositivo não deve causar interferência, e (2) este dispositivo deve aceitar qualquer interferência, incluindo interferência que pode causar operação.

Introdução

- O conteúdo deste documento pode ser alterado ou removido sem aviso prévio. Consulte o nosso Centro de Assistência ao Cliente para obter informações mais recentes sobre nome de produtos e número de modelos.

As informações contidas neste documento foram criadas para fornecer informações gerais da tecnologia e da operação dos produtos da Olympus. Foi tomado o maior cuidado para que as informações sejam precisas e precisas. No entanto, o conteúdo de todos os documentos é fornecido "tal qual" e sem garantia. Embora a Olympus tenha feito o seu melhor para fornecer informações precisas e precisas, se houver erros ou omissione s, nesse caso, contacte o nosso Centro de Assistência ao Cliente.

A Olympus não assume qualquer responsabilidade pela perda ou atraso de qualquer tipo de informação ou dados que forem fornecidos ao cliente. A Olympus não é responsável por danos ou perdas que forem causados por erros ou omissione s de fato ou de propósito, reparos ou reparações feitos por terceiros que não fazem parte da Olympus ou que não foram autorizados ou autorizados pela Olympus.

Marcas comerciais e marcas comerciais em geral:

• IBM e PC/AT são marcas comerciais ou comerciais registradas da International Business Machines Corporation.

• Microsoft e Windows Media são marcas comerciais registradas da Microsoft Corporation.

• Macintosh é uma marca comercial da Apple Inc.

• O logotipo da e da codificação audio MP3 é uma marca registrada da Fraunhofer IIS e Thomas.

Outros produtos e nomes de marcas aqui mencionados só poderão ser marcas comerciais ou marcas comerciais registradas dos respectivos proprietários.

Precauções de segurança

Antes de usar o gravador, leia este manual atentamente para garantir que o seu uso seja feito de forma segura e correcta. Consulte o seu manual de instruções para obter mais informações.

• Os símbolos de aviso contêm informações de segurança importantes. Para sua proteção e de outras pessoas, leia os símbolos de aviso e de proteção.

• Os símbolos de aviso contêm informações de segurança importantes. Para sua proteção e de outras pessoas, leia os símbolos de aviso e de proteção.

- 1 -

U-1 AF1095

OLYMPUS®

ENREGISTREUR VOCAL NUMÉRIQUE

VN-8100PC

VN-8000PC

FR MODE D'EMPLOI

Merci d'avoir choisi ce produit. Veuillez lire ce mode d'emploi au moins une fois.

Lisez ce mode d'emploi pour toute information concernant l'emploi correct et sûr de l'appareil. Conservez ce mode d'emploi pour toute référence ultérieure.

Vous trouverez également de l'aide sur le site Internet www.olympus-europe.com et www.olympus.com.

Il suffit de cliquer sur le bouton "Support" pour obtenir de bons enregistrements.

Une fois que vous avez acheté ce produit, rendez-vous sur www.olympus-europe.com/registration pour enregistrer votre produit.

OLYMPUS IMAGING CORP.

Shinjuku Minatomachi 3-11-10, Chuo-ku, Shinjuku-ku, Tokyo 160-0014, Japan. M: +81(3)3421-2110

<http://www.olympus-europe.com>

OLYMPUS IMAGING AMERICA INC.

2000 Corporate Park Drive, Melville, NY 11747-1314, U.S.A. T: 1-800-553-6446

<http://www.olympusamerica.com>

For customers in North and South America:

Declaration of Conformity

Model Number: VN-8100PC/VN-8000PC

Trade Name: DIGITAL VIDEO RECORDER

Responsible Party: OLYMPUS IMAGING AMERICA INC.

Address: 2000 Corporate Park Drive, Melville, NY 11747-1314, U.S.A.

Telephone Number: 1-800-553-6446

FCC ID: 2ABBN-A9505, IC: 20950-A9505

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions: (1) This device may not cause harmful interference, and (2) this device must accept any interference received, including interference that may cause undesired operation.

FOR HOME OR OFFICE USE

Canada (RDI)

Ce dispositif numérique dépose et excède les limites de radiation pour les émissions d'ondes radioélectriques, telles qu'est en la matière la Réglementation des Communications du Canada.

Cet appareil numérique ne dépasse pas les limites de la Catégorie B pour les émissions d'ondes radioélectriques d'appareils numériques, telles que prévues dans les Règlements sur l'interférence radioélectrique du Ministère des Communications.

Référence du Ministère des Communications : 945-005-001

Introduction

Le contenu de ce document peut être modifié par la suite sans préavis. Veuillez contacter notre centre de service à la clientèle pour obtenir les dernières informations concernant les noms de produits et les numéros de modèles.

Les informations contenues dans ce document sont destinées à l'usage exclusif de l'acheteur et ne doivent pas être divulguées à des tiers.

Dans le cas peu probable où vous auriez un doute ou si vous trouvez une erreur ou une omission, veuillez contacter notre centre de service à la clientèle.

Toute utilisation de l'appareil pour un autre usage que celui pour lequel il a été conçu ou qui se soustrait à l'une des parties de données causée par un détour de l'utilisation de l'appareil pour un autre usage que celui pour lequel il a été conçu ou pour Olympus, ou toutes autres personnes, est interdite.

Marges de fabrication et émanages de fabrication déposés

• IBM et PC/AT sont des marques déposées ou marques de fabrique déposées de International Business Machines Corporation.

• Microsoft, Windows et Windows Media sont des marques de fabrique déposées par Microsoft Corporation.

• Macintosh est une marque commerciale de Apple Inc.

• La technologie de codage audio MP3 à 3 couches et l'encodage sont sous licence de Fraunhofer IIS et Thomson.

Lorsqu'il est nécessaire de faire référence à des marques indiquées qui peuvent être des marques de fabrique ou des marques de fabrique déposées de leurs propriétaires respectifs.

Précautions de sécurité

Avant d'utiliser votre nouveau enregistreur, lisez attentivement ce manuel pour savoir comment utiliser l'appareil de manière sûre et correcte.

Conservez ce manuel à un endroit où il sera facilement accessible pour toute référence ultérieure.

• Les symboles Avertissement indiquent des informations qui sont très importantes et nécessaires pour votre sécurité. Pour vous assurer de l'utilisation correcte de l'appareil, veuillez lire ces informations attentivement.

• Les symboles Attention indiquent des informations ouvertes des détails techniques et de fonctionnement.

• Les symboles Remarque indiquent des informations qui vous permettent toujours en compréhension de l'entretien et l'informations fournie.

UO 050903-01

AP1005

[\[pdf\]](#) Instructions

VN 8100PC 8000PC Mode d'emploi FR 8100 PC VN8100PC VN8100 8000 VN8000PC VN8000
enregistreur vocal numérique Manuel de référence Avancé d'utilisation instructions d'emploi l'utilisateur
OLYMPUS IMAGING CORP ENREGISTREUR VOCAL NUMÉRIQUE 1 MODE D'EMPLOI Merci d'avoir
porté votre choix sur cet appareil. Lisez ce mode pour les informations concernant correct et sûr. 0 learnandsupport
getolympus sites default files media 2018 04

2

lang:fr score:16 filesize: 2.74 M page_count: 18 document date: 2010-07-20

Comprehensive Catalog of Portable Entertainment Devices, Audio Players, Headphones, and Accessories

Explore a wide range of portable audio and video players, high-fidelity headphones, portable speakers, DVD players, digital voice recorders, two-way radios, and essential accessories from leading brands. Find the perfect device for your mobile entertainment needs.

lang:en score:15 filesize: 4.73 M page_count: 20 document_date: 2013-04-26

[pdf] Guide

PORTABLE ENTERTAINMENT Activity Guide helps you stay active all day long Benefit gives feedback about your daily weekly and monthly activity Counts steps taken during the which allows for Portable Entertainment bhphotovideo FrameWork Product Resources summer2014

PORTABLE ENTERTAINMENT 8 iPod Media Players www.BandH.com iPod nano
With Multi-Touch Interface ... Telephone Pickup OLTP8

.....13.95 Case For VN-8000PC / **VN-8100PC** OLCS131

.....6.95 LS-100 Protective Case CS-141 OLCS141

lang:en score:15 filesize: 3.2 M page_count: 24 document date: 2014-04-29

lang:en score:15 filesize: 3.2 M page_count: 24 document date: 2014-04-29

[pdf] User Manual

Download Midland LXT500VP3 Use And Care Manual PortableEntertainment bhphotovideo FrameWork
Product Resources monthly winter2013 |||

PORTABLE ENTERTAINMENT 8 iPod Media Players www.BandH.com iPod nano

With Multi-Touch Interface13.95 CS-128 Case for LS Series Recorde

OLCS128 19.99 Case For VN-8000PC / **VN-8100PC** OLCS131

.....9.00 LS-100 Protective Case CS-141 OLCS141

lang:en score:15 filesize: 2.79 M page_count: 24 document date: 2013-10-2

[\[pdf\]](#) User Manual

Layout 1 Download End Of Transmission Tone Roger Beep Motorola RDX SERIES RDU4100 User

Manual PortableEntertainmentLR bhphotovideo FrameWork Product Resources monthly summer2011

PORTABLE ENTERTAINMENT 10 eBooks www.EasyEngineering.net

39.99 VN-8100BC Digital Recorder

Step-up features from the VN-7000: Record over 850 hours | IP via 2GB memory card

lang:en score:14 filesize: 3.99 M page_count: 24 document_date: 2011-05-02

[B&H Photo Video Portable Entertainment Catalog](#)

Explore a comprehensive catalog of portable entertainment devices from B&H Photo Video, featuring digital voice recorders, two-way radios, eBooks, internet devices, iPad accessories, audio players, speakers, headphones, portable TVs, and DVD/Blu-ray players from leading brands like Sony, Olympus, Panasonic, and more.

lang:en score:12 filesize: 3.54 M page_count: 26 document date: 2010-10-14