

CASIO DQD-700J-8JF

CASIO WAVE CEPTOR Radio Clock DQD-700J-8JF User Manual

Model: DQD-700J-8JF

1. PRODUCT OVERVIEW

The CASIO WAVE CEPTOR DQD-700J-8JF is a radio-controlled digital alarm clock designed for accurate timekeeping and environmental monitoring. It features a large, easy-to-read LCD display that shows the current time, date, day of the week, temperature, and humidity. Equipped with a dual electronic alarm function, it allows users to set two separate alarm times with options for daily, weekday, or weekend activation. The clock also includes a radio wave reception indicator to confirm successful time synchronization.



Figure 1: Front view of the CASIO WAVE CEPTOR DQD-700J-8JF radio clock, displaying time, date, temperature, and humidity on its digital screen.

2. SETUP

2.1 Battery Installation

1. Open the battery compartment cover located on the back of the unit.
2. Insert two AAA batteries, ensuring correct polarity (+/-).
3. Close the battery compartment cover securely.

2.2 Initial Time Setting (Radio Wave Reception)

Upon battery installation, the clock will automatically attempt to receive radio wave signals to set the correct time and date. Place the clock in a location with good signal reception, ideally near a window and away from electronic devices that may cause interference. The radio wave reception indicator will show the signal strength.

- If reception is successful, the time and date will be set automatically.
- If reception fails, the clock will display a default time. You may need to manually set the time (refer to Section 3.1).

3. OPERATING INSTRUCTIONS

3.1 Setting the Alarm

This clock features two independent electronic alarms (Alarm 1 and Alarm 2).

1. Press the **ALARM SET** button to select Alarm 1 or Alarm 2. The selected alarm icon will flash.
2. Use the **HOUR** and **MINUTE** buttons to adjust the desired alarm time.
3. Press the **MODE** button to cycle through alarm day settings: **DAILY** (Monday-Sunday), **WEEKDAY** (Monday-Friday), or **WEEKEND** (Saturday-Sunday).
4. Press the **ALARM ON/OFF** switch to activate or deactivate the alarm. The alarm icon will appear when active.

3.2 Using the Temperature and Humidity Display

The clock continuously displays the current indoor temperature and humidity. No special operation is required to view these readings.

- Temperature is displayed in degrees Celsius (°C).
- Humidity is displayed as a percentage (%).

3.3 Hourly Chime

The hourly chime can be activated or deactivated. Refer to the specific button on your device, often labeled **CHIME** or **SIGNAL**, to toggle this feature.

4. MAINTENANCE

To ensure optimal performance and longevity of your CASIO WAVE CEPTOR clock, follow these maintenance guidelines:

- **Cleaning:** Wipe the clock with a soft, dry cloth. Avoid using abrasive cleaners, solvents, or chemical sprays, as these can damage the casing or display.
- **Battery Replacement:** Replace batteries promptly when the display dims or functions become erratic. Always replace all batteries at the same time with new ones of the same type. Dispose of used batteries according to local regulations.
- **Storage:** If storing the clock for an extended period, remove the batteries to prevent leakage and potential damage.

5. TROUBLESHOOTING

If you encounter issues with your clock, please refer to the following common problems and solutions:

- **Time not updating or incorrect:**
 - Ensure the clock is placed in an area with good radio signal reception, away from electronic interference.
 - Check if the batteries are low or incorrectly installed.
 - Perform a manual time setting if automatic reception consistently fails (refer to the full product manual for detailed steps on manual time setting, if available).
- **Alarm not sounding:**
 - Verify that the alarm is activated (alarm icon visible on display).

- Check the alarm volume setting, if adjustable.
- Ensure the alarm time is correctly set.
- **Display is dim or blank:**
 - Replace the batteries with new ones.
 - Check for proper battery installation.

6. SPECIFICATIONS

Feature	Detail
Model Number	DQD-700J-8JF
Brand	CASIO
Body Size (W x H x D)	89mm x 92mm x 60mm
Item Dimensions (W x H)	8.9cm x 6cm
Item Weight	175g (0.21 kg)
Material	Synthetic Resin
Color	Silver
Display Type	Digital LCD
Power Source	Battery Operated (2 AAA batteries included)
Movement	Quartz
Special Features	Radio Wave Reception, Dual Electronic Alarm, Temperature Display, Humidity Display, Hourly Chime
Mounting Type	Freestanding
Country of Origin	China

7. WARRANTY AND SUPPORT

This CASIO product is covered by a manufacturer's warranty. For detailed information regarding warranty terms, conditions, and duration, please refer to the warranty card included with your purchase or visit the official CASIO website. For technical support, troubleshooting assistance beyond this manual, or service inquiries, please contact CASIO customer service through their official channels.

Please retain your proof of purchase for warranty claims.