



[Manuals.plus](#) /

> [Gallery](#) /

> Gallery Maria Theresa Chandelier User Manual

Gallery 804879400479

Gallery Maria Theresa Chandelier User Manual

Model: 804879400479

INTRODUCTION

This manual provides detailed instructions for the safe assembly, installation, operation, and maintenance of your Gallery Maria Theresa Chandelier. Please read all instructions carefully before beginning installation to ensure proper function and safety. This chandelier is designed to enhance the aesthetic of your living space with its elegant crystal design.

The Gallery Maria Theresa Chandelier (Model 804879400479) features 13 lights and is adorned with Empress Crystal. It measures approximately 30 inches in height and 28 inches in width. Assembly is required for this product.

SAFETY INFORMATION

- **WARNING:** Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with electrical wiring.
- Do not install this fixture in wet or damp locations. This product is intended for indoor use only.
- Ensure the mounting surface can support the weight of the fixture.
- Handle crystal components with care to prevent breakage.
- Do not exceed the maximum wattage of 40 watts per bulb.
- Keep packaging materials away from children.

PACKAGE CONTENTS

Carefully unpack all components and check against the list below. Retain all packaging materials until assembly is complete to ensure no parts are discarded.

- Chandelier Frame (main body)
- Crystal Components (various shapes and sizes for dressing the chandelier)
- Mounting Hardware (canopy, mounting strap, screws, wire nuts)
- Chain (18 inches)
- Instruction Manual and Diagram
- Certificate of Authenticity

Note: Light bulbs are not included and must be purchased separately.

SETUP AND INSTALLATION

Installation of this chandelier requires electrical wiring knowledge. It is highly recommended to have a qualified, licensed electrician perform the installation to ensure safety and compliance with electrical codes.

1. Prepare for Installation:

- Turn off the main power supply at the circuit breaker or fuse box.
- Ensure the mounting location is structurally sound and can support the chandelier's weight.
- Unpack all components and lay them out on a clean, soft surface to prevent scratches.

2. Assemble the Chandelier Frame:

- Follow the provided diagram and instructions to assemble the main frame of the chandelier. This typically involves attaching arms and central column sections.

3. Mount the Fixture:

- Attach the mounting strap to the junction box in the ceiling.
- Connect the chain to the chandelier's top loop and the mounting canopy. Adjust the chain length as desired (maximum 18 inches provided).
- Carefully lift the chandelier and make the electrical connections: connect the fixture's live wire (usually black) to the house's live wire, the fixture's neutral wire (usually white) to the house's neutral wire, and the ground wire to the house's ground wire. Secure connections with wire nuts.
- Tuck wires into the junction box and secure the canopy to the mounting strap.

4. Dress with Crystals:

- Once the frame is securely mounted, begin attaching the Empress Crystal components. Refer to the provided diagram for the correct placement of each crystal strand and pendant. This process can be time-consuming and requires careful handling.

5. Install Light Bulbs:

- Screw 13 E12 candelabra base bulbs (not included) into the sockets. Ensure bulbs do not exceed 40 watts each.

6. Restore Power:

- Once assembly and wiring are complete, restore power at the circuit breaker.



Figure 1: Fully assembled Gallery Maria Theresa Chandelier. This image displays the intricate crystal design and 13 illuminated candle-style bulbs. The chandelier features multiple tiers of crystal strands and pendants, reflecting light to create a sparkling effect. It is designed for ceiling mount installation.

OPERATING INSTRUCTIONS

The Gallery Maria Theresa Chandelier is operated via a standard wall switch. For enhanced control over lighting ambiance, consider installing a compatible dimmer switch (sold separately).

- **Bulb Compatibility:** This fixture is compatible with LED, incandescent, halogen, and compact fluorescent bulbs. Ensure bulbs have an E12 candelabra base.
- **Wattage:** Do not exceed 40 watts per bulb.
- **Control:** The chandelier can be turned ON/OFF using a standard wall switch. If a dimmer switch is installed, adjust the light intensity by rotating or sliding the dimmer control.

MAINTENANCE

Regular maintenance will help preserve the beauty and functionality of your chandelier.

- **Cleaning the Frame:** Dust the metal frame regularly with a soft, dry cloth. For more thorough cleaning, dampen the cloth slightly with water and a mild, non-abrasive cleaner. Avoid harsh chemicals that may damage the finish.
- **Cleaning the Crystals:** The Empress Crystals can be cleaned with a soft, lint-free cloth dampened with a specialized crystal cleaner or a solution of mild soap and water. Gently wipe each crystal. Avoid spraying cleaner directly onto the fixture to prevent liquid from entering electrical components.
- **Bulb Replacement:** Always turn off the power at the circuit breaker before replacing bulbs. Allow bulbs to

cool completely before touching. Unscrew the old bulb and screw in a new E12 candelabra base bulb, ensuring it does not exceed 40 watts.

TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	<ul style="list-style-type: none">• Power is off at the switch or circuit breaker.• Loose wiring connection.• Defective bulb.	<ul style="list-style-type: none">• Check wall switch and circuit breaker.• Verify all wiring connections are secure (consult an electrician if unsure).• Replace bulb with a new one.
Lights flicker.	<ul style="list-style-type: none">• Loose bulb.• Loose wiring connection.• Incompatible dimmer switch.	<ul style="list-style-type: none">• Tighten bulbs in their sockets.• Check wiring connections (consult an electrician).• Ensure dimmer switch is compatible with LED/CFL bulbs if used.
Chandelier hangs unevenly.	<ul style="list-style-type: none">• Improperly installed mounting hardware.• Unevenly distributed crystal weight.	<ul style="list-style-type: none">• Re-check mounting hardware installation.• Verify crystals are attached according to the diagram.

If problems persist, please contact Gallery customer support.

SPECIFICATIONS

Brand	Gallery
Model Number	804879400479
Dimensions (H x W)	30 inches x 28 inches
Material	Crystal (Empress Crystal)
Color	Clear
Number of Lights	13
Bulb Base	E12 Candelabra
Max Wattage per Bulb	40 Watts
Voltage	120 Volts

Light Source Compatibility	LED, Incandescent, Halogen, Compact Fluorescent
Control Method	Touch / Push Button (via wall switch)
Mounting Type	Ceiling Mount, Suspended
Indoor/Outdoor Usage	Indoor
Required Assembly	Yes
Included Components	Chain (18 inches)

WARRANTY INFORMATION

Your Gallery Maria Theresa Chandelier is backed by a Gallery warranty, established in 1978. Each item includes a Certificate of Authenticity, certifying it as an authentic Gallery lighting fixture. Please retain your proof of purchase and Certificate of Authenticity for warranty claims.

For specific warranty terms and conditions, please refer to the documentation included with your product or contact Gallery customer support.

CUSTOMER SUPPORT

For any technical assistance, questions regarding assembly, installation, or troubleshooting, Gallery provides free technical support.

Please refer to the contact information provided with your product for the toll-free support number.

When contacting support, please have your model number (804879400479) and proof of purchase ready.