

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Brilliant](#) /

› [BRILLIANT Luca 4-Flame Spot Tube Light Instruction Manual](#)

Brilliant 35832/56

BRILLIANT Luca 4-Flame Spot Tube Light

Model: 35832/56

INTRODUCTION

This manual provides essential information for the safe and efficient installation, operation, and maintenance of your BRILLIANT Luca 4-Flame Spot Tube Light. Please read these instructions carefully before installation and retain them for future reference.



Image 1: The BRILLIANT Luca 4-Flame Spot Tube Light. This image displays the complete light fixture, featuring a long, brown metal bar with four individual spot heads. Each spot head is adjustable and includes a beige glass shade, designed to direct light. The central mounting plate is also visible.

SAFETY INSTRUCTIONS

- Always disconnect power at the main fuse or circuit breaker before installation, maintenance, or bulb replacement.
- Installation should be performed by a qualified electrician or competent person.
- Ensure the mounting surface can support the weight of the fixture.
- Do not exceed the maximum wattage specified for the bulbs (40W per bulb).
- This product is designed for indoor use only (IP20 rating). Do not expose to moisture or extreme temperatures.
- Allow bulbs to cool before touching or replacing them.
- Keep packaging materials out of reach of children.

PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- 1x BRILLIANT Luca 4-Flame Spot Tube Light fixture
- Mounting material (screws, wall plugs, etc.)
- Instruction Manual

Note: Light bulbs (E14, R50 reflector type, max 40W) are not included and must be purchased separately. LED bulbs are compatible.

SPECIFICATIONS

Brand	Brilliant
Model Number	35832/56
Dimensions (L x W x H)	85 x 23.2 x 23.2 cm
Weight	1.22 kg
Material	Metal, Glass
Color	Brown (fixture), Beige (shade)
Number of Bulbs	4
Bulb Socket Type	E14
Max Wattage per Bulb	40 Watts
Voltage	240 Volts
IP Rating	IP20 (Indoor use only)
Special Features	Dimmable (with appropriate bulbs and external dimmer), Adjustable Spot Heads
Installation Type	Ceiling Mount

SETUP AND INSTALLATION

Important: Before starting installation, ensure the power supply is switched off at the main circuit breaker to prevent electric shock.

- Prepare the Mounting Surface:** Choose a suitable location on your ceiling or wall. Ensure the surface is clean, dry, and structurally sound to support the light fixture.
- Mark Drilling Points:** Hold the mounting bracket of the fixture against the desired installation spot. Use a pencil to mark the positions for drilling holes.
- Drill Holes:** Drill holes at the marked positions using an appropriate drill bit for your ceiling/wall material. Insert the provided wall plugs into the drilled holes.
- Secure Mounting Bracket:** Attach the mounting bracket to the ceiling/wall using the provided screws. Ensure it is firmly secured.
- Electrical Connection:** Connect the household electrical wires to the terminal block on the fixture. Follow standard

wiring color codes (e.g., Live to Live, Neutral to Neutral, Earth to Earth). Ensure all connections are secure.

6. **Attach Fixture to Bracket:** Carefully align the light fixture with the secured mounting bracket and attach it using the remaining screws or fastening mechanism.
7. **Install Bulbs:** Insert four E14 R50 reflector bulbs (not included) into the lamp holders. Do not exceed 40 Watts per bulb. LED bulbs are recommended for energy efficiency.
8. **Restore Power:** Once installation is complete and all connections are secure, restore power at the main circuit breaker.

Consult a qualified electrician if you are unsure about any part of the installation process.

OPERATING INSTRUCTIONS

- **Switching On/Off:** Operate the light using your standard wall switch.
- **Adjusting Spot Heads:** The individual spot heads are pivotable and the arms are rotatable. Gently adjust each spot head and arm to direct the light to your desired area.
- **Dimming Function:** If you are using dimmable E14 bulbs and have an external dimmer switch installed, you can adjust the light intensity by operating the dimmer. Ensure your bulbs are compatible with your dimmer type.

MAINTENANCE

- **Cleaning:** Disconnect power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners or solvents, as these can damage the finish.
- **Bulb Replacement:**
 - a. Ensure the light is switched off and has cooled down completely.
 - b. Carefully unscrew the old E14 bulb from its socket.
 - c. Screw in a new E14 R50 reflector bulb, ensuring it is no more than 40 Watts.
 - d. Restore power and test the light.
- **Regular Checks:** Periodically check all connections and mounting screws to ensure they remain tight and secure.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	<ul style="list-style-type: none">◦ No power supply.◦ Loose wiring connection.◦ Faulty bulb.	<ul style="list-style-type: none">◦ Check circuit breaker/fuse.◦ Ensure all wiring connections are secure (power off first).◦ Replace bulb with a new one.
Light flickers.	<ul style="list-style-type: none">◦ Loose bulb.◦ Incompatible dimmer/bulb.◦ Faulty wiring.	<ul style="list-style-type: none">◦ Tighten bulb.◦ Ensure dimmable bulbs are used with a compatible dimmer.◦ Consult a qualified electrician.
Dimming does not work.	<ul style="list-style-type: none">◦ Non-dimmable bulbs installed.◦ Incompatible dimmer switch.	<ul style="list-style-type: none">◦ Replace with dimmable E14 bulbs.◦ Ensure dimmer switch is compatible with LED or incandescent bulbs as appropriate.

If problems persist, contact customer support or a qualified electrician.

WARRANTY AND SUPPORT

Information regarding warranty and spare parts availability is not provided in the product details. For support, please refer to the retailer or manufacturer's official website.

Manufacturer: Brilliant

© 2024 Brilliant. All rights reserved.