

[Manuals.plus](#) /

› [Nuvo](#) /

› Nuvo Lighting 60/4755 Gemini Collection 5-Light Chandelier Instruction Manual

Nuvo 60/4755

Nuvo Lighting 60/4755 Gemini Collection 5-Light Chandelier Instruction Manual

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Nuvo Lighting 60/4755 Gemini Collection 5-Light Chandelier. Please read all instructions carefully before beginning installation and retain this manual for future reference.

The Nuvo Lighting 60/4755 is a transitional style 5-light chandelier featuring a brushed nickel finish and slate gray oval fabric shades. It is designed for indoor use and is suitable for various room types, including living rooms and dining areas.

2. SAFETY INFORMATION

- **Electrical Safety:** Always turn off the main power supply at the circuit breaker or fuse box before beginning any electrical installation or maintenance. Failure to do so may result in electric shock, serious injury, or death.
- **Qualified Installation:** Installation should be performed by a qualified electrician or a person with experience in electrical wiring.
- **UL/cUL Listed:** This fixture is UL and cUL Listed, indicating compliance with North American safety standards.
- **Proposition 65 Warning:** This product may contain chemicals known to the State of California to cause cancer, birth defects, or other reproductive harm. Wash hands after handling.
- **Bulb Requirements:** Use only bulbs of the specified type and wattage. Do not exceed the maximum wattage indicated on the fixture.
- **Secure Mounting:** Ensure the fixture is securely mounted to a structurally sound ceiling support capable of holding the fixture's weight.

3. PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation. If any parts are missing or damaged, do not attempt to install the fixture. Contact customer support for assistance.

- Chandelier Fixture Body (Brushed Nickel)
- 5 x Slate Gray Oval Fabric Shades
- Mounting Hardware (e.g., mounting plate, screws, wire nuts)
- Chain (48 inches)
- Electrical Wire (12 feet)

Note: Five A19 medium base incandescent bulbs (max 60W each) are required but **not included** with this product.

4. SETUP AND INSTALLATION

Assembly is required for this chandelier. Follow these general steps for installation. Consult a qualified electrician if you are unsure about any part of the process.

1. **Turn Off Power:** Before starting, ensure the power to the installation area is completely turned off at the circuit breaker.
2. **Unpack and Inspect:** Carefully remove all components from the packaging and inspect for any damage.
3. **Assemble Fixture:** Follow the specific assembly instructions provided with your fixture to attach the arms, chain, and any decorative elements to the main body.
4. **Mounting Bracket Installation:** Secure the mounting bracket to the ceiling junction box. Ensure the bracket is firmly attached and can support the weight of the chandelier. This fixture is adaptable for sloped ceilings.
5. **Wiring:** Connect the fixture's electrical wires to the corresponding household wires (typically black to black, white to white, and ground to ground) using appropriate wire nuts. Ensure all connections are secure.
6. **Hang Fixture:** Carefully lift and hang the chandelier from the mounting bracket using the provided chain. Adjust the chain length to achieve the desired hanging height. The bottom of the chandelier should typically be 30 to 36 inches above a dining table.
7. **Install Shades:** Attach the five slate gray oval fabric shades to the fixture.
8. **Install Bulbs:** Screw in five A19 medium base (E26) incandescent bulbs, ensuring each does not exceed 60 watts.
9. **Restore Power:** Once installation is complete and all connections are secure, restore power at the circuit breaker.



Image 1: The Nuvo Lighting 60/4755 Gemini Collection 5-Light Chandelier in brushed nickel finish with fabric shades.



Image 2: The Nuvo Lighting 60/4755 Chandelier installed above a dining table in a room with blue walls.

5. OPERATING INSTRUCTIONS

Once properly installed and wired, the Nuvo Lighting 60/4755 Chandelier operates via a standard wall switch connected to the fixture's electrical circuit. The fixture is designed for incandescent light sources.

- **Power On/Off:** Use the wall switch to turn the chandelier on or off.
- **Dimmer Compatibility:** This fixture is compatible with most standard dimmer switches, allowing you to adjust the light output to create the desired ambiance. Ensure your dimmer switch is rated for incandescent loads.
- **Bulb Type:** Uses five A19 medium base (E26) incandescent bulbs.
- **Maximum Wattage:** Do not exceed 60 watts per bulb.

6. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your chandelier.

- **Cleaning:** To clean the fixture, ensure the power is off. Use a soft, dry cloth to wipe down the metal surfaces. For the fabric shades, gently dust with a soft brush or vacuum with a brush attachment. Avoid using abrasive cleaners, solvents, or polishes, as these can damage the finish or fabric.
- **Bulb Replacement:** Before replacing bulbs, turn off the power to the fixture and allow the bulbs to cool completely. Carefully unscrew the old bulb and screw in a new A19 medium base (E26) incandescent bulb, ensuring it does not exceed 60 watts.
- **Periodic Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

7. TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common troubleshooting steps:

- **Lights Not Turning On:**
 - Check if the power switch is in the 'ON' position.
 - Verify that the circuit breaker has not tripped.
 - Ensure bulbs are securely screwed into their sockets and are not burnt out.
 - Confirm all electrical connections are secure and correctly wired.
- **Lights Flickering:**
 - Check for loose bulbs or connections.
 - If using a dimmer, ensure it is compatible with incandescent bulbs and properly installed.
- **Fixture is Loose:**
 - Turn off power and re-tighten any loose mounting screws or chain links.

If these steps do not resolve the issue, consult a qualified electrician or contact Nuvo Lighting customer support.

8. SPECIFICATIONS

Feature	Detail
Brand	Nuvo
Model Number	60/4755
Product Dimensions	25"L x 25"W x 21.25"H
Item Weight	5 pounds
Material	Glass, Metal
Finish Type	Brushed Nickel
Shade Material	Fabric (Slate Gray Oval)
Number of Light Sources	5
Light Source Type	Incandescent
Bulb Base	E26
Max Wattage per Bulb	60 watts
Voltage	120 Volts
Installation Type	Chandelier (Ceiling Mount with Chain)
Special Features	UL Listed, cUL Listed, Sloped Ceiling Adaptable
Assembly Required	Yes
Indoor/Outdoor Usage	Indoor

9. WARRANTY AND SUPPORT

This Nuvo Lighting product is covered by a **1-year limited warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical support, or replacement parts, please contact Nuvo Lighting customer service. You may also visit the official Nuvo Store for additional product information and support resources.

Nuvo Store: [Visit the Nuvo Store on Amazon](#)

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Email

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Details

Submit question

Open the live page

<https://manuals.plus/asin/B005B7QA4M>

More documents and user manuals: <https://manuals.plus/>