

Versa G015-BLACK

Versa Double Watch Winder G015-BLACK Instruction Manual

Model: G015-BLACK

INTRODUCTION

This manual provides comprehensive instructions for the setup, operation, maintenance, and troubleshooting of your Versa Double Watch Winder, Model G015-BLACK. Please read these instructions carefully before using the product to ensure proper function and longevity.





Image: The Versa Double Watch Winder, featuring two empty winding modules, presented in a sleek black finish.

SETUP

- 1. Unpacking:** Carefully remove the watch winder and all accessories from the packaging. Ensure all components, including the power adapter and watch pillows, are present.
- 2. Power Connection:** Connect the provided 100-240V AC power adapter to the winder's power input port and then to a suitable electrical outlet.
- 3. Watch Placement:**
 - Gently compress the spring-action watch pillow and insert your automatic watch onto it.
 - The pillows are designed to accommodate a wide range of wrist sizes, from 6 inches to 8.25 inches. For larger watches or wristbands, an additional attachment is included to expand the pillow size.
 - Ensure the watch is securely seated on the pillow and the non-slip grips hold it in place.
 - Insert the watch and pillow assembly into one of the winder's modules. The pillow should click positively into place.



Image: Three watch pillows, one with a watch, illustrating the secure attachment mechanism for timepieces.

Adjustable Watch Pillow Great for Small and Large Wristbands and Oversize Watches



Pillow without adapter:
6 – 7.25 inches



Pillow with large adapter:
6.75 – 8 inches

Image: A diagram detailing the adjustable watch pillow, showing how it adapts to various wrist sizes with and without the included adapter.

OPERATING INSTRUCTIONS

The Versa Double Watch Winder features independent controls for each winding module, allowing for customized settings for each watch.



MULTIPLE SETTINGS

For direction and TPD
(Turns Per Day)

ADJUSTABLE

Spring action pillow to hold small and large wrists



PLENTY OF SPACE

To hold large size watches



 **Versa**

Image: A detailed view of the winder's control panel, highlighting the individual on/off switches, Turns Per Day (TPD) selectors, and rotation direction options for each module.

1. **Independent Control:** Each watch turner has its own on/off switch. Use these to activate or deactivate individual winding modules as needed.

2. **Turns Per Day (TPD) Settings:** Select the desired TPD using the rotary switch for each module. The available settings are:

- 650 TPD
- 850 TPD
- 1050 TPD
- 1250 TPD

Most automatic watches operate optimally between 650-850 TPD. It is recommended to start with these settings in bi-directional rotation. Consult your watch manufacturer's specifications for precise TPD requirements. If you experience issues keeping your watch wound, adjust the TPD setting accordingly.

3. **Direction Settings:** Choose the rotation direction for each module using the dedicated switch. Options include:

- Clockwise
- Counter-clockwise
- Bi-directional (alternating clockwise and counter-clockwise)

There are 12 different setting combinations possible by adjusting TPD and direction for each module.

4. **Winding Cycle:** The winder operates in cycles to prevent overwinding. Each cycle involves approximately 7 minutes of turning, followed by a rest period. The duration of the rest period varies depending on the selected TPD setting. This cycle repeats as long as the winder is powered on.

MAINTENANCE

- **Cleaning:** To clean the exterior of the winder, use a soft, dry cloth. Avoid abrasive cleaners or solvents that may damage the finish.
- **Pillow Care:** Ensure watch pillows are free from dust and debris. If a pillow becomes damaged, contact customer support for potential replacement options.
- **Placement:** Place the winder on a stable, level surface away from direct sunlight, extreme temperatures, and high humidity.

TROUBLESHOOTING

- **Winder Not Operating:**
 - Verify that the power adapter is securely connected to both the winder and a working electrical outlet.
 - Ensure the individual on/off switch for the specific winding module is in the 'ON' position.
- **Watch Not Winding:**
 - Confirm that the TPD and direction settings are appropriate for your specific automatic watch model. Refer to your watch's manual or an online database for recommended settings.
 - Ensure the watch is correctly seated on the pillow and the pillow is properly inserted into the winder module.
- **Unusual Noise:** While the winder is designed for quiet operation, slight noises may occur if the watch pillow is not perfectly snug. Ensure the pillow is fully inserted and the watch is centered.
- **Compatibility Note:** This watch winder is not compatible with Seiko Kinetic watches, as their winding mechanism differs from traditional automatic movements.
- **Magnetization:** The winder has been tested and is designed not to magnetize your automatic watches.

SPECIFICATIONS

Feature	Detail
Model Number	G015-BLACK
Dimensions (L x W x H)	6.5 x 5.5 x 10 inches
Weight	2.97 Pounds
Power Input	AC 100-240V
Motor Type	Direct-drive motor
Watch Capacity	2 automatic watches (one per module)

Feature	Detail
TPD Settings	650, 850, 1050, 1250
Rotation Directions	Clockwise, Counter-clockwise, Bi-directional
Manufacturer	Versa

WARRANTY

The Versa Double Watch Winder G015-BLACK comes with a **1-Year Warranty** from the date of purchase. This warranty covers manufacturing defects and ensures the product functions as intended under normal use. Please retain your proof of purchase for warranty claims.

SUPPORT


For any questions, concerns, or assistance with your Versa Double Watch Winder, please contact our customer service team. We are committed to providing support and resolving any issues you may encounter.

Contact information can typically be found on the Versa official website or through your purchase platform.

© Versa. All rights reserved.

Related Documents - G015-BLACK

 <p>Versa G088 Watch Winder: Instruction Manual and Usage Guide</p> <p>Comprehensive instruction manual for the Versa G088 watch winder, covering specifications, operation, features, and tips for optimal watch winding. Includes brand compatibility settings.</p>
 <p>Versa G078 Watch Winder Instruction Manual</p> <p>Instruction manual for the Versa G078 watch winder, detailing specifications, features, operation, and tips for setting TPD and rotation direction for various watch brands.</p>
 <p>Versa G084 Watch Winder Instruction Manual</p> <p>Comprehensive instruction manual for the Versa G084 watch winder, detailing specifications, features, operation, and troubleshooting tips for automatic watch winding.</p>

	<p><u>Versa Watch Winder G016 Instruction Manual</u></p> <p>Instruction manual for the Versa G016 watch winder, detailing specifications, features, operation, and tips for optimal use with various watch brands.</p>
	<p><u>Versa VW-DP Motion Sensor: Operation, Installation, and Specifications</u></p> <p>Comprehensive guide to the Versa VW-DP Motion Sensor, covering its features, installation instructions, operational programming, walk test procedures, and technical specifications. Includes details on pet immunity and FCC compliance.</p>
	<p><u>Z-Wave Plug-in Dimmer Outlet Conformance Statement</u></p> <p>This document details the Z-Wave Protocol Implementation Conformance Statement for the Versa Plug-in Dimmer Outlet, including product features, technical information, and supported command classes.</p>