

Progress Lighting P4441-20

Progress Lighting P4441-20 Gather Chandelier Instruction Manual

Model: P4441-20 | Brand: Progress Lighting

1. INTRODUCTION

Thank you for choosing the Progress Lighting P4441-20 Gather Chandelier. This five-light chandelier features a smart simplicity with antique bronze metal arms that curve downwards to support white etched glass shades. The etched glass provides distinctive and pleasing illumination, making it a versatile addition to various home styles. This manual provides essential information for the safe and proper installation, operation, and maintenance of your new lighting fixture.



Figure 1: Progress Lighting P4441-20 Gather Chandelier, Antique Bronze. This image displays the chandelier's five-light design with antique bronze finish and white etched glass shades.

2. IMPORTANT SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing.

- Always consult a qualified electrician for installation if you are not comfortable with electrical wiring.
- Ensure all electrical connections comply with local codes and ordinances, and the National Electric Code (NEC).
- This product is intended for indoor, residential use only.
- Do not exceed the maximum wattage specified for the bulbs.
- Handle glass shades with care to prevent breakage.
- Proposition 65 Warning: This product may contain chemicals known to the State of California to cause cancer and birth defects or other reproductive harm.

3. WHAT'S INCLUDED

Verify that all components are present before beginning installation:

- Chandelier Fixture (with pre-attached arms and wiring)
- White Etched Glass Shades (5 pieces)
- Mounting Hardware (crossbar, screws, wire nuts)
- Chain (42 inches of 9 gauge chain supplied)
- Canopy/Ceiling Plate
- Installation Sheet



Figure 2: Dimensional drawing of the P4441-20 Chandelier. This diagram illustrates the overall height (15 inches) and width (20.5 inches) of the fixture.

4. SETUP AND INSTALLATION

Follow these general steps for installation. Refer to the included installation sheet for detailed diagrams and specific instructions.

1. **Prepare for Installation:** Turn off power at the main circuit breaker or fuse box. Clear the work area and ensure you have all necessary tools (screwdriver, wire strippers, pliers, ladder).
2. **Assemble Fixture:** Carefully unpack the chandelier. The arms may need to be gently unfolded and positioned evenly. Attach the glass shades to each light socket.
3. **Determine Chain Length:** The chandelier comes with 42 inches of 9 gauge chain. Adjust the chain length to achieve the desired hanging height. For dining tables, the bottom of the chandelier should typically be 30-36 inches above the tabletop. For foyers or living rooms, ensure at least 7 feet of clearance from the floor to the bottom of the fixture. Use pliers to open and close chain links as needed.
4. **Mounting the Crossbar:** Secure the mounting crossbar to your electrical junction box using the provided screws.
5. **Wiring:** Connect the fixture's wires to the corresponding house wires (black to black, white to white, ground to ground) using wire nuts. Ensure all connections are secure.
6. **Secure Canopy:** Slide the canopy up the chain and secure it to the mounting crossbar, covering the electrical

connections.

- 7. **Install Bulbs:** Screw in the appropriate light bulbs (E26 base, max 100 watts per bulb, incandescent recommended).
- 8. **Restore Power:** Turn the power back on at the circuit breaker.

Professional Installation Recommended: For safety and optimal performance, it is highly recommended to have this fixture installed by a qualified electrician, especially if you are unfamiliar with electrical wiring.

Your browser does not support the video tag.

Video 1: Progress Lighting Chandelier Overview. This video provides a general overview of Progress Lighting chandeliers, including insights into design and installation considerations.

Your browser does not support the video tag.

Video 2: Brushed Nickel Collective Video. While showcasing a brushed nickel collection, this video may offer visual cues for general chandelier features and installation, applicable to the Gather series.

5. OPERATING INSTRUCTIONS

The P4441-20 Gather Chandelier is designed for simple operation via a standard wall switch. It features five light sockets, providing ample illumination for your space.

- **Power On/Off:** Use your existing wall switch to turn the chandelier on or off.
- **Dimmable Functionality:** This fixture is compatible with dimmer switches, allowing you to adjust the light intensity to create your desired ambiance. Ensure you use dimmable bulbs if connecting to a dimmer switch.
- **Bulb Type:** Uses 5 incandescent bulbs with an E26 base, up to 100 watts each.

6. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your chandelier.

- **Cleaning:** To clean the fixture, turn off the power and allow it to cool. Wipe the metal parts with a soft, dry cloth. For the glass shades, use a mild glass cleaner on a soft cloth, then wipe dry. Avoid abrasive cleaners or solvents that could damage the finish.
- **Bulb Replacement:** Ensure the power is off and bulbs have cooled before replacing. Unscrew the old bulb and screw in a new E26 base bulb, not exceeding 100 watts.

7. TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power, loose wiring, faulty bulb.	Check circuit breaker/fuse. Ensure all wire connections are secure. Replace bulb.
Lights flicker.	Loose bulb, incompatible dimmer, loose wiring.	Tighten bulbs. Ensure dimmer is compatible with bulb type. Check wiring connections.
Fixture hangs unevenly.	Improper chain adjustment or mounting.	Re-adjust chain links for even distribution. Verify mounting hardware is securely and levelly installed.

If problems persist, contact Progress Lighting customer service or a qualified electrician.


8. SPECIFICATIONS

Feature	Detail
Brand	Progress Lighting
Model Number	P4441-20
Color	Antique Bronze
Material	Alloy Steel, Glass
Style	Modern / Contemporary
Light Fixture Form	Chandelier
Product Dimensions (L x W x H)	20.5" x 20.5" x 15"
Number of Light Sources	5
Wattage (Max per bulb)	100 watts
Voltage	120 Volts
Bulb Base	E26
Installation Type	Semi Flush Mount (Chain supplied for adjustable hanging)
Indoor/Outdoor Usage	Indoor
Assembly Required	Yes
Certifications	UL, cUL

9. WARRANTY AND SUPPORT

This Progress Lighting P4441-20 Gather Chandelier is covered by a **1-year Limited Warranty**. This warranty guarantees your complete satisfaction with your purchase and includes professional after-sales customer service support. For warranty claims, technical assistance, or any questions regarding your product, please refer to the contact information provided on the original packaging or visit the official Progress Lighting website.

Related Documents - P4441-20

	<p>Progress Lighting P400399 20-Light Chandelier Installation Guide</p> <p>Comprehensive installation instructions and safety information for the Progress Lighting P400399 20-Light Chandelier. Learn how to safely assemble and mount your new fixture.</p>
---	---

[Progress Lighting Riley P400209-031 5-Light Black Chandelier - Specifications and Overview](#)

Detailed specifications, features, and product overview for the Progress Lighting Riley P400209-031 5-light black chandelier with clear glass shades. Includes dimensions, electrical, mounting, and warranty information.

Progress Lighting P400391 & P400392 Chandelier Installation and Assembly Guide

Detailed installation and assembly instructions for Progress Lighting P400391 (5-Light Chandelier) and P400392 (6-Light Chandelier). Includes safety information, parts list, hardware details, and step-by-step guidance.

Progress Lighting P400323 & P400324 Chandelier Installation Guide

Official installation and assembly guide for Progress Lighting Laila collection chandeliers (models P400323 and P400324). Includes package contents, hardware, safety information, and step-by-step assembly instructions.

Progress Lighting P400395 6-Light Chandelier Assembly Instructions

Comprehensive assembly and installation guide for the Progress Lighting P400395 6-Light Chandelier. Features package contents, hardware details, safety precautions, and step-by-step installation procedures.

Progress Lighting P400370 4-LT Chandelier Installation Guide

Detailed installation manual for the Progress Lighting P400370 4-Light Chandelier, including package contents, hardware list, safety information, assembly steps, and warranty details.