

[Manuals.plus](#) /

› [Behringer](#) /

› Behringer EUROLIVE B115MP3 Speaker System User Manual

Behringer B115MP3

Behringer EUROLIVE B115MP3 Speaker System User Manual

Model: B115MP3

1. INTRODUCTION

The Behringer EUROLIVE B115MP3 is a high-power, two-way PA sound reinforcement speaker system designed for live and playback applications. This ultra-compact and lightweight system delivers excellent sound even at extreme sound pressure levels, featuring an integrated MP3 player for audio file playback via USB stick.





Figure 1: Front view of the Behringer EUROLIVE B115MP3 Speaker System, showcasing its robust grille and the Behringer logo.

2. IMPORTANT SAFETY INSTRUCTIONS

Always follow these basic safety precautions when using your EUROLIVE B115MP3 speaker system:

- Read these instructions.
- Keep these instructions.
- Heed all warnings.
- Follow all instructions.
- Do not use this apparatus near water.
- Clean only with a dry cloth.
- Do not block any ventilation openings. Install in accordance with the manufacturer's instructions.
- Do not install near any heat sources such as radiators, heat registers, stoves, or other apparatus (including amplifiers) that produce heat.

- Do not defeat the safety purpose of the polarized or grounding-type plug. A polarized plug has two blades with one wider than the other. A grounding type plug has two blades and a third grounding prong. The wide blade or the third prong are provided for your safety. If the provided plug does not fit into your outlet, consult an electrician for replacement of the obsolete outlet.
- Protect the power cord from being walked on or pinched particularly at plugs, convenience receptacles, and the point where they exit from the apparatus.
- Only use attachments/accessories specified by the manufacturer.
- Use only with the cart, stand, tripod, bracket, or table specified by the manufacturer, or sold with the apparatus. When a cart is used, use caution when moving the cart/apparatus combination to avoid injury from tip-over.
- Unplug this apparatus during lightning storms or when unused for long periods of time.
- Refer all servicing to qualified service personnel. Servicing is required when the apparatus has been damaged in any way, such as power-supply cord or plug is damaged, liquid has been spilled or objects have fallen into the apparatus, the apparatus has been exposed to rain or moisture, does not operate normally, or has been dropped.

3. KEY FEATURES

- High-power 1000 watt two-way PA sound reinforcement speaker system for live and playback applications.
- Ultra-compact and lightweight system delivers excellent sound even at extreme sound pressure levels.
- High-performance MP3 player included to play audio files via USB stick.
- Equipped with a 15-inch woofer for powerful bass and a 1.35-inch aluminum-diaphragm compression driver for exceptional high-frequency reproduction.
- Integrated mixer with two mic/line inputs, individual volume controls, and a 2-band EQ.
- Dedicated 2-band EQ for perfect sound adjustment.
- Versatile trapezoidal enclosure design allows different positioning: stand mounting with 35-mm pole socket or tilt on its side for use as a floor monitor.
- Ergonomically shaped handles for easy carrying and setup.

4. SETUP

4.1 Unpacking

Carefully unpack your EUROLIVE B115MP3 speaker system. Inspect the unit for any signs of damage that may have occurred during transit. If damage is found, contact your dealer immediately.

4.2 Placement

The B115MP3 can be used in various configurations:

- **Pole Mounting:** Use the integrated 35-mm pole socket to mount the speaker on a standard speaker stand. Ensure the stand is stable and capable of supporting the speaker's weight (approximately 20.5 kg / 45.15 lbs).
- **Floor Monitor:** The trapezoidal design allows the speaker to be tilted on its side for use as a floor monitor, directing sound towards performers.
- **Tabletop:** For smaller applications, the speaker can be placed on a stable, flat surface.

4.3 Power Connection

Connect the supplied power cord to the AC inlet on the rear panel of the speaker and then to a suitable power outlet. Ensure the power switch is in the "OFF" position before connecting to power.

4.4 Audio Connections

The B115MP3 features multiple input options:

- **Mic/Line Inputs:** Use XLR or 1/4" TRS cables to connect microphones, mixers, or other audio sources to the dedicated input channels.
- **USB Input:** Insert a USB stick containing MP3 audio files into the USB port for direct playback.

5. OPERATING INSTRUCTIONS

5.1 Powering On/Off

1. Ensure all volume controls are set to minimum before powering on.
2. Flip the power switch to the "ON" position. The power indicator LED will illuminate.
3. To power off, set all volume controls to minimum, then flip the power switch to "OFF".

5.2 Adjusting Volume and EQ

Use the individual volume controls for each input channel to set the desired level. The 2-band EQ (Bass and Treble) allows you to fine-tune the speaker's frequency response to suit your environment and audio source.

5.3 MP3 Playback via USB

1. Insert a USB stick (formatted as FAT16 or FAT32) containing MP3 files into the USB port.
2. Use the controls on the MP3 player section (Play/Pause, Next/Previous Track, Mode) to navigate and play your audio files.
3. Ensure the MP3 player's volume is adjusted appropriately using its dedicated control.

Note: The integrated MP3 player supports standard MP3 audio files. Other formats (e.g., Apple files, Rhapsody files) may not be compatible.

6. MAINTENANCE

- **Cleaning:** Disconnect the speaker from power before cleaning. Use a soft, dry cloth to wipe down the exterior. Do not use liquid cleaners or aerosols.
- **Storage:** If storing the speaker for an extended period, keep it in a dry, dust-free environment, preferably in its original packaging or a protective cover.
- **Ventilation:** Ensure ventilation openings are clear of dust and debris to prevent overheating.

7. TROUBLESHOOTING

Problem	Possible Cause	Solution
No sound output.	Power not connected; volume controls too low; input source not connected or active.	Check power cable and switch; increase master and input volumes; verify input source connection and output.
Distorted sound.	Input signal too high (clipping); EQ settings incorrect; damaged cable.	Reduce input gain; adjust EQ settings; try a different cable.
MP3 player not reading USB.	Incorrect USB format; unsupported file type; corrupted USB stick.	Ensure USB is FAT16/FAT32; verify files are MP3; try a different USB stick.

Problem	Possible Cause	Solution
No power.	Power cable loose; power outlet faulty; internal fuse blown.	Check power cable connection; test outlet with another device; contact qualified service personnel if fuse is suspected.

8. SPECIFICATIONS

Model	EUROLIVE B115MP3
Output Wattage	1000 Watts
Item Weight	20.5 Kilograms (45.15 Pounds)
Product Dimensions (L x W x H)	77.98 x 52.83 x 41.66 cm (30.7 x 20.8 x 16.4 inches)
Connector Type	USB
Audio Input	Mic/Line, USB
Power Source	Corded Electric
Speaker Amplification Type	Active
Color	Black
Manufacturer	Music Tribe
UPC	794504547610

9. WARRANTY AND SUPPORT

For detailed warranty information and technical support, please refer to the official Behringer website or contact your local Behringer distributor. Keep your proof of purchase for any warranty claims.
Online Support: Visit www.behringer.com/support for FAQs, downloads, and contact information.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Answered questions about this manual

What kind of USB player or drive can I connect to the Behringer EUROLIVE B115MP3 speaker?

The Behringer EUROLIVE B115MP3 features an integrated MP3 player that is designed to work with standard USB flash drives (USB sticks). To ensure compatibility, please follow these requirements:File Format: The player supports standard MP3...

[Read full answer](#)