Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

Metz Aurus 42 3D Media Twin R

Metz Aurus 42 3D Media Twin R 42-inch Full HD 3D OLED Television User Manual

Model: Aurus 42 3D Media Twin R | Brand: Metz

1. Initial Setup

This section guides you through the initial setup process of your Metz Aurus 42 3D Media Twin R television. Please follow these steps carefully to ensure proper installation and functionality.

1.1 Unpacking and Placement

- Carefully remove the television and all accessories from the packaging. Retain the packaging for future transport or service.
- Place the television on a stable, flat surface using the provided table stand, or mount it securely to a wall using a compatible VESA mount (sold separately). Ensure adequate ventilation around the unit.
- The television dimensions are approximately 104.6 cm (width) x 10.2 cm (depth) x 68.2 cm (height) without stand, and it weighs 27.1 kg. With the stand, the weight is 31 kg.



Image 1.1: Front view of the Metz Aurus 42 3D Media Twin R Television, showcasing its sleek design and integrated soundbar.

1.2 Connecting Power

- Connect the power cord to the AC input on the television and then to a suitable wall outlet (AC 220-240V, 50Hz).

- The television has an integrated on/off switch. Ensure it is in the 'off' position before connecting to power.

1.3 External Device Connections

Your television offers various ports for connecting external devices:

- **HDMI Ports (x4):** For high-definition audio and video sources such as Blu-ray players, gaming consoles, and set-top boxes.
- **USB 2.0 Ports (x2):** For connecting USB storage devices to play media or for Timeshift recording.
- **DVI-I Port (x1):** For connecting computers or other DVI-compatible devices.
- **Component Video (YPbPr/YCbCr) Input (x1):** For analog high-definition video sources.
- **AV Input (x1):** For standard definition analog video and audio sources.
- **Ethernet Port:** For network connectivity (Note: This model does not support Wi-Fi directly).
- **Common Interface Plus (CI+) Slot:** For conditional access modules (CAMs) required by some pay-TV services.

2. Operating Instructions

This section details the general operation of your Metz Aurus 42 3D Media Twin R television.

2.1 Basic Operation

- **Power On/Off:** Use the integrated power switch on the television or the power button on the remote control to turn the unit on or off.
- **Remote Control:** The television comes with a remote control for convenient operation. Ensure batteries are correctly inserted.
- **Input Selection:** Use the 'Source' or 'Input' button on the remote to switch between connected devices (HDMI, AV, etc.).

2.2 Display and Audio Features

- **Display Technology:** Enjoy vibrant visuals on the 42-inch Full HD (1920 x 1080 pixels) OLED display.
- **3D Capability:** The television supports 3D content. Compatible 3D glasses (sold separately) are required for viewing 3D material.
- **Audio System:** Features a Bass reflex system with mecaSoundpro technology and 4 integrated speakers, delivering an estimated RMS power of 40W.
- **Equalizer:** A 7-band equalizer is available for audio customization.

2.3 Digital Tuner and Recording

- **Digital Tuner:** Integrated DVB-C, DVB-S2, and DVB-T tuners allow reception of digital terrestrial, cable, and satellite broadcasts.
- **Timeshift Recording:** Utilize the Timeshift function to pause live TV and resume viewing later. A 750 GB hard drive is integrated for recording.
- **Electronic Program Guide (EPG):** Access the EPG to view program schedules and plan recordings.

2.4 Special Features

- **24p Playback:** Supports 24p film mode for a cinematic viewing experience.
- **Parental Control:** Activate parental lock features to restrict access to certain channels or content.
- **Teletext:** Access teletext services for news and information.
- **Sleep Timer:** Set a timer for the television to automatically turn off.

3. Maintenance

Proper maintenance ensures the longevity and optimal performance of your television.

- **Screen Cleaning:** Gently wipe the screen with a soft, lint-free cloth. For stubborn marks, use a screen-specific cleaning solution applied to the cloth, not directly to the screen.
- **Cabinet Cleaning:** Use a soft, dry cloth to clean the television cabinet. Avoid abrasive cleaners or solvents.
- **Ventilation:** Ensure that the ventilation openings on the television are not blocked to prevent overheating.
- **Power Disconnection:** Always unplug the television from the power outlet before cleaning or performing any maintenance.

4. Troubleshooting

If you encounter issues with your television, refer to the following common problems and solutions before contacting customer support.

- **No Power:**
  - Check if the power cord is securely connected to both the television and the wall outlet.
  - Ensure the integrated on/off switch is in the 'on' position.
  - Verify the wall outlet is functioning by plugging in another device.
- **No Picture/Sound:**
  - Confirm the correct input source is selected (e.g., HDMI 1, AV).
  - Check all cable connections between the television and external devices.
  - If using an antenna or cable, ensure it is properly connected and tuned.
- **Remote Control Not Working:**
  - Replace the batteries in the remote control.
  - Ensure there are no obstructions between the remote and the television's sensor.
- **Poor Picture Quality:**
  - Adjust picture settings (brightness, contrast, sharpness) in the television menu.
  - Check the quality of the input signal or source device.

If the problem persists after attempting these solutions, please refer to the support section.

5. Technical Specifications

Feature	Specification
Brand	Metz
Model Name	Aurus 42 3D Media Twin R
Model Number	4003915678919
Display Size	42 inches (106.7 cm)

Feature	Specification
Display Technology	OLED
Resolution	1920 x 1080 Pixels (Full HD)
3D Support	Yes
Aspect Ratio	16:9
Brightness	400 cd/m²
Dynamic Contrast Ratio	1,000,000:1
Response Time	5 ms
Viewing Angle (H/V)	178° / 178°
Audio System	Bass reflex system, mecaSoundpro
RMS Power Output	40 W (4 speakers)
Equalizer	7-band
Digital Tuner	DVB-C, DVB-S2, DVB-T
HDMI Ports	4
USB 2.0 Ports	2
DVI-I Ports	1
Component Video (YPbPr/YCbCr) Input	1
AV Input	1
Ethernet	Yes
Wi-Fi	No
Common Interface Plus (CI+)	Yes
Hard Drive Capacity	750 GB
Power Consumption (Operating)	75 W
Power Consumption (Standby)	0.17 W
Energy Efficiency Class	A
AC Input Voltage	220 - 240 V
AC Input Frequency	50 Hz
Dimensions (W x D x H)	104.6 x 10.2 x 68.2 cm
Weight (without stand)	27.1 kg
Weight (with stand)	31 kg
Mounting Type	Table stand

Feature	Specification
Special Features	24p, Parental Control, EPG, Timeshift Recording, Teletext, Sleep Timer

6. Warranty and Support

For warranty information, please refer to the documentation provided with your purchase or contact your retailer. Metz products are designed for reliability and performance.

If you require technical assistance or have questions not covered in this manual, please contact Metz customer support or your authorized service center. Keep your purchase receipt and model information readily available when seeking support.

For the most up-to-date support information, visit the official Metz website.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B00ATC8DZI

More documents and user manuals: **https://manuals.plus/**