

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [VTech](#) /

› [VTECH Communications CS6729-2 2 Handset Answering System with Caller ID/Call Waiting User Manual](#)

VTech CS6729-2

VTECH Communications CS6729-2

2 HANDSET ANSWERING SYSTEM WITH CALLER ID/CALL WAITING USER MANUAL

INTRODUCTION

This user manual provides comprehensive instructions for the VTECH Communications CS6729-2 2 Handset Answering System. It covers setup, operation, maintenance, and troubleshooting to ensure optimal performance of your new telephone system. Please read this manual thoroughly before using your phone.

SETUP AND INSTALLATION

Package Contents

Ensure all items are present in your package:

- Cordless Handsets (2)
- Base Unit with Digital Answering System
- AC Power Adapter for Base Unit
- Telephone Line Cord
- Rechargeable Batteries (4 AAA batteries required, included)
- Wall Mount Bracket

Battery Installation

Before initial use, install the included AAA batteries into each cordless handset. Open the battery compartment cover on the back of the handset, insert the batteries according to the polarity markings, and close the cover. Place the handset on the base unit or charger to charge for at least 16 hours before first use.

Connecting the Base Unit

Connect the small end of the AC power adapter to the power jack on the back of the telephone base. Plug the large end of the AC power adapter into a wall outlet not controlled by a wall switch. Connect one end of the telephone line cord to the telephone jack on the back of the telephone base. Plug the other end of the telephone line cord into a telephone wall jack.



The VTech CS6729-2 cordless phone system, showing the main base unit with one handset and a secondary charging cradle with the second handset. The base unit features an integrated answering machine with controls.



A closer view of the VTech CS6729-2 base unit and one cordless handset. The base unit displays a red LED for the message counter and has buttons for answering machine control, while the handset features a backlit display and keypad.

OPERATING INSTRUCTIONS

Making and Receiving Calls

To make a call, press **TALK/FLASH** or any dial pad key, then dial the number. To receive a call, press **TALK/FLASH** when the phone rings. To end a call, press **OFF/CANCEL** or place the handset back on the base unit/charger.

Answering System Features

The integrated digital answering system can record up to 14 minutes of messages. You can retrieve messages from any handset or remotely. The voicemail waiting indicator will notify you of new messages. Messages are time and date stamped for easy reference.

Caller ID/Call Waiting

The phone displays the caller's name and number (if available) before you answer. If you have Call Waiting service, the phone will alert you to an incoming call while you are on another call.

Phonebook Directory

Store up to 50 names and numbers in the phonebook directory for quick dialing. Refer to the handset menu for instructions on adding, editing, and deleting entries.

Intercom

Use the intercom feature to communicate between handsets. This system supports up to 5 handsets (additional handsets sold separately).

Redial

The phone stores the last 10 dialed numbers. Press **REDIAL/PAUSE** to access and redial these numbers.

Volume Control

Adjust the earpiece and speakerphone volume during a call using the **VOLUME** buttons on the side of the handset.

Mute

Press the **MUTE/DELETE** button during a call to mute your microphone. The other party will not hear you, but you can still hear them. Press again to unmute.

Conference Calls

You can set up a 3-way conference call between an outside line and up to two cordless handsets.

Trilingual Prompts

The system offers trilingual prompts, allowing you to choose between English, Spanish, or French for voice announcements and menu options.

MAINTENANCE

Cleaning

Clean the phone and base unit with a soft, damp cloth. Do not use cleaning sprays or harsh chemicals. Avoid getting moisture in any openings.

Battery Care

To maintain optimal battery life, fully charge the handsets regularly. If the phone will not be used for an extended period, remove the batteries to prevent leakage.

TROUBLESHOOTING

If you experience issues with your phone system, try the following solutions:

Problem	Solution
No dial tone	Ensure the power adapter and telephone line cord are securely plugged into the base unit and wall outlets. Check if the phone line is active.
Cannot make/receive calls	Check battery charge level. Ensure the handset is within range of the base unit. Verify the telephone line connection.

Problem	Solution
Answering system not recording messages	Ensure the answering system is turned ON. Check if the memory is full; delete old messages if necessary.
Poor sound quality	Move closer to the base unit. Check for interference from other electronic devices.
Handset not charging	Ensure the handset is properly seated in the charging cradle. Clean the charging contacts on both the handset and cradle.

SPECIFICATIONS



- **Model:** CS6729-2
- **Technology:** DECT 6.0 Digital
- **Handsets:** 2 (expandable up to 5)
- **Answering System:** Digital, 14 minutes recording time
- **Phonebook Capacity:** 50 names and numbers
- **Redial Memory:** Last 10 numbers
- **Batteries:** 4 AAA rechargeable batteries (included)
- **Product Dimensions:** 1 x 3.2 x 6.9 inches (handset)
- **Item Weight:** 1.3 pounds
- **Color:** Gray
- **Power Source:** Corded Electric





WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the warranty card included with your product or visit the official VTech website. Keep your purchase receipt as proof of purchase for warranty claims.



Related Documents - CS6729-2

 <p>CS6729 CS6729-2 CS6729-2i CS6729-3 CS6729-4 CS6729-4D CS6729-5 DECT 6.0 cordless telephones</p> <p>Go to www.vtechphones.com to register your product and access VTech product news.</p> <p>Learn the art of cordless by going and subscribe our digital channel</p> <p>vtech User's manual</p>	<p>VTech CS6729 Series DECT 6.0 Cordless Telephone User Manual</p> <p>Comprehensive user manual for the VTech CS6729 series DECT 6.0 cordless telephones, covering installation, operation, features, safety instructions, and troubleshooting.</p>
<p>VG 208 208-2</p>  <p>vtech User's manual</p>	<p>VTech VG208 / VG208-2 User Manual: Features, Safety, and Operation Guide</p> <p>Comprehensive user manual for the VTech VG208 and VG208-2 DECT 6.0 cordless phones. Learn about installation, operation, features like answering machine, caller ID, call blocking, intercom, safety instructions, and technical specifications.</p>

	<p>VTech LS5145 User's Manual</p> <p>Comprehensive user's manual for the VTech LS5145 cordless telephone system. Features include Bluetooth 5.8 wireless technology, answering system, caller ID integration, and support for multiple handsets. Provides detailed instructions for setup, operation, and troubleshooting.</p>
	<p>VTech CD1113 Cordless Phone User Manual</p> <p>Comprehensive user manual for the VTech CD1113 cordless phone, detailing installation, operation, features such as Caller ID and speed dial, troubleshooting tips, safety instructions, and warranty information.</p>
	<p>VTech DS6421 Series Cordless Phone User Manual with Bluetooth & Answering System</p> <p>Comprehensive user manual for the VTech DS6421 Series cordless telephone system, detailing setup, features like Bluetooth connectivity, answering system operation, and troubleshooting for models DS6421-2, DS6421-3, and DS6421-4.</p>
	<p>VTech IS8121/IS8122 Series DECT 6.0 Cordless Phone with Answering System & Smart Call Blocker User Manual</p> <p>User manual for the VTech IS8121/IS8122 series DECT 6.0 cordless telephone and answering system, featuring Smart Call Blocker technology to filter unwanted calls, Bluetooth connectivity, and caller ID. Learn how to set up and use your advanced home phone.</p>