

[Manuals.plus](#) /

> [ALLISTER](#) /

> ALLISTER Garage Door Opener Trolley Carrier Kit 113980 TRTAZ11A Instruction Manual

## ALLISTER 113980 / TRTAZ11A

# ALLISTER Garage Door Opener Trolley Carrier Kit 113980 TRTAZ11A Instruction Manual

Model: 113980 / TRTAZ11A

## INTRODUCTION

---

This manual provides essential instructions for the installation, operation, and maintenance of your ALLISTER Garage Door Opener Trolley Carrier Kit, Model 113980 / TRTAZ11A. Please read these instructions thoroughly before proceeding with installation or use to ensure proper function and safety.

## PRODUCT OVERVIEW

---



This image displays the complete ALLISTER 113980 Trolley Carrier Kit. On the left is the main trolley assembly, a metal mechanism designed to connect the garage door to the opener's chain or belt. On the right, from top to bottom, are a red emergency release cord, a red emergency release handle with a 'NOTICE' label, and the carrier component which attaches to the trolley assembly.

The ALLISTER 113980 Trolley Carrier Kit is a replacement component designed for various ALLISTER, Allstar, and Pulsar garage door openers. It facilitates the connection between the garage door and the opener's drive

mechanism, allowing for smooth operation of the garage door.

## COMPATIBILITY

---

This trolley carrier kit is compatible with the following garage door opener models:

- Allstar, Allister, and Pulsar garage door openers.
- Specific models: ARD-II A, Access 200/250, Access 2000/2500, Access 3000/3500 (for openers built prior to September 1993).
- Allister Century Series 310/510/710.
- MVP garage door openers.

## SAFETY INFORMATION

---

Always prioritize safety when working with garage door openers. Garage doors and openers contain powerful springs and motors that can cause serious injury or death if not handled correctly. It is recommended that installation and repairs be performed by qualified personnel.

- **Disconnect Power:** Always disconnect the garage door opener from its power source before performing any installation, maintenance, or repair.
- **Spring Tension:** Never attempt to adjust or repair garage door springs. These are under extreme tension and can cause severe injury.
- **Moving Parts:** Keep hands and clothing clear of all moving parts of the garage door and opener.
- **Emergency Release:** Understand how to use the emergency release handle (red cord) to manually open or close the garage door in case of power failure or malfunction.

## INSTALLATION / SETUP

---

This section outlines the general steps for replacing an existing trolley carrier. Specific procedures may vary based on your garage door opener model. Refer to your original opener's manual for detailed instructions.

### 1. Prepare for Installation:

- Ensure the garage door is fully closed.
- Disconnect power to the garage door opener at the outlet or circuit breaker.
- Pull the emergency release cord to disengage the existing trolley from the garage door.

### 2. Remove Old Trolley:

- Carefully remove the linkage and chain (or belt) from the old trolley. This may involve loosening nuts or bolts, or detaching clips.
- Slide the old trolley off the rail.

### 3. Install New Trolley:

- Slide the new ALLISTER 113980 trolley onto the rail, ensuring it faces the correct direction (refer to your opener's manual for orientation).
- Attach the chain or belt to the new trolley, ensuring proper tension as specified by your opener's manual.
- Connect the garage door to the new trolley using the appropriate linkage.

### 4. Test Operation:

- Reconnect power to the garage door opener.
- Perform a test cycle of the garage door, observing its movement for any obstructions or unusual noises.

- Ensure safety reversal systems are functioning correctly.

## OPERATING INSTRUCTIONS

---

The trolley carrier kit itself does not have direct operating controls. Its function is integral to the garage door opener system. Operation of the garage door is controlled by your existing garage door opener's remote, wall console, or other access devices.

**Emergency Release:** In case of power outage or opener malfunction, pull the red emergency release cord downward to disengage the trolley from the garage door. This allows for manual opening and closing of the door. To re-engage, push the trolley release lever back into position and operate the opener; the trolley will automatically re-engage when it contacts the door arm.

## MAINTENANCE

---

Regular maintenance ensures the longevity and reliable operation of your garage door opener system, including the trolley carrier.

- **Visual Inspection:** Periodically inspect the trolley and rail for signs of wear, damage, or obstructions. Ensure all connections are secure.
- **Lubrication:** Consult your garage door opener's manual for recommended lubrication schedules and types for the rail and moving parts. Do not over-lubricate.
- **Cleanliness:** Keep the rail and trolley free from dirt, debris, and excessive grease.

## TROUBLESHOOTING

---

If you experience issues after installing the new trolley, consider the following:

- **Door Not Moving:** Ensure the trolley is properly engaged with the garage door. Check if the emergency release cord has been pulled. Verify power to the opener.
- **Unusual Noises:** Inspect the trolley and rail for obstructions or loose components. Check chain/belt tension.
- **Door Reverses:** This is often related to safety sensor alignment or force settings on the opener, not typically the trolley itself. Refer to your opener's manual.
- **Trolley Stuck:** Disconnect power and manually inspect the rail for bends or obstructions that might impede trolley movement.

For complex issues, consult a qualified garage door technician.

## SPECIFICATIONS

---

Attribute	Detail
Brand	ALLISTER
Manufacturer	Linear
Part Number	113980
Item Model Number	TRTAZ11A
Item Package Quantity	1
UPC	640213237130
ASIN	B00F65HVRV

## WARRANTY INFORMATION

---

Specific warranty details for the ALLISTER 113980 Trolley Carrier Kit are typically provided by the manufacturer or seller at the time of purchase. Please retain your proof of purchase for any warranty claims. For detailed warranty terms, refer to the documentation included with your product or contact the manufacturer directly.

## SUPPORT

---

For technical assistance, troubleshooting, or replacement parts, please contact the manufacturer, Linear, or your authorized ALLISTER dealer. When contacting support, please have your product model number (113980 / TRTAZ11A) and purchase information readily available.

Manufacturer: Linear