

Cellet BKP200

Cellet Portable Bluetooth Wireless Keyboard BKP200 User Manual

Model: BKP200 | Brand: Cellet

1. INTRODUCTION

The Cellet Portable Bluetooth Wireless Keyboard BKP200 offers a convenient and functional solution for typing on the go. Its foldable design and QWERTY layout with low-profile keys provide an efficient typing experience. The built-in rechargeable lithium battery ensures extended use, making it ideal for smartphones, tablets, laptops, and other Bluetooth-enabled devices.

What's in the Box

- Wireless foldable keyboard
- Keyboard case (doubles as a phone holder stand)
- Micro USB charging cable
- User manual



Image: The Cellet Portable Bluetooth Wireless Keyboard, shown unfolded, alongside its protective case which functions as a phone/tablet stand, and a micro USB charging cable.

2. IMPORTANT SAFETY INSTRUCTIONS

Before using this product, please read all instructions carefully and retain them for future reference. Adherence to these guidelines ensures safe operation and prevents damage.

1. This product may be used by children and individuals with physical, sensory, or mental disabilities, or those lacking experience and knowledge, provided they receive proper supervision or instruction regarding safe use and understanding of associated hazards.
2. Cleaning and maintenance must not be performed by children without supervision.
3. Children should be supervised to ensure they do not play with the appliance.
4. Use the product only for its intended purpose.
5. For indoor use only. Do not expose the product to water, excessive moisture, or snow.
6. Do not place the product in or near flammable, explosive, or hazardous objects.
7. Do not operate the product with a damaged cord or plug.
8. Do not use the product if it has been damaged in any way.
9. Do not disassemble the product. Disassembly may result in safety hazards.
10. Avoid throwing or shaking the product.

3. SETUP

Initial Charging

Before first use, fully charge the keyboard for approximately 1.5 to 2 hours using the provided Micro USB charging cable. The charging indicator light will glow red during charging and turn off once fully charged. If the battery is low, the Bluetooth status light will flash.

Bluetooth Pairing Steps

1. **Step 1:** Unfold the keyboard. The Bluetooth status indicator light will illuminate for 3 seconds and then turn off.
2. **Step 2:** Press the **Fn + C** buttons simultaneously. The Bluetooth indicator light will begin blinking, indicating it is in pairing mode.
3. **Step 3:** On your device (smartphone, tablet, etc.), activate Bluetooth and search for available devices. Select "Cellet BKP200 Keyboard" from the list to connect.
4. **Step 4:** Once successfully connected, the Bluetooth indicator light on the keyboard will turn off.



Image: The Cellet foldable keyboard displayed with a tablet and smartphone, illustrating its universal compatibility.

4. OPERATING INSTRUCTIONS

Operating System Selection

To optimize keyboard functionality for your device, select the correct operating system:

- For Android devices: Press and hold **Fn + Q**.
- For Windows devices: Press and hold **Fn + W**.
- For iOS devices: Press and hold **Fn + E**.

Shortcut Key Functions

To use the shortcut keys, press and hold the **Fn** key while simultaneously pressing the desired shortcut key.

Common Shortcut Keys

Function	Key Combination	Notes
Previous Track	Fn + 1	
Volume Down	Fn + 2	
Volume Up	Fn + 3	
Play/Pause	Fn + 4	
Switching Language	Fn + 5	
Search	Fn + 6	
Copy	Fn + 7	
Cut	Fn + 8	
Select All	Fn + 9	

System-Specific Functions:

Android Systems	Function
PgUp	Last page
PgDn	Next page

iOS Systems	Function
Home	Home
PgUp	Cursor to the top
PgDn	Cursor to the bottom

Windows Systems	Function
Web browser	Open web browser
ESC	Escape

Windows Systems	Function
PgUp	Last page
PgDn	Next page

SMARTPHONE/TABLET STAND

KEYBOARD CASE FUNCTIONS
AS A SMARTPHONE OR
TABLET STAND



Image: The keyboard case is shown transforming into a stand, holding both a smartphone and a tablet in landscape orientation for convenient viewing while typing.

5. MAINTENANCE

Proper care and maintenance will extend the life of your Cellet keyboard.

1. Clean the keyboard with a soft cloth dampened with water or alcohol.
2. Keep the keyboard away from sharp objects.
3. Do not place heavy objects on the keyboard.
4. Do not microwave the keyboard.
5. Do not force or distort the keyboard.
6. Keep away from any oil, chemicals, or other organic liquids.

6. TROUBLESHOOTING

If you encounter issues with your keyboard, consider the following:

- **Keyboard not pairing:** Ensure the keyboard is fully charged and in pairing mode (Bluetooth indicator blinking). Check your device's Bluetooth settings to ensure it's discoverable and try re-scanning for devices.
- **Keys not responding:** Verify the keyboard is connected to your device. If connected, try restarting both the keyboard and your device. Ensure no debris is lodged under the keys.
- **Intermittent connection:** Ensure the keyboard is within the 10-meter operating range of your device and there are no significant obstructions. Other wireless devices might cause interference.
- **Incorrect characters typed:** Confirm that you have selected the correct operating system for your device (Fn + Q for Android, Fn + W for Windows, Fn + E for iOS).
- **Battery not charging:** Check the Micro USB cable and charging port for damage. Try using a different charging cable or power source.

If problems persist, refer to the Cellet support website or contact customer service for further assistance.

7. SPECIFICATIONS

Detailed technical specifications for the Cellet BKP200 Portable Bluetooth Wireless Keyboard:

Feature	Specification
Bluetooth Version	5.1
Interface	USB-C (for charging)
Operating Distance	Up to 10 meters
Modulation System	GFSK
Operating Voltage	3.0-4.2V
Operating Current	<3.0mA
Standby Current	<0.3mA
Sleep Current	<0.1mA
Charging Current	<200mA
Standby Time	Around 100 days
Charge Time	<2 hours
Lithium Battery Capacity	110mAh
Uninterrupted Working Time	>40 hours
Lithium Battery Life	3 years
Lithium Battery Dimensions	30 x 15 x 23mm
Key Force	50-80g

Feature	Specification
Key Life	3 million strokes
Working Temperature	-10 to +55 °C
Item Weight	7.5 ounces
Product Dimensions (Folded)	5.75 x 3.5 x 0.75 inches
Product Dimensions (Unfolded)	11.5 x 3.3 x 0.27 inches (approximate, derived from image)
Color	Black
Compatible Operating Systems	Android, iOS, Windows

ULTRA COMPACT SIZE

Full 5 Row Keyboard with 66 keys



Closed Size: 5.7" x 3.3" x 0.55"



Open Size: 11.5" x 3.3" x 0.27"

Image: The Cellet keyboard in both its closed, compact state and its unfolded, full-size state, with dimensions indicating its portability and functional size.

8. WARRANTY AND SUPPORT

For warranty information or technical support, please visit the official Cellet website or contact their customer service department. Keep your purchase receipt for warranty claims.

Environmentally Friendly Disposal

To dispose of the product responsibly, follow these guidelines:

1. Carefully pry up the plastic top to remove it completely. This action will likely render the keyboard unusable.
2. Turn the top over and remove any tape securing the battery.
3. Separate the battery from the circuit board.
4. Dispose of the battery according to local regulations and laws. Recycle remaining keyboard parts where possible.