

**BRINKS 675-80002**

## **BRINKS 80mm 4-Dial Resettable Combination Lock Box**

Model: 675-80002

### **1. INTRODUCTION**

The BRINKS 80mm 4-Dial Resettable Combination Lock Box is a robust and secure solution for storing keys or key cards, providing convenient access for authorized individuals. Its durable construction and resettable combination mechanism make it ideal for various applications, including granting access to cleaners, realtors, contractors, or family members.



Image 1.1: Front view of the BRINKS 80mm 4-Dial Resettable Combination Lock Box, showing the combination dials and the BRINKS logo.

## 2. FEATURES

This lock box is engineered with features designed for security and ease of use:

- **80mm Aluminum Body:** Provides high security and durability.
- **4-Dial Resettable Combination:** Allows for easy setting, resetting, and personalization of your access code.
- **Key Capacity:** Accommodates up to 10 keys or key cards.
- **Wall Mountable:** Designed for easy installation on any solid surface.
- **Versatile Usage:** Suitable for both indoor and outdoor applications, including front doors, backdoors, backyards, or side gates.



Image 2.1: Diagram highlighting key features: 80mm body, capacity for 10+ keys/cards, 4-dial resettable combination, and wall mountable design.

# Best Used For

✓ Backyards



✓ Side Gates



Image 2.2: Examples of ideal usage locations for the lock box, such as backyards and side gates.

## 3. SETUP

### 3.1 Mounting the Lock Box

The BRINKS lock box is designed for easy mounting on any solid surface. Ensure the chosen location is secure and provides convenient access while remaining discreet if desired.

1. Select a suitable mounting surface (e.g., wall, post).
2. Mark the drilling points using the lock box as a template.
3. Drill pilot holes appropriate for your mounting hardware (not included).
4. Secure the lock box to the surface using screws or other suitable fasteners.



Image 3.1: Rear view of the lock box, illustrating the design for wall mounting.

### 3.2 Setting Your Combination

The lock box comes with a factory-set combination, typically 0-0-0-0. You can easily reset this to a personalized code.

1. Open the lock box using the current combination (factory default or previous setting).
2. Locate the reset lever or button inside the lock box, usually on the back of the door or inside the compartment.
3. Move the reset lever to the 'SET' position (or press the reset button). Refer to the specific markings inside your lock box.
4. While the lever is in the 'SET' position, rotate the dials to your desired new 4-digit combination. Choose a memorable but secure code.
5. Return the reset lever to the 'LOCK' position (or release the reset button).
6. Scramble the dials to lock the box and test your new combination to ensure it works correctly before closing the door.





Image 3.2: A hand adjusting the combination dials on the lock box.



Image 3.3: Detailed view of a hand manipulating the combination dials during the setting process.

## 4. OPERATING INSTRUCTIONS

### 4.1 Opening the Lock Box

1. Rotate the four dials to align with your preset combination.
2. Once the correct combination is entered, pull down the cover to reveal the key compartment.

### 4.2 Storing and Retrieving Keys

1. Place keys or key cards inside the compartment. Ensure they fit without obstructing the closing mechanism.
2. To close, push the cover back up until it clicks securely into place.
3. Scramble the dials to lock the box and secure its contents.





Image 4.1: The lock box in an open position, showing a key placed inside the compartment.



Image 4.2: A hand demonstrating the action of inserting a key into the open lock box.

## 5. MAINTENANCE

To ensure the longevity and smooth operation of your BRINKS lock box, consider the following maintenance tips:

- **Cleaning:** Periodically wipe the exterior with a soft, damp cloth to remove dirt and grime. Avoid abrasive cleaners.
- **Lubrication:** If the dials become stiff, apply a small amount of silicone-based lubricant to the moving parts of the combination mechanism. Do not use oil-based lubricants as they can attract dust.
- **Inspection:** Regularly check for any signs of wear, damage, or corrosion, especially if installed outdoors.

## 6. TROUBLESHOOTING

If you encounter issues with your lock box, try the following solutions:

- **Difficulty Opening:**
  - Ensure the combination is precisely aligned with the indicator marks.
  - Verify you are using the correct combination.
  - Check for any debris obstructing the opening mechanism.
- **Dials are Stiff:**
  - Apply a small amount of silicone lubricant to the dials.
  - Clean any accumulated dirt around the dials.
- **Forgotten Combination:**
  - Unfortunately, if the combination is forgotten and the box is locked, there is no master key or override. You may need to contact BRINKS customer support for further assistance or consider professional locksmith services.

## 7. SPECIFICATIONS

Feature	Detail
---------	--------

Brand	BRINKS
Model Name	Lock Box
Item Model Number	675-80002
Lock Type	Combination Lock
Special Feature	Resettable
Material	Metal
Color	Black
Finish Type	Powder Coated
Item Dimensions (L x W x H)	1.75 x 3.13 x 6 inches
Item Weight	1 Pounds
Mounting Type	Wall Mount
UPC	039208986571

## 8. WARRANTY INFORMATION

The BRINKS 80mm 4-Dial Resettable Combination Lock Box includes a **Lifetime Warranty**. This warranty covers defects in material and workmanship under normal use. For specific terms and conditions, please refer to the warranty documentation provided with your purchase or contact BRINKS customer support.

## 9. SUPPORT

For further assistance, technical support, or warranty claims, please contact BRINKS customer service. You can typically find contact information on the BRINKS official website or through the retailer where you purchased the product.

Visit the official BRINKS Store for more information:[BRINKS Store on Amazon](#)

© 2025 BRINKS. All rights reserved.



## PORTABLE SECURITY



MOUNTAIN security

### [\[pdf\]](#) Declaration of Conformity Catalog

84000 00013 REVE.indd Brinks Padlocks Home 1617953 BRINKS Catalog assets unilogcorp 187 ITEM DOC |||

PORTABLE SECURITY Portable Security Catalog Contents AS A TRUSTED BRAND IN SECURITY PRODUCTS, THE B ... Strength 3500 lbs. KEY BLANKS KB Axxess ILCO N/A N/A N/A Pack Item Number Description 1 pack **675-80002-4** KEY SAFE WALL MOUNT Case Pack QTY UPC Code 4 039208986571 Cut Pull Strength Stren...

lang:en score:17 filesize: 24.19 M page\_count: 24 document date: 2019-05-06