

Manuals.plus /

› Feiss /

› Feiss FM256GBZ Fusion Glass Flush Mount Ceiling Lighting User Manual

Feiss FM256GBZ

Feiss Fusion Glass Flush Mount Ceiling Lighting User Manual

Model: FM256GBZ

1. INTRODUCTION

This manual provides detailed instructions for the installation, operation, and maintenance of your Feiss Fusion Glass Flush Mount Ceiling Lighting fixture. The Feiss Fusion two-light flush mount fixture, featuring a Grecian Bronze finish, is designed to provide ample illumination while enhancing the aesthetic appeal of your space. Its design incorporates elements from both Asian and Arts & Crafts styles, creating a distinctive look with vertical and horizontal linear banding that contrasts beautifully against the Amber Ribbed glass shades and diffuser.



Figure 1: Feiss Fusion Glass Flush Mount Ceiling Lighting (Model FM256GBZ)

2. SAFETY INFORMATION

Please read all instructions carefully before beginning installation. Failure to do so may result in electric shock, fire, or other injuries that could be hazardous or even fatal. Always consult a qualified electrician if you are unsure about any part

of the installation process.

- Always disconnect power at the main circuit breaker before installation or servicing.
- Ensure all electrical connections comply with local codes and ordinances, as well as the National Electric Code (NEC).
- This fixture is UL Approved for Indoor Locations. Do not install in damp or wet locations.
- Use only the specified bulb type and wattage to avoid overheating and potential fire hazards.
- Handle glass components with care to prevent breakage.

3. PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation.

- Feiss Fusion Flush Mount Fixture (Model FM256GBZ)
- Ribbed Amber Glass Shade
- Diffuser
- Mounting Hardware
- 8" Black and White Wire
- Instruction Manual

4. SETUP AND INSTALLATION

Installation should be performed by a qualified electrician or a competent individual with knowledge of electrical wiring.

4.1 Tools Required (Not Included)

- Phillips Head Screwdriver
- Flathead Screwdriver
- Wire Strippers
- Electrical Tape
- Safety Glasses

4.2 Installation Steps

1. **Turn Off Power:** Locate the circuit breaker that supplies power to the light fixture location and turn it off. Verify power is off using a voltage tester.
2. **Prepare Wiring:** If replacing an existing fixture, carefully remove it. Pull the electrical wires from the junction box.
3. **Attach Mounting Bracket:** Secure the fixture's mounting bracket to the junction box using the provided screws. Ensure it is firmly attached.
4. **Make Electrical Connections:**
 - Connect the black wire from the fixture to the black (hot) wire from the junction box.
 - Connect the white wire from the fixture to the white (neutral) wire from the junction box.
 - Connect the bare copper or green ground wire from the fixture to the ground wire from the junction box (or to the green ground screw on the mounting bracket).
 - Secure all connections with wire nuts and wrap with electrical tape for added security.
5. **Mount Fixture:** Carefully push the wired connections into the junction box. Align the fixture base with the mounting bracket and secure it using the provided screws.

6. **Install Bulbs:** Insert two A19 style bulbs (not included) into the E26 medium base light sockets. Do not exceed 60 watts per bulb.
7. **Attach Glass Shade and Diffuser:** Carefully place the ribbed amber glass shade and diffuser onto the fixture. Secure them using the thumb screws or retaining clips as per the design.
8. **Restore Power:** Turn the power back on at the main circuit breaker.



Figure 2: Example of Feiss Fusion Glass Flush Mount Ceiling Lighting in a room setting.

5. OPERATING INSTRUCTIONS

The Feiss Fusion Flush Mount Ceiling Lighting operates like a standard ceiling light fixture. Once installed and powered, it can be controlled via a wall switch.

- **Bulb Compatibility:** This fixture is compatible with Incandescent, CFL, Halogen, or LED bulbs with an E26 medium base.
- **Dimming Functionality:** The fixture supports full range dimming when used with dimmable bulbs and a compatible dimmer switch (sold separately).
- **Wattage:** The maximum wattage for this fixture is 120 total watts (2 x 60 Watt Max A19 Style Bulbs).

6. MAINTENANCE

Regular cleaning will help maintain the appearance and performance of your lighting fixture.

- **Cleaning the Shade:** Use a clean, soft, dry cloth to wipe the glass shade. If necessary, you may use a white cloth dampened with a mild solution of soapy water to gently wash the shade. Rinse thoroughly with a white cloth dipped in clean water, then dry completely.
- **Cleaning the Fixture Body:** Wipe the metal parts with a soft, dry cloth. Avoid using abrasive cleaners or solvents, as they may damage the finish.
- **Bulb Replacement:** Always turn off power at the circuit breaker before replacing bulbs. Allow bulbs to cool completely before touching them.

7. TROUBLESHOOTING

If you encounter issues with your lighting fixture, refer to the following common problems and solutions.

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture. Loose wire connections. Faulty bulb.	Check circuit breaker and wall switch. Turn off power, check all wire connections. Replace bulb with a known good one.
Light flickers or dims unexpectedly.	Loose bulb. Incorrect dimmer switch for bulb type. Loose wiring.	Tighten bulb. Ensure dimmer switch is compatible with installed bulbs (especially LEDs). Turn off power, check all wire connections.
Glass shade appears yellow or reduces light.	Natural characteristic of amber ribbed glass. Bulb color temperature.	This is an inherent property of the amber glass. Consider using bulbs with a higher Kelvin (cooler) color temperature if a whiter light is desired.

8. SPECIFICATIONS

Feature	Detail
Model Number	FM256GBZ
Brand	Feiss
Dimensions (H x W)	4.5" Height x 11.5" Width
Item Weight	5.3 lbs
Finish	Grecian Bronze
Shade Material	Ribbed Amber Glass
Number of Lights	2
Light Socket Type	E26 Medium Base
Max Wattage per Bulb	60 Watt (A19 Style)
Total Max Wattage	120 Watts
Voltage	120 Volts
Power Source	Corded Electric
Installation Type	Flush Mount
Indoor/Outdoor Usage	Indoor
Certifications	UL Approved for Indoor Locations

9. WARRANTY AND SUPPORT

This Feiss lighting fixture comes with a **1-year warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use.

For technical support, replacement parts, or warranty claims, please contact Feiss customer service. Refer to the Feiss official website or your purchase documentation for the most current contact information.

Online Resources: For additional information and product details, you may visit the official Feiss store on AmazonFeiss Store

