

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Elk Home](#) /

› [Elk Home 66894/6 Laboratory 6-Light Chandelier Instruction Manual](#)

Elk Home 66894/6

Elk Home 66894/6 Laboratory 6-Light Chandelier Instruction Manual

Model: 66894/6

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Elk Home 66894/6 Laboratory 6-Light Chandelier. Please read all instructions carefully before beginning installation and retain this manual for future reference.

SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the fuse box or circuit breaker before installation or servicing. Consult a qualified electrician if you are unsure about the installation process.

- Ensure the electrical supply to the fixture is disconnected before installation, maintenance, or bulb replacement.
- All wiring connections must be in accordance with local and national electrical codes.
- Do not exceed the maximum wattage specified for the bulbs.
- This fixture is designed for indoor use only.
- Handle glass components with care to prevent breakage.

PACKAGE CONTENTS

Verify that all components are present before beginning installation.

- Chandelier fixture body
- Glass shades (6 pieces)
- Mounting hardware kit
- Instruction manual



Image: The Elk Home 66894/6 Laboratory 6-Light Chandelier in Weathered Zinc finish, showcasing its six light sources and overall design.

SETUP AND INSTALLATION

1. Prepare for Installation:

- Turn off the main power supply at the circuit breaker or fuse box.
- Ensure the mounting surface is structurally sound to support the weight of the fixture.
- Gather necessary tools: screwdriver, wire strippers, electrical tape, safety glasses.

2. Mounting the Fixture:

- Attach the mounting bracket to the junction box using the provided screws.
- Adjust the chain length to your desired hanging height. Secure the chain to the canopy and the fixture loop.
- Carefully lift the fixture and thread the wires through the center hole of the mounting bracket.

3. Wiring Connections:

- Connect the fixture's black wire to the house's black (live) wire using a wire connector.
- Connect the fixture's white wire to the house's white (neutral) wire using a wire connector.
- Connect the fixture's ground wire to the house's ground wire (bare copper or green) and to the mounting bracket's ground screw.
- Ensure all connections are secure and insulated with electrical tape if necessary.

4. Securing the Canopy:

- Tuck all wires neatly into the junction box.
- Push the canopy up against the ceiling, covering the junction box and mounting bracket.
- Secure the canopy with the provided screws or decorative nuts.

5. Installing Bulbs and Shades:

- Screw in six E26 base bulbs (not included) into the sockets. Do not exceed 60 watts per bulb.
- Carefully attach the glass shades to each light socket according to the fixture design.

6. Final Step:

- Restore power at the circuit breaker or fuse box.
- Test the fixture to ensure proper operation.

OPERATING INSTRUCTIONS

The Elk Home 66894/6 Chandelier is a hardwired fixture operated by a standard wall switch (not included). Simply toggle the wall switch to turn the light fixture on or off. If a dimmer switch is installed, ensure it is compatible with the type of bulbs used.

MAINTENANCE

- **Cleaning:** Always disconnect power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners or solvents, as they may damage the finish. Clean glass shades with a mild glass cleaner and a soft cloth.
- **Bulb Replacement:** Disconnect power before replacing bulbs. Allow bulbs to cool completely before touching. Replace with E26 base bulbs, not exceeding 60 watts per bulb.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Light does not turn on.	No power to the fixture. Loose wiring connection. Faulty bulb.	Check circuit breaker/fuse. Verify all wiring connections are secure (power off). Replace bulb.
Light flickers.	Loose bulb. Incompatible dimmer switch. Loose wiring connection.	Tighten bulb. Ensure dimmer is compatible with bulbs. Check wiring connections (power off).

SPECIFICATIONS

- **Model Number:** 66894/6
- **Dimensions:** 20"L x 20"W x 28"H
- **Material:** Metal (Weathered Zinc finish), Glass shades
- **Number of Lights:** 6
- **Bulb Base:** E26
- **Max Wattage per Bulb:** 60 watts
- **Voltage:** 120 Volts
- **Installation Type:** Hardwired, Ceiling Mounted
- **Indoor/Outdoor Usage:** Indoor use only
- **Item Weight:** 8 Pounds

WARRANTY

This Elk Home fixture comes with a **1-year limited warranty** from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accidents, misuse, abuse, or unauthorized modifications. For warranty claims, please contact Elk Home customer support.

CUSTOMER SUPPORT

For technical assistance, missing parts, or warranty inquiries, please visit the official Elk Home website or contact their customer service department. Please have your model number (66894/6) and proof of purchase ready when contacting support.