

AMS W9463

AMS Uhrenfabrik Quartz Wall Clock

MODEL W9463 USER MANUAL

1. Introduction

Thank you for choosing the AMS Uhrenfabrik Quartz Wall Clock, Model W9463. This manual provides essential information for the proper setup, operation, and maintenance of your new clock. Please read these instructions carefully before use and retain them for future reference.

2. Safety Information

- Do not expose the clock to extreme temperatures, direct sunlight, or high humidity.
- Avoid dropping the clock or subjecting it to strong impacts.
- Use only the specified battery type (1 AA battery). Incorrect battery usage may cause leakage or damage.
- Keep batteries out of reach of children. If swallowed, seek immediate medical attention.
- Do not attempt to disassemble or repair the clock yourself. Contact qualified service personnel for assistance.
- Ensure the clock is securely mounted if hung on a wall to prevent falling.

3. Package Contents

Carefully unpack your AMS Uhrenfabrik Quartz Wall Clock and ensure all items are present and undamaged.

- AMS Uhrenfabrik Quartz Wall Clock (Model W9463)
- Instruction Manual



Image of the AMS Uhrenfabrik Clock, Model W9463, showcasing its silver metal frame and analog display.

4. Setup and Installation

4.1 Battery Installation

Your clock requires one (1) AA battery (not included).

1. Locate the battery compartment on the back of the clock.
2. Open the battery compartment cover.
3. Insert one new AA battery, ensuring the positive (+) and negative (-) terminals align correctly with the markings inside the compartment.
4. Close the battery compartment cover securely.

4.2 Mounting the Clock

This clock is designed for indoor wall mounting.

1. Choose a suitable location on an indoor wall, away from direct heat sources, moisture, or strong vibrations.
2. Use an appropriate wall anchor and screw (not included) for your wall type to ensure secure mounting.

3. Hang the clock using the integrated hanging slot on the back. Ensure it is level and stable.

4.3 Setting the Time

Once the battery is installed, the clock will begin to run.

1. Locate the time setting knob on the back of the clock mechanism.
2. Gently turn the knob in either direction to move the hour and minute hands to the correct time.
3. Avoid forcing the hands directly. Always use the setting knob.

5. Operating Instructions

The AMS Uhrenfabrik Quartz Wall Clock operates continuously once the battery is installed and the time is set. The quartz movement ensures accurate timekeeping. Simply observe the hour and minute hands to read the current time.

6. Maintenance

6.1 Cleaning

- To clean the clock, gently wipe the surface with a soft, dry cloth.
- Do not use abrasive cleaners, solvents, or chemical sprays, as these may damage the finish or internal components.
- For glass surfaces, a mild glass cleaner applied to a cloth (not directly to the clock) can be used.

6.2 Battery Replacement

Replace the AA battery approximately once a year, or when the clock begins to lose time or stops running. Follow the battery installation steps in Section 4.1.

7. Troubleshooting

Problem	Solution
Clock is not running.	Check if the battery is inserted correctly with the correct polarity. Replace with a new AA battery. Ensure the time setting knob is not stuck.
Clock is losing or gaining time.	Replace the AA battery with a fresh one. Quartz movements are generally accurate, but a weak battery can affect performance.
Hands are stuck or not moving smoothly.	Ensure no foreign objects are obstructing the hands. If the issue persists after battery replacement, contact support.

8. Specifications

- **Brand:** AMS
- **Model Number:** W9463
- **Dimensions (approx.):** 16.54 inches (42 cm) W x 3.15 inches (8 cm) D x 16.54 inches (42 cm) H
- **Item Weight:** 3.3 Pounds (1.5 kg)

- **Movement:** Quartz movement
- **Power Source:** 1 x AA Battery (not included)
- **Material:** Metal frame, Glass
- **Color:** Silver
- **Display Type:** Analog
- **Indoor/Outdoor Usage:** Indoor
- **Origin:** Made in Germany

9. Warranty and Support

For information regarding warranty coverage, please refer to the documentation provided at the time of purchase or contact your retailer. For technical support or service inquiries, please reach out to the manufacturer or the authorized service center in your region.