

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [VTech](#) /

› [VTech Classic Light BM1100 Baby Monitor User Manual](#)

## VTech BM1100

# VTech Classic Light BM1100 Baby Monitor User Manual

## 1. INTRODUCTION

---

Thank you for choosing the VTech Classic Light BM1100 Baby Monitor. This audio baby monitor utilizes digital 6.0 FHSS technology to provide clear, interference-free sound transmission, ensuring you stay connected with your baby. This manual provides essential information for the safe and efficient operation of your device, including setup, usage, maintenance, and troubleshooting.

## 2. PACKAGE CONTENTS

---

Ensure all items are present in your package. If any items are missing or damaged, please contact your retailer.

- 1 x Baby Unit (Transmitter)
- 1 x Parent Unit (Receiver)
- 2 x Power Adapters (for Baby Unit and Parent Unit)
- 1 x Rechargeable Battery (pre-installed in Parent Unit)
- 1 x User Manual (this document)

## 3. PRODUCT OVERVIEW

---

Familiarize yourself with the components and controls of your VTech Classic Light BM1100 Baby Monitor.



Image: The VTech Classic Light BM1100 Baby Monitor, featuring the Baby Unit (left) and Parent Unit (right). The Baby Unit includes a power button and a night light button. The Parent Unit features sound indicator LEDs, a link indicator, a battery indicator, and volume control buttons.

### 3.1 Baby Unit (Transmitter)

- **Power Button:** Turns the unit on or off.
- **Night Light Button:** Activates or deactivates the night light feature.
- **Microphone:** Detects sounds from the baby's room.
- **Speaker:** Emits sounds (e.g., night light sound).
- **Power Jack:** Connects to the power adapter.

### 3.2 Parent Unit (Receiver)

- **Power Button:** Turns the unit on or off.
- **Volume Up/Down Buttons:** Adjusts the listening volume.
- **Sound Indicator LEDs:** Five LEDs light up to indicate the intensity of sound detected by the Baby Unit.
- **Link Indicator:** Shows connection status with the Baby Unit.
- **Battery Indicator:** Shows battery status, including low battery warning.
- **Speaker:** Emits sounds from the baby's room.
- **Belt Clip:** For convenient carrying.
- **Power Jack:** Connects to the power adapter for charging and operation.

## 4. SETUP

---

Follow these steps to set up your baby monitor for first use.

## 4.1 Charging the Parent Unit

1. Connect the small end of one power adapter to the power jack on the Parent Unit.
2. Plug the large end of the power adapter into a wall outlet.
3. Charge the Parent Unit for at least 12 hours before initial use. The battery indicator will show charging status. A full charge provides up to 14 hours of operating time.

## 4.2 Connecting the Baby Unit

1. Connect the small end of the second power adapter to the power jack on the Baby Unit.
2. Plug the large end of the power adapter into a wall outlet. The Baby Unit operates only on AC power.

## 4.3 Positioning the Units

- Place the Baby Unit at least 1 meter (3 feet) away from your baby.
- Position the Baby Unit and Parent Unit within range. The maximum outdoor range is 300 meters, and the indoor range is typically 50-60 meters.
- Avoid placing units near other electronic devices (e.g., cordless phones, Wi-Fi routers) to prevent interference.
- Ensure both units are placed on a flat, stable surface or mounted securely.

# 5. OPERATING INSTRUCTIONS

---

## 5.1 Turning On/Off

- **To turn on:** Press and hold the Power button on both the Baby Unit and Parent Unit until the power indicator lights up.
- **To turn off:** Press and hold the Power button on both units until the power indicator turns off.

## 5.2 Adjusting Volume (Parent Unit)

Press the **Volume Up** (▲) or **Volume Down** (▼) buttons on the Parent Unit to adjust the listening volume to your preferred level.

## 5.3 Night Light Function (Baby Unit)

Press the **Night Light** button on the Baby Unit to turn the soothing night light on or off. The light helps to calm your baby.

## 5.4 Sound Indicator LEDs (Parent Unit)

The five LEDs on the Parent Unit indicate the sound level detected by the Baby Unit. More LEDs light up as the sound intensity increases, providing a visual alert even when the volume is low or muted.

## 5.5 Out-of-Range Warning

If the Parent Unit loses connection with the Baby Unit (e.g., due to distance or interference), an audible warning will sound, and the link indicator will flash. Move the Parent Unit closer to the Baby Unit to re-establish connection.

## 5.6 Low Battery Indicator (Parent Unit)

When the Parent Unit's battery is low, the battery indicator will illuminate or flash, and an audible alert may

sound. Connect the Parent Unit to its power adapter to recharge the battery.

## 5.7 Eco Mode

The VTech Classic Light BM1100 features an Eco Mode, which reduces radio wave emissions when the units are in close proximity and the baby is quiet. This mode helps conserve energy and minimize exposure to radio frequencies.

## 6. MAINTENANCE

---

Proper care ensures the longevity of your baby monitor.

- **Cleaning:** Clean the units with a soft, damp cloth. Do not use cleaning sprays or liquid cleaners.
- **Water Exposure:** Do not immerse the units in water. Avoid placing them near water sources.
- **Storage:** Store the monitor in a cool, dry place when not in use for extended periods.
- **Battery Care:** For optimal battery life, fully charge the Parent Unit before storing it.

## 7. TROUBLESHOOTING

---

If you experience issues with your baby monitor, refer to the following common problems and solutions.

Problem	Solution
No sound from Parent Unit.	Ensure both units are powered on. Check the volume level on the Parent Unit. Ensure units are within range.
Static or interference.	Move the units closer to each other. Relocate units away from other electronic devices.
Parent Unit battery drains quickly.	Ensure the Parent Unit is fully charged (12 hours for first use). Battery life may decrease over time.
Out-of-range warning.	Move the Parent Unit closer to the Baby Unit. Ensure there are no major obstructions between the units.
Night light not working.	Ensure the Baby Unit is powered on and connected to the mains. Press the Night Light button.

## 8. SPECIFICATIONS

---

Feature	Detail
Model Number	29300
Technology	Digital 6.0 FHSS
Color	White
Power Source	Mains (AC power adapters)

Feature	Detail
Parent Unit Battery	Rechargeable (up to 14 hours usage)
Number of Channels	8
Frequency Range	400-470 MHz
Maximum Range	300 meters (outdoor), 50-60 meters (indoor)
Special Features	Eco Mode, Night Light, Sound Indicator LEDs, Low Battery Indicator, Out-of-Range Warning, Belt Clip
GTIN	03417760293004

## 9. WARRANTY AND SUPPORT

---

### 9.1 Manufacturer's Warranty

This VTech product comes with a **3-year manufacturer's warranty** from the date of purchase. Please retain your proof of purchase for warranty claims. The warranty covers defects in materials and workmanship under normal use.

### 9.2 Customer Support

For technical assistance, warranty service, or product information, please refer to the contact details provided in your product packaging or visit the official VTech website for your region. Do not attempt to repair the product yourself.