Swann SWDVR-44600H-US

Swann SWDVR-44600H-US 4 Channel 1080P HD Home Security DVR User Manual

Introduction

Welcome to your new Swann security system. This manual provides essential information for the installation, operation, and maintenance of your SWDVR-44600H-US 4 Channel 1080P HD Home Security DVR. Please read this guide thoroughly before use and retain it for future reference.

Package Contents

What's in the Box:

- DVR4-4600 with Hard Drive
- Ethernet Cable
- HDMI Cable
- Power Adapter
- Mouse
- Quick Start Guide
- Theft Deterrent Stickers



This image displays the Swann SWDVR-44600H-US DVR unit along with its included accessories: a power adapter, HDMI cable, Ethernet cable, USB mouse, and theft deterrent stickers. These are the items typically found in the product package.

Product Overview

Front Panel:



This image shows the front panel of the Swann SWDVR-44600H-US Digital Video Recorder. Visible features include the Swann logo, '4 Channel Digital Video Recorder' text, and two indicator lights labeled 'PWR' (Power) and 'HDD' (Hard Disk Drive) to show operational status.

Rear Panel:



This image displays the rear panel of the Swann SWDVR-44600H-US DVR, highlighting its various connectivity ports. From left to

right, these include four BNC video input ports (labeled 1-4), audio input and output ports, an eSATA port, HDMI output, VGA output, two USB ports, an Ethernet (LAN) port, PTZ control terminals, and the DC 12V power input.

Key Components:

- **Video Inputs (1-4):** Connect your security cameras here.
- **Audio In/Out:** For connecting microphones and speakers.
- **HDMI Output:** Connect to an HDTV or monitor for high-definition video display.
- **VGA Output:** Connect to a VGA-compatible monitor.
- **LAN & USB Ports:** For network connection and USB devices like the included mouse or external storage.
- **DC 12V In:** Power input for the DVR.
- **PWR/HDD Indicators:** Front panel lights indicating power status and hard drive activity.

Setup

Initial Connection:

1. Connect your cameras to the **Video In** ports on the rear panel.
2. Connect a monitor to the **HDMI** or **VGA** output.
3. Connect the included mouse to one of the **USB** ports.
4. Connect the Ethernet cable to the **LAN** port for network access (optional, for remote viewing).
5. Connect the power adapter to the **DC 12V In** port and then to a power outlet. The DVR will power on automatically.

First-Time Setup Wizard:

Upon first power-on, the DVR will guide you through a setup wizard to configure basic settings such as language, date/time, network, and password. Follow the on-screen prompts.

Operating Your DVR

Live View:

After initial setup, the DVR will display the live feed from connected cameras. Use the mouse to navigate the on-screen interface.

Recording:

The DVR is pre-configured to record continuously. You can adjust recording settings (e.g., motion detection, schedule) via the main menu.

Playback:

To view recorded footage, access the "Playback" option from the main menu. You can search by date, time, and event type.

Remote Access:

For remote viewing on a smartphone or computer, download the SwannView Link app (or equivalent) and follow the instructions for network configuration in the DVR's menu.

Maintenance

Hard Drive Management:

The 1TB hard drive will automatically overwrite the oldest footage when full. Regularly back up important recordings to external storage via USB or network.

Firmware Updates:

Check the Swann support website periodically for firmware updates to ensure optimal performance and security. Follow the provided instructions for updating.

Cleaning:

Keep the DVR unit clean and free from dust. Use a soft, dry cloth. Do not use liquid cleaners.

Troubleshooting

No Video Output:

- Ensure all cables (HDMI/VGA, power) are securely connected.
- Verify the monitor input source is correctly selected.
- Check if the DVR's power indicator light is on.

No Recording:

- Check hard drive status in the DVR menu.
- Ensure recording schedules or motion detection settings are correctly configured.
- Verify cameras are properly connected and functioning.

Remote Access Issues:

- Confirm the DVR is connected to the internet.
- Check network settings (IP address, port forwarding) in the DVR menu and your router.
- Ensure the correct app and account details are used.

Specifications

Feature	Detail
Model Number	SWDVR-44600H-US
Video Channels	4
Video Resolution	1080p HD
Hard Drive Size	1 TB
Video Compression	H.264

Feature	Detail
Connectivity	Wired (Ethernet, BNC)
Video Outputs	HDMI, VGA
USB Ports	2
Dimensions	3.74 x 14.17 x 10.83 inches
Weight	3.75 pounds

Warranty and Support

Warranty Information:

Your Swann SWDVR-44600H-US is covered by a limited warranty. Please refer to the warranty card included in your package or visit the official Swann website for detailed terms and conditions.

Technical Support:

For technical assistance, troubleshooting, or further inquiries, please visit the Swann support website or contact their customer service. Contact details can be found on the Swann website.

Note: Proof of purchase may be required for warranty claims.