

Quorum International 3066-11-86

Quorum International 2-Light Flush Mount Ceiling Light

Model: 3066-11-86 | Instruction Manual

1. INTRODUCTION AND OVERVIEW

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Quorum International 2-Light Flush Mount Ceiling Light, Model 3066-11-86. This fixture features an oiled bronze finish and faux alabaster glass shades, designed to provide soft, ambient illumination.

Its compact dimensions (11.5 inches wide by 6 inches high) make it suitable for various indoor spaces such as bedrooms, entryways, and hallways. The two-light design ensures ample lighting for its intended applications.



Figure 1: Front view of the Quorum International 2-Light Flush Mount Ceiling Light.

2. SAFETY INFORMATION

WARNING: To avoid electric shock, always turn off power at the main circuit breaker or fuse box before beginning installation or performing any maintenance. Do not attempt installation if you are not familiar with electrical wiring. Consult a qualified electrician.

- Read all instructions carefully before installation.
- Ensure the fixture is properly grounded.
- Do not exceed the maximum wattage specified for the bulbs.
- Handle glass components with care to prevent breakage.
- This fixture is designed for indoor use only.

3. PACKAGE CONTENTS

Before beginning installation, ensure all components are present and undamaged. If any parts are missing or damaged, do not proceed with installation and contact customer support.

- Flush Mount Fixture (Oiled Bronze)
- Faux Alabaster Glass Shade
- Mounting Hardware (screws, wire nuts, mounting bracket)

4. SETUP AND INSTALLATION

Tools Required: Phillips head screwdriver, flathead screwdriver, wire strippers, pliers, electrical tape, voltage tester, ladder.

1. **Turn Off Power:** Locate the circuit breaker or fuse box that controls the power to the light fixture's location. Turn off the power completely. Use a voltage tester to confirm that the power is off at the junction box.
2. **Remove Old Fixture (if applicable):** Carefully disconnect and remove any existing light fixture. Note the wiring connections for reference.
3. **Install Mounting Bracket:** Attach the provided mounting bracket to the electrical junction box in the ceiling using the screws supplied with the junction box or the fixture. Ensure the bracket is securely fastened.
4. **Wire Connections:**
 - Connect the bare copper (ground) wire from the fixture to the bare copper or green (ground) wire from the junction box using a wire nut.
 - Connect the white (neutral) wire from the fixture to the white (neutral) wire from the junction box using a wire nut.
 - Connect the black (hot) wire from the fixture to the black (hot) wire from the junction box using a wire nut.

Ensure all connections are secure and covered with wire nuts. Wrap electrical tape around wire nuts for added security.

5. **Mount Fixture:** Carefully push the connected wires into the junction box. Align the fixture base with the mounting bracket and secure it in place using the screws provided.
6. **Install Bulbs:** Screw in two E26 Medium base bulbs (not included). Do not exceed 60 watts per bulb. This fixture is compatible with Incandescent, Fluorescent, LED, Halogen, or Xenon bulbs.
7. **Attach Shade:** Carefully place the faux alabaster glass shade onto the fixture and secure it according to the design (typically by screwing on a decorative finial or using retention clips). Do not overtighten.
8. **Restore Power:** Once installation is complete, turn the power back on at the circuit breaker and test the light fixture.



Figure 2: Example of the flush mount light installed in a hallway.

5. OPERATING INSTRUCTIONS

To operate the Quorum International 2-Light Flush Mount Ceiling Light, simply use the standard wall switch connected to the circuit. If a remote control system is desired, it must be purchased and installed

separately, and its operation will be governed by its own instruction manual.

6. MAINTENANCE

Cleaning

To clean the fixture, ensure the power is off. Wipe the metal finish with a soft, dry cloth. For the glass shade, use a soft, damp cloth with a mild, non-abrasive cleaner if necessary, then dry thoroughly. Do not use harsh chemicals or abrasive materials, as these can damage the finish or glass.

Bulb Replacement

Always turn off the power at the circuit breaker before replacing bulbs. Allow bulbs to cool completely before touching them. Unscrew the old bulbs and replace them with new E26 Medium base bulbs, ensuring they do not exceed the maximum 60 watts per bulb.

7. TROUBLESHOOTING

If you encounter issues with your light fixture, refer to the following common troubleshooting steps:

- **Light does not turn on:**
 - Check if the wall switch is in the ON position.
 - Verify that the circuit breaker for the fixture is not tripped.
 - Ensure bulbs are securely screwed into their sockets and are not burnt out.
 - Confirm that all wire connections are secure and properly made.
- **Light flickers:**
 - Check that the bulbs are fully tightened in their sockets.
 - Ensure the bulbs are compatible with the fixture and are not faulty.
 - Inspect wire connections for any looseness.

If these steps do not resolve the issue, consult a qualified electrician or contact Quorum International customer support.

8. SPECIFICATIONS

Brand	Quorum International
Model Number	3066-11-86
Dimensions	11.5 inches (Width) x 6 inches (Height)
Finish	Oiled Bronze
Shade Material	Faux Alabaster Glass
Number of Lights	2
Bulb Base	E26 Medium
Max Wattage	60 Watts per bulb

Voltage	120 Volts
Light Source Compatibility	Incandescent, Fluorescent, LED, Halogen, Xenon
Installation Type	Flush Mount
Indoor/Outdoor Use	Indoor
Certifications	UL Listed
Item Weight	4 Pounds

9. WARRANTY AND SUPPORT

For specific warranty information regarding your Quorum International 2-Light Flush Mount Ceiling Light, please refer to the documentation included with your purchase or visit the official Quorum International website. Keep your purchase receipt as proof of purchase for any warranty claims.

For technical assistance or customer support, please contact Quorum International directly through their official channels.