

## Revo 641181

# Revo SuperConnect Multi Format Deluxe Table Radio (Model 641181) User Manual

Model: 641181

## 1. INTRODUCTION

The Revo SuperConnect is a multi-format digital radio designed to provide access to various audio sources. It supports DAB, DAB+, FM with RDS, and Internet Radio, offering a wide selection of stations. Additionally, it features wireless audio playback capabilities including DLNA, WLAN, Bluetooth with aptX for streaming from compatible devices, and Spotify Connect for accessing music services. The unit is constructed with an American Walnut cabinet, anodised aluminium, and mild-steel components, featuring an OLED display and joystick control for navigation.

## 2. PACKAGE CONTENTS

Please check that all items listed below are present in your product packaging:

- Revo SuperConnect Multi Format Deluxe Table Radio
- Remote Control
- Power Adapter (AC)
- User Manual (this document)

## 3. PRODUCT OVERVIEW

### 3.1 Front Panel

The front panel features the OLED display, control joystick, power button, and preset buttons for quick access to saved stations.



**Figure 3.1:** Front view of the Revo SuperConnect radio. The left side features a monochrome OLED display showing "Internet radio" and "BBC Radio 6Music". To the right of the display is a vertical joystick control with a 'SELECT' label. Below the display are buttons for 'MODE', 'MENU', 'INFO', 'ALARM', and playback controls. On the right side of the front panel, there is a speaker grille and a row of eight circular preset buttons labeled 1 through 8, along with a headphone jack.

### 3.2 Rear Panel

The rear panel includes connections for power, auxiliary input, digital output, and the telescopic antenna.



**Figure 3.2:** Rear view of the Revo SuperConnect radio. A telescopic antenna is visible at the top. Below it, the text "SUPERCONNECT" and "www.revo.co.uk" are printed. Towards the bottom, from left to right, are RCA audio input jacks (L AUDIO R), an AUX IN 3.5mm jack, a DIGITAL OUT optical port, and a 18V DC power input. Various regulatory compliance logos are also present.

## 4. SETUP

### 4.1 Power Connection

1. Connect the supplied AC power adapter to the 18V DC input port on the rear of the SuperConnect.
2. Plug the power adapter into a suitable wall outlet.
3. The unit will power on and enter standby mode.

### 4.2 Antenna Setup

- For optimal DAB/DAB+ and FM reception, fully extend the telescopic antenna located on the rear of the unit.
- Adjust the antenna's position for the best signal quality.

### 4.3 Network Setup (Wi-Fi)

To access Internet Radio, Spotify Connect, and DLNA features, the SuperConnect must be connected to a Wi-Fi network.

1. Power on the unit. If it's the first time, it may automatically enter network setup.
2. Navigate to the **Menu** using the joystick, then select **System Settings > Network > Network Wizard**.
3. The radio will scan for available Wi-Fi networks.
4. Select your desired network from the list.
5. Enter the network password (WPA/WPA2 key) using the joystick to select characters. Press **Select** to confirm each character and the final password.
6. Once connected, the display will show a confirmation message.

## 5. OPERATING INSTRUCTIONS

---

### 5.1 Basic Controls

- **Power Button:** Press to turn the unit on or off (standby).
- **Joystick:** Move up/down/left/right to navigate menus and adjust volume. Press in to select.
- **Mode Button:** Cycles through available modes (DAB, FM, Internet Radio, Bluetooth, Spotify, DLNA, Aux In).
- **Menu Button:** Accesses the main menu for the current mode or system settings.
- **Info Button:** Displays additional information about the current station or track.
- **Alarm Button:** Sets and manages alarms.
- **Preset Buttons (1-8):** Press and hold to save a station; press briefly to recall a saved station.

### 5.2 DAB/DAB+ Radio

1. Press the **Mode** button until DAB Radio is selected.
2. The radio will perform an auto-scan for available DAB/DAB+ stations if it's the first time or if no stations are found.
3. Use the joystick to scroll through the list of available stations.
4. Press the joystick to select a station.

### 5.3 FM Radio

1. Press the **Mode** button until FM Radio is selected.
2. To auto-tune, press and hold the joystick. The radio will scan for the next available station.
3. To manually tune, rotate the joystick to adjust the frequency.

### 5.4 Internet Radio

Requires an active Wi-Fi connection.

1. Press the **Mode** button until Internet Radio is selected.
2. You can browse stations by location, genre, or search for specific stations.
3. Use the joystick to navigate and select your desired station.

### 5.5 Bluetooth Streaming

The SuperConnect supports Bluetooth with aptX for high-quality wireless audio streaming.

1. Press the **Mode** button until Bluetooth is selected. The radio will enter pairing mode.
2. On your Bluetooth-enabled device (smartphone, tablet), go to its Bluetooth settings and search for available devices.
3. Select "Revo SuperConnect" from the list.
4. Once paired, audio from your device will stream through the SuperConnect.

### 5.6 Spotify Connect

Requires a Spotify Premium account and an active Wi-Fi connection.

1. Ensure your SuperConnect is connected to the same Wi-Fi network as your device running the Spotify app.
2. Open the Spotify app on your smartphone, tablet, or computer.
3. Play a song and tap the "Devices Available" icon (usually a speaker or computer icon).
4. Select "Revo SuperConnect" from the list of available devices.
5. The SuperConnect will begin playing audio from Spotify.

### 5.7 DLNA Audio Streaming

Allows wireless audio playback from external computers and music servers on the same network.

1. Ensure your SuperConnect and DLNA-compatible device (e.g., PC with media server software) are on the same Wi-Fi network.
2. Press the **Mode** button until DLNA is selected.
3. The radio will display available media servers. Select your desired server.
4. Browse your music library and select tracks for playback.

## 6. MAINTENANCE

### 6.1 Cleaning

- Always disconnect the power adapter before cleaning.
- Use a soft, dry cloth to wipe the surfaces of the radio.
- Do not use abrasive cleaners, waxes, or solvents as they may damage the finish.

### 6.2 Software Updates

The SuperConnect may receive firmware updates to improve performance or add features. Check the system settings menu for available updates periodically.

## 7. TROUBLESHOOTING

Problem	Possible Cause	Solution
No power	Power adapter not connected or faulty outlet.	Ensure power adapter is securely connected to the radio and a working wall outlet.
No sound	Volume too low, mute activated, or incorrect source selected.	Increase volume, check if mute is active, verify correct input mode (DAB, FM, Internet Radio, etc.).
Cannot connect to Wi-Fi	Incorrect password, weak signal, or router issue.	Re-enter Wi-Fi password carefully. Move radio closer to router. Restart router.
Poor DAB/FM reception	Antenna not extended or poor signal area.	Fully extend and adjust the telescopic antenna. Try repositioning the radio.
Bluetooth pairing fails	Device not in pairing mode, or too far away.	Ensure SuperConnect is in Bluetooth mode and your device is searching. Keep devices within range.

## 8. SPECIFICATIONS

- **Model Number:** 641181
- **Product Dimensions:** 4.72 x 10.63 x 7.09 inches
- **Item Weight:** 6.16 pounds
- **Power Source:** AC (18V DC input)
- **Connectivity Technology:** Wi-Fi, Bluetooth (aptX)
- **Tuner Technology:** DAB, FM
- **Radio Bands Supported:** FM, DAB, DAB+, Internet Radio
- **Special Features:** DAB, DAB+ and FM Tuner with RDS, Intuitive joystick controlled user interface, Spotify Connect, DLNA

Audio Streaming

- **Included Components:** Remote Control
- **Manufacturer:** Revo Technologies
- **Color:** Shadow Matte Black

9. WARRANTY INFORMATION

This product is covered by a manufacturer's warranty. Please refer to the warranty card included with your purchase or visit the official Revo website for detailed warranty terms and conditions specific to your region.

10. CUSTOMER SUPPORT




For further assistance, technical support, or to view frequently asked questions, please visit the official Revo website: [www.revo.co.uk](http://www.revo.co.uk)



© 2023 Revo Technologies. All rights reserved.

Related Documents - 641181

	<p><a href="#">Revo SUPERSIGNAL Radio Owner's Guide - Setup, Features, and Troubleshooting</a></p> <p>This comprehensive owner's guide provides detailed instructions for the Revo SUPERSIGNAL radio. Learn about setup, DAB and FM radio modes, Bluetooth connectivity, alarm clock functions, system settings, and troubleshooting common issues.</p>
	<p><a href="#">REVO Smart Cupping Massage User Manual</a></p> <p>Comprehensive user manual for the REVO Smart Cupping Massage device, detailing its introduction, specifications, operating guidelines, safety precautions, cleaning, maintenance, troubleshooting, and frequently asked questions.</p>
	<p><a href="#">REVO Face Genie User Manual: Features, Usage, and Safety</a></p> <p>Comprehensive user manual for the REVO Face Genie, detailing its components, functions, usage instructions, safety precautions, and troubleshooting. Learn how to use the device for skin tightening, brightening, and soothing.</p>

	<p><a href="#">Revo Bake Titan Tilt 7.5 Addendum: Updated Features Guide</a></p> <p>This addendum provides updated feature information for the Revo Bake Titan Tilt 7.5, including instructions for changing temperature units and using the reverse function. It supplements the original user manual.</p>
	<p><a href="#">REVO RW4NVR1 Wireless NVR Kit Product Manual</a></p> <p>Comprehensive product manual for the REVO RW4NVR1 Wireless NVR Kit, detailing features, specifications, installation, operation, network setup, and maintenance for home and business security.</p>
	<p><a href="#">REVO Digital Video Recorder User's Manual</a></p> <p>This user's manual provides comprehensive instructions for installing, configuring, and operating the REVO Digital Video Recorder (DVR), covering features, setup, and troubleshooting for various models. It also includes documentation for the RASplus Remote Administration System.</p>