

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Quoizel](#) /

› [Quoizel TY1444WT Taylor Track Lighting Kit Instruction Manual](#)

## Quoizel TY1444WT

# Quoizel TY1444WT Taylor 4-Light Track Lighting Kit Instruction Manual

Model: TY1444WT

## 1. INTRODUCTION

This manual provides essential information for the safe installation, operation, and maintenance of your Quoizel TY1444WT Taylor 4-Light Track Lighting Kit. Please read these instructions thoroughly before beginning installation and retain them for future reference.

## 2. SAFETY INFORMATION

### WARNING: RISK OF ELECTRIC SHOCK.

- Always turn off the electrical supply at the main fuse or circuit breaker box before beginning installation or performing any maintenance.
- Consult a qualified electrician if you are unsure about the installation process.
- Ensure all electrical connections are made in accordance with local codes and ordinances.
- Do not install this fixture in wet locations. It is approved for DAMP locations only.
- Use only the specified bulb type and wattage to avoid overheating.

## 3. PACKAGE CONTENTS

Verify that all components are present before discarding packaging materials.

- 1 x Quoizel TY1444WT Taylor 4-Light Track Lighting Fixture
- Mounting Hardware (for existing junction box)
- Opal Etched Glass Shades (4 units)

*Note: Light bulbs are not included and must be purchased separately.*

## 4. SPECIFICATIONS

Feature	Specification
Model Number	TY1444WT
Dimensions (L x W x H)	43.75" x 4.75" x 10.75"
Weight	7 lbs
Number of Lights	4
Max Wattage per Bulb	100 Watts
Total Wattage	400 Watts
Bulb Base	E26 (Medium Base)
Bulb Type Compatibility	Incandescent, CFL, Halogen, LED
Voltage	120 Volts
Finish	Western Bronze
Shade Material	Opal Etched Glass
Location Rating	UL Approved for DAMP Locations
Control Method	Remote (requires compatible dimmer switch and dimmable bulbs)

## 5. INSTALLATION INSTRUCTIONS

Follow these steps carefully to install your track lighting kit. If you are not familiar with electrical wiring, consult a qualified electrician.

### 1. Prepare for Installation:

- Turn off the power at the circuit breaker or fuse box to the outlet box where the fixture will be installed.
- Ensure the power is off by testing the circuit with a voltage tester.
- Carefully unpack the fixture and all parts. Place all parts on a clean, flat surface.

### 2. Mount the Fixture:

- Attach the mounting bracket (if separate) to the existing junction box in the ceiling using the provided screws. Ensure it is securely fastened.
- The fixture is designed to mount to an existing junction box.

### 3. Make Electrical Connections:

- Connect the bare copper or green ground wire from the fixture to the ground wire from the junction box (usually bare copper or green) using a wire nut.
- Connect the white wire from the fixture to the white (neutral) wire from the junction box using a wire nut.
- Connect the black wire from the fixture to the black (hot) wire from the junction box using a wire nut.

nut.

- Ensure all wire nuts are tightly secured and no bare wire is exposed.

#### 4. Secure the Fixture:

- Carefully tuck all wires into the junction box.
- Align the fixture base with the mounting bracket and secure it with the provided screws.

#### 5. Install Light Bulbs and Shades:

- Screw the appropriate E26 base bulbs (up to 100W incandescent or equivalent LED/CFL) into each socket. Do not overtighten.
- Attach the opal etched glass shades to each light head according to the fixture design. Ensure they are securely in place.

#### 6. Restore Power:

- Turn the power back on at the circuit breaker or fuse box.
- Test the fixture to ensure it is working correctly.



Figure 1: Front view of the Quoizel TY1444WT Taylor Track Lighting Kit with four adjustable light heads and opal etched glass shades.



Figure 2: Angled view of the track lighting kit, showing the Western Bronze finish and the ceiling canopy.

## 6. OPERATING INSTRUCTIONS

Once installed, your Quoizel TY1444WT Taylor Track Lighting Kit is ready for use.

- **Power On/Off:** Operate the fixture using the standard wall switch connected to the circuit.
- **Bulb Type:** This fixture uses E26 medium base bulbs, up to 100 watts each. Compatible bulb types include incandescent, CFL, halogen, or LED.
- **Dimming Functionality:** For full-range dimming, ensure you use dimmable bulbs and a compatible

dimmer switch (sold separately) installed on the circuit.

- **Adjusting Light Heads:** The individual light heads can be adjusted to direct light as needed. Gently pivot or rotate the heads to achieve the desired illumination angle.

## 7. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your lighting fixture.

- **Cleaning:** To clean the fixture, ensure the power is off and the fixture is cool. Wipe with a soft, dry cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish or glass.
- **Bulb Replacement:**
  - Turn off the power at the circuit breaker before replacing bulbs.
  - Allow bulbs to cool completely before touching them.
  - Carefully unscrew the old bulb and replace it with a new E26 medium base bulb of the specified wattage (max 100W).
  - Ensure the new bulb is securely screwed in but not overtightened.
- **Glass Shade Care:** Handle glass shades with care. If a shade becomes loose, gently re-secure it.



Figure 3: Close-up view of an individual light head, highlighting the opal etched glass shade and its attachment point.

## 8. TROUBLESHOOTING

If you encounter issues with your lighting kit, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on	No power to the fixture Loose wire connection Defective bulb	Check circuit breaker/fuse Ensure all wire connections are secure (power off first) Replace bulb with a known working one
Light flickers	Loose bulb Incompatible dimmer switch/bulb Loose wire connection	Tighten bulb Ensure dimmer and bulbs are compatible (if using dimming) Check wire connections (power off first)

Problem	Possible Cause	Solution
Bulbs burn out quickly	Incorrect wattage bulb Poor quality bulbs Voltage fluctuations	Use bulbs within the specified wattage range (max 100W) Try a different brand of bulb Consult an electrician if voltage issues are suspected

## 9. WARRANTY INFORMATION




This Quoizel lighting fixture is covered by a manufacturer's warranty. Please refer to the original purchase documentation or contact Quoizel customer support for specific warranty terms and conditions.




## 10. CUSTOMER SUPPORT

For further assistance, technical support, or to inquire about replacement parts, please contact Quoizel customer service through their official website or the retailer where the product was purchased.

© 2025 Quoizel. All rights reserved.

### Related Documents - TY1444WT

	<p><a href="#">Quoizel QP6755MBK Zyler Matte Black 4-Light Pendant Installation Guide</a></p> <p>Comprehensive installation guide for the Quoizel QP6755MBK Zyler 4-light matte black pendant ceiling light. Includes safety warnings, package contents, mounting hardware, and step-by-step assembly instructions.</p>
	<p><a href="#">Quoizel LANS8624MBK Installation Guide</a></p> <p>Step-by-step installation guide for the Quoizel LANS8624MBK vanity light fixture, including safety information, package contents, and mounting instructions.</p>
	<p><a href="#">Quoizel SPL542LG and SPL542K Installation Guide</a></p> <p>This installation guide provides step-by-step instructions for assembling and installing the Quoizel SPL542LG and SPL542K lighting fixtures. It includes essential safety warnings, required tools, package contents, mounting hardware details, and maintenance tips. Ensure proper electrical safety and consult a licensed electrician if needed.</p>

	<p><a href="#"><b>Quoizel QSF6157WS and QP6157WS Installation Guide</b></a></p> <p>Detailed installation guide for Quoizel QSF6157WS and QP6157WS pendant and semi-flush ceiling lights. Includes safety information, package contents, mounting hardware, and step-by-step assembly instructions for two installation options.</p>
	<p><a href="#"><b>Quoizel MAP5028GFL, MAP1728GFL, MAP5028EK, MAP1728EK Installation Guide</b></a></p> <p>Comprehensive installation guide for Quoizel pendant and semi-flush ceiling lights, models MAP5028GFL, MAP1728GFL, MAP5028EK, and MAP1728EK. Includes safety information, package contents, mounting hardware, and step-by-step assembly instructions.</p>
	<p><a href="#"><b>Quoizel PCCET538MBK Celeste Island Light Installation Guide</b></a></p> <p>Comprehensive installation guide for the Quoizel PCCET538MBK Celeste Island Light. Includes safety warnings, package contents, mounting hardware details, and step-by-step assembly instructions for a safe and proper installation.</p>