

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [Minka Lavery](#) /

› [Minka Lavery 6963-84 Overland Park 3-Light Vanity Light Fixture Instruction Manual](#)

## Minka Lavery 6963-84

# Minka Lavery 6963-84 Overland Park 3-Light Vanity Light Fixture Instruction Manual

Model: 6963-84

## INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Minka Lavery 6963-84 Overland Park 3-Light Vanity Light Fixture. Please read all instructions carefully before beginning installation and retain this manual for future reference.

The Minka Lavery 6963-84 is a 3-light vanity fixture featuring a brushed nickel finish and etched white glass shades. It is designed for indoor use in damp locations, such as bathrooms, and is ETL approved for use in the US and Canada.

## SAFETY INFORMATION

- **WARNING:** To avoid electric shock, ensure power is turned off at the circuit breaker or fuse box before installation, servicing, or changing bulbs.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). Consult a qualified electrician if you are unfamiliar with proper electrical wiring connections.
- Use only the specified bulb type and wattage. Exceeding the maximum wattage may cause overheating and damage to the fixture.
- Do not install this fixture in wet locations. It is suitable for damp locations only.
- Handle glass components with care to prevent breakage.
- Keep flammable materials away from the light bulbs.

## PACKAGE CONTENTS

Verify that all components are present before beginning installation:

- Vanity Light Fixture (Brushed Nickel)
- Etched White Glass Shades (3)
- Mounting Hardware Kit

- 7-inch Long Wire (pre-attached)

*Note: Light bulbs are not included and must be purchased separately.*

## SETUP AND INSTALLATION

---

Follow these steps for proper installation of your vanity light fixture. It is recommended to have a second person assist during installation.

1. **Turn Off Power:** Locate the circuit breaker or fuse box that supplies power to the installation location and turn off the power.
2. **Prepare Mounting Surface:** Ensure the wall plate mount area (7" W x 4.5" H) is clean and clear of obstructions.
3. **Attach Mounting Bracket:** Secure the mounting bracket (from the hardware kit) to the electrical junction box in the wall.
4. **Make Electrical Connections:** Connect the fixture's wires to the household electrical wires according to standard wiring practices (black to black, white to white, ground to ground). Use the provided wire nuts and ensure all connections are secure.
5. **Mount Fixture:** Carefully align the fixture with the mounting bracket and secure it using the provided screws. The fixture can be installed with the lights facing either up or down.
6. **Install Glass Shades:** Attach the three etched white glass shades to the fixture. Ensure they are securely fastened but do not overtighten.
7. **Install Light Bulbs:** Insert the recommended light bulbs (E26 base, A19 style, up to 100W each) into the sockets.
8. **Restore Power:** Turn the power back on at the circuit breaker or fuse box.



Image: The Minka Lavery 6963-84 vanity light fixture shown installed above a bathroom mirror, illuminating the area.



Image: A technical diagram illustrating the overall height (8.25 inches), width (22.75 inches), and wall plate dimensions (7 x 4.5 inches) of the fixture.

## OPERATING INSTRUCTIONS

Once installed, operate the Minka Lavery 6963-84 vanity light fixture using a standard wall switch. The fixture is compatible with dimmable bulbs and dimmer switches, allowing you to adjust the light output as desired. Ensure that any dimmer switch used is compatible with the type of bulbs installed (LED, incandescent, etc.).



## MINKA LAVERY

### OVERLAND PARK-3 LIGHT VANITY

- Etched white glass shade



|                          |            |
|--------------------------|------------|
| <b>NUMBER OF BULBS</b>   | 3          |
| <b>MAX WATT PER BULB</b> | 100        |
| <b>SOCKET BASE</b>       | E26 Medium |
| <b>RECOMMENDED BULB</b>  | A19        |
| <b>DIMMABLE</b>          | Y          |
| <b>BULB INCLUDED</b>     | N          |

Image: A table detailing key specifications including number of bulbs (3), max wattage per bulb (100W), socket base (E26 Medium), recommended bulb (A19), dimmable (Yes), and bulb included (No).

#### MAINTENANCE

Regular maintenance will ensure the longevity and appearance of your light fixture.

- **Cleaning:** To clean the fixture, turn off the power and wipe with a soft, dry cloth. Do not use abrasive cleaners, polishes, or solvents as they may damage the finish. For glass shades, remove them carefully and wash with mild soap and water, then dry thoroughly before reattaching.
- **Bulb Replacement:** Ensure power is off before replacing bulbs. Allow old bulbs to cool before removal. Replace with E26 base, A19 style bulbs, not exceeding 100 watts per bulb.



Image: A detailed close-up of the brushed nickel finish, highlighting its texture and appearance.

## TROUBLESHOOTING

| Problem                | Possible Cause  | Solution   |
|------------------------|---|--|
| Light does not turn on | <ol style="list-style-type: none"><li>1. Power is off</li><li>2. Loose wiring connection</li><li>3. Faulty bulb</li></ol>   | <ol style="list-style-type: none"><li>1. Check circuit breaker/fuse</li><li>2. Verify all wire connections are secure (with power off)</li><li>3. Replace bulb</li></ol>   |
| Light flickers         | <ol style="list-style-type: none"><li>1. Loose bulb</li><li>2. Incompatible dimmer switch</li><li>3. Loose wiring</li></ol> | <ol style="list-style-type: none"><li>1. Tighten bulb</li><li>2. Ensure dimmer is compatible with bulb type</li><li>3. Check wiring connections (with power off)</li></ol> |
| Glass shade is loose   | Shade not tightened properly  | Gently tighten the shade until secure  |

## SPECIFICATIONS

- **Model Number:** 6963-84
- **Dimensions (H x W x D):** 8.25" x 22.75" x 5.75"
- **Weight:** 5.03 lbs
- **Wall Plate Mount:** 7" W x 4.5" H
- **Finish:** Brushed Nickel

- **Shade Material:** Etched White Glass
- **Number of Lights:** 3
- **Max Wattage per Bulb:** 100 Watts
- **Bulb Base:** E26 (Medium Base)
- **Compatible Bulb Types:** LED, Fluorescent, Halogen, Incandescent (A19 Style Recommended)
- **Dimmable:** Yes (with compatible bulbs and dimmer switch)
- **Installation Position:** Lights Up or Down
- **Location Rating:** Damp Locations
- **Certifications:** ETL Approved (US and Canada)
- **Voltage:** 120 Volts

## WARRANTY INFORMATION

---

This Minka Lavery product comes with a limited warranty. For specific details regarding warranty coverage, terms, and conditions, please refer to the warranty documentation included with your purchase or contact Minka Lavery customer support.

## SUPPORT

---

If you have any questions regarding the installation, operation, or maintenance of your Minka Lavery 6963-84 Overland Park 3-Light Vanity Light Fixture, please contact Minka Lavery customer support. Contact information can typically be found on the product packaging or the official Minka Lavery website.