

[Manuals.plus](#) /

› [Coway](#) /

› Coway Airmega 300 Smart Air Purifier User Manual

Coway AP-1515H

Coway Airmega 300 Smart Air Purifier User Manual

Model: AP-1515H | Brand: Coway

1. INTRODUCTION AND OVERVIEW

The Coway Airmega 300 is a powerful and intelligent air purifier designed to effectively clean the air in your home. It features a HyperCaptive filtration system capable of reducing 99.999% of 0.01-micron particles, including pollen and other allergens, and also reduces 99% of volatile organic compounds and odors.

This unit is designed to clean spaces up to 1,256 sq. ft. in 30 minutes, making it suitable for large rooms and open-plan areas. Its smart features, including real-time air quality monitoring, ensure optimal performance and energy efficiency.



Figure 1: Coway Airmega 300 Smart Air Purifier. This image shows the compact and modern design of the air purifier, suitable for various home environments.

Airmega 300



2,513 ft² in 60mins
1,256 ft² in 30mins



Dual
Purification



Air Quality
Monitoring



3 Smart Modes



HyperCaptive™
Filtration



Filter
Replacement
Indicator



Figure 2: Key features of the Airmega 300, including dual purification, HyperCaptive filtration, smart modes, air quality monitoring, and filter replacement indicators.

2. SETUP

Setting up your Coway Airmega 300 is straightforward. Follow these steps to ensure proper installation and operation:

1. **Unboxing:** Carefully remove the air purifier from its packaging. Retain packaging for future transport or storage.
2. **Filter Installation:** The Airmega 300 comes with pre-installed filters. Before first use, open the side covers and remove all plastic packaging from the pre-filter, deodorization filter, and True HEPA Filter. Ensure filters are correctly oriented and securely placed back into their compartments.
3. **Placement:** Place the unit on a flat, stable surface. For optimal air circulation, ensure there is at least 1.5 to 2 feet of open space around the unit, especially on the sides where air is drawn in. The unit's design with elevated legs facilitates proper airflow from the bottom.
4. **Power Connection:** Plug the power cord into a standard electrical outlet. The unit is now ready for operation.

Powerful Dual Purification




Figure 3: Diagram illustrating the dual suction purification system and filter layers (Pre-Filter, Activated Carbon, Green True HEPA) of the Airmega 300.

HyperCaptive™ Filtration

Pre-Filter



Hair



Pet hair



Large dust



Dust mite

Max2 Filter

Activated Carbon

+

Green True HEPA™



Food Smells



Cigarette Fumes



Pet Odor



VOCs



Fine Dust



Germs



Bacteria



Mold



Virus



Pollen



Figure 4: Detailed view of the HyperCaptive Filtration System, showing what each filter layer (Pre-Filter, Activated Carbon, Green True HEPA) is designed to capture, from hair and dust to mold, viruses, and VOCs.

3. OPERATING MODES

The Coway Airmega 300 offers several operating modes to optimize air purification based on your needs and environmental conditions:

- **Smart Mode:** This intelligent mode automatically adjusts fan speeds based on the room's real-time air quality, detected by the built-in pollution sensor. This ensures energy efficiency without compromising effectiveness. The air quality indicator light on the unit will change colors (blue for good, purple for moderate, pink for unhealthy, red for very unhealthy) to reflect current air quality.
- **Eco Mode:** When the air quality remains purified for 30 minutes or more in Eco Mode, the fan will automatically turn off to conserve energy. It will reactivate when pollution is detected.
- **Sleep Mode:** Activated when the pollution sensor detects clean air for 3 minutes, Sleep Mode reduces the purifier's noise and power consumption, providing a quiet environment for rest.
- **Timer:** You can schedule the unit to purify for 1, 4, or 8 hours of use to conserve energy.

Your browser does not support the video tag.

Video 1: Demonstration of the Coway Airmega's Air Quality Monitoring system. This video illustrates how the unit's sensors detect changes in air quality and adjust operation accordingly.

Your browser does not support the video tag.

Video 2: Overview of the Coway Airmega's ability to maintain clean indoor air, highlighting its effectiveness in various environments.

4. MAINTENANCE

Regular maintenance ensures your Airmega 300 operates at peak efficiency. The unit provides alerts for filter maintenance:

- **Filter Alerts:** The air filter indicator lights on the control panel will notify you when the filters need to be replaced or the pre-filters need to be cleaned. These alerts are based on the amount of air processed, not just time.
- **Pre-Filter Cleaning:** The pre-filter is washable and should be cleaned regularly to maintain efficiency. Simply remove the side cover, slide out the pre-filter, and rinse it under running water. Allow it to air dry completely before reinserting.
- **Max2 Filter Replacement:** The Max2 filter (combining deodorization and True HEPA) needs to be replaced when indicated by the unit. Do not wash this filter. Follow the instructions in the user manual for proper replacement.

Real-Time Air Quality Monitoring

Its particle sensors communicate indoor air quality in real-time by the colored LED indicator.




Figure 5: Illustration of the convenient, washable pre-filter being removed for cleaning. This filter captures large particles like hair and fur, extending the life of other filters.

5. TROUBLESHOOTING

If you encounter any issues with your Coway Airmega 300, please refer to the following common troubleshooting tips:

- **Unit Not Turning On:** Ensure the power cord is securely plugged into a working electrical outlet. Check if the side covers are properly closed, as safety interlocks may prevent operation if open.
- **Poor Air Purification:** Verify that all filters are correctly installed and free from plastic packaging. Clean the pre-filter if indicated, or replace the Max2 filter if its indicator light is on. Ensure the unit is placed in an area with adequate airflow.
- **Unusual Noise:** Check for any obstructions in the air intake or outlet. Ensure the unit is on a stable, level surface. If the noise persists, contact customer support.
- **Air Quality Indicator Not Changing:** Clean the pollution sensor located on the side of the unit. Dust accumulation can affect its accuracy.

For issues not resolved by these steps, please contact Coway customer support.

6. SPECIFICATIONS

Feature	Detail
Brand	Coway
Model Number	AP-1515H
Coverage Area	Up to 1,256 sq. ft. (cleans in 30 minutes)
Filtration System	HyperCaptive (Pre-filter, Deodorization filter, True HEPA Filter)
Particle Removal	99.999% of 0.01-micron particles
VOC/Odor Reduction	99%
Smart Modes	Auto, Sleep, Eco
Air Quality Indicator	Real-time pollution monitor with color-coded LED
Noise Level	22 dB (Sleep Mode)
Product Dimensions	13.6"D x 13.6"W x 21.2"H
Item Weight	21.4 pounds
Wattage	57 watts



Figure 6: Dimensions of the Coway Airmega 300, showing its compact square footprint and height.

7. WARRANTY & SUPPORT

The Coway Airmega 300 is backed by a **5-year Limited Manufacturer's Warranty**. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical assistance, or any other inquiries, please contact Coway customer support through their official website or the contact information provided in your product packaging.