

## STRONG SRT 7007

# STRONG SRT 7007 HD Satellite Receiver User Manual

Model: SRT 7007

## 1. INTRODUCTION

The STRONG SRT 7007 HD Satellite Receiver is designed for receiving unencrypted digital TV and radio programs via satellite. This receiver supports DVB-S/S2 standards and delivers Full HD resolution. It features a pre-installed channel list for quick setup, a USB port for media playback, and versatile connectivity options including HDMI and SCART, making it compatible with both modern and older television sets. Its 12-volt compatibility also makes it suitable for mobile use, such as in camping or caravans.



**Figure 1.1:** Front view of the STRONG SRT 7007 HD Satellite Receiver. The receiver is black with a digital display showing "4000" and a green indicator light. It has power, channel, and volume buttons on the right side.

## 2. WHAT'S IN THE BOX

Please check the contents of your package. If any items are missing or damaged, contact your retailer.

- SRT 7007 HD Sat-Receiver
- Remote Control
- Power Adapter
- User Manual



Figure 2.1: The product packaging box, displaying the receiver and key features.

### 3. SETUP AND CONNECTIONS

Follow these steps to connect your STRONG SRT 7007 HD Satellite Receiver to your television and satellite dish.

#### 3.1 Rear Panel Connections



Figure 3.1: Rear panel of the receiver showing various input and output ports. From left to right: SAT IN, Ethernet, USB, HDMI, TV SCART, Audio L/R, Coaxial S/PDIF, and DC 12V power input.

1. **Satellite Antenna Connection:** Connect your satellite dish cable to the "SAT IN" port on the rear panel.
2. **Video/Audio Connection to TV:**
  - For modern TVs: Use an HDMI cable (not included) to connect the "HDMI" port on the receiver to an HDMI

input on your TV.

- For older TVs: Use a SCART cable (not included) to connect the "TV SCART" port on the receiver to the SCART input on your TV.
3. **Ethernet Connection (Optional):** Connect an Ethernet cable to the "ETHERNET" port for network features, if available and desired.
  4. **USB Connection (Optional):** Insert a USB storage device into the "USB" port for media playback or software updates.
  5. **Audio Output (Optional):** For external audio systems, use the "AUDIO L/R" RCA outputs or the "COAXIAL S/PDIF" digital audio output.
  6. **Power Connection:** Connect the provided power adapter to the "DC 12V" input on the receiver, then plug the adapter into a power outlet. The receiver also supports 12V power for camping use (adapter not included).

### 3.2 Initial Setup

Once all connections are made, power on your TV and select the correct input source (HDMI or SCART) corresponding to your receiver connection. The receiver should power on and guide you through the initial setup wizard, which typically includes language selection, country, and channel scanning. The receiver comes with a pre-installed German channel list for convenience.

## 4. OPERATING INSTRUCTIONS

---

This section provides an overview of the main functions and how to operate your receiver using the remote control.



Figure 4.1: The remote control for the SRT 7007, featuring power, number keys, navigation, volume, channel, and media playback buttons.

## 4.1 Basic Functions

- **Power On/Off:** Press the **POWER** button on the remote control or the front panel to turn the receiver on or off.
- **Channel Selection:** Use the number buttons to directly enter a channel number, or use the **CH+** / **CH-** buttons to navigate through channels.
- **Volume Control:** Use the **VOL+** / **VOL-** buttons to adjust the volume.
- **Menu Navigation:** Press the **MENU** button to access the main menu. Use the arrow keys (**▲ ▼ ◀ ▶**) to navigate and **OK** to confirm selections.
- **Electronic Program Guide (EPG):** Press the **EPG** button to view the integrated electronic TV program guide, which provides information about current and upcoming programs.

## 4.2 Multimedia Playback

The receiver supports playback of pictures, music, and video files via its USB port.

- Insert a USB storage device (e.g., USB stick or external hard drive) into the USB port on the rear panel.
- Navigate to the "Multimedia" or "USB" section in the main menu.
- Select the desired file type (Photo, Music, Video) and browse your files.
- Use the playback controls on the remote (Play, Pause, Stop, Fast Forward, Rewind) to manage media.

*Note:* Software for USB recording and Timeshift function may be available on the manufacturer's website (strong.tv).

## 5. MAINTENANCE

Proper maintenance ensures the longevity and optimal performance of your receiver.

- **Cleaning:** Disconnect the receiver from the power supply before cleaning. Use a soft, dry cloth to wipe the exterior. Do not use liquid or aerosol cleaners, as they may damage the unit.
- **Ventilation:** Ensure that the ventilation openings on the receiver are not blocked. Adequate airflow is crucial to prevent overheating.
- **Placement:** Place the receiver on a stable, flat surface away from direct sunlight, heat sources, and excessive moisture.
- **Software Updates:** Periodically check the manufacturer's website (strong.tv) for available software updates. Updates can improve performance and add new features.

## 6. TROUBLESHOOTING

If you encounter issues with your receiver, refer to the following common problems and solutions.

Problem	Possible Cause	Solution
No picture or sound	Power cable not connected Incorrect TV input selected Satellite cable disconnected	Check power connection to receiver and outlet. Ensure your TV is set to the correct HDMI or SCART input. Verify satellite cable is securely connected to "SAT IN" port.
"No Signal" message	Weak or no satellite signal Incorrect satellite settings	Check satellite dish alignment. Perform a channel scan or factory reset and re-scan channels. Ensure LNB settings are correct in the receiver menu.
Remote control not working	Batteries are dead or inserted incorrectly Obstruction between remote and receiver	Replace batteries with new AAA batteries, ensuring correct polarity. Remove any objects blocking the line of sight to the receiver's IR sensor.
Slow channel switching	Normal operation for some receivers Software issue	This can be a characteristic of the device. Check for and install any available software updates from strong.tv.

## 7. SPECIFICATIONS

Detailed technical specifications for the STRONG SRT 7007 HD Satellite Receiver.

## Digital HD Satellite Receiver SRT 7007

- Power saving: switches to standby after a definable time
- Fast and easy channel database up/download to/from USB device
- Teletext and full multi-lingual DVB subtitling supported\*
- Multiple audio track support\*
- 8 favourite lists for TV and radio channels
- Parental control for locking selected channels with a password
- Multi-lingual On Screen Display (OSD)
- Easy to use channel handling options for finding, editing, moving, favouring and locking of channels
- Power on with the last viewed channel
- Video output via: HDMI, SCART (RGB, CVBS)
- Digital audio output via S/PDIF coaxial for connection to a digital amplifier
- Automatic, network and manual channel scan options
- Supports MPEG-4 and H.264
- Supports DiSEqC 1.0, 1.1, 1.2, GOTO X, SatCR
- **Connections:** SAT IN, USB, Ethernet, HDMI, TV SCART, S/PDIF coaxial, Audio L/R, DC power
- **Accessories:** Remote control, 2x AAA batteries, power adapter

1 Subject to your local signal conditions  
 2 Dolby Digital Plus, Dolby and the double-D symbol are registered trademarks of Dolby Laboratories  
 3 STRONG cannot guarantee the playback of video files although extensions are listed, as it depends on codec used, data bit rate and resolution (all MPEG codec formats are supported).  
 4 Availability depending on broadcaster



1. Satellite antenna
2. Ethernet
3. USB
4. TV (HDMI)
5. TV (SCART)
6. Audio Hi-Fi amplifier
7. Digital audio amplifier
8. Power adapter

**Demodulator**  
 Demodulation: QPSK, 8PSK  
 Input symbol rate: DVBS-QPSK 1-45 Ms/s  
 DVBS-2 8PSK/QPSK 10-30 Ms/s  
 FEC decoder: Auto, 1/2, 2/3, 3/4, 5/6, 7/8  
 in DVBS-S mode  
 1/2, 3/5, 2/3, 3/4, 4/5, 5/6, 8/9, 9/10 in  
 DVBS-2 mode  
 3/5, 2/3, 3/4, 5/6, 8/9, 9/10 in 8PSK mode

**Video Decoder**  
 Input rate: Max. 20 Mbit/s  
 Aspect ratio: 16:9 widescreen, Pillarbox,  
 4:3 Pan&Scan, Letterbox  
 Video resolution: PAL: 50 Hz: 576i, 576p,  
 720p, 1080i, 1080p  
 NTSC: 60 Hz: 480i, 480p, 720p, 1080i,  
 1080p

**Audio Decoder**  
 Audio decoding: MPEG-1 Layer 1 & 2,  
 AC3, Dolby Digital, Downmix  
 Audio mode: Mono L/R, Stereo  
 Audio Support: E-AC3, Dolby Digital,  
 Dolby Digital Plus  
 Sampling rate: 32, 44.1, 48 kHz

**Tuner**  
 Type: 1 F-Type, EC169-24, Female  
 Input frequency range: 950 - 2150 MHz  
 RF impedance: 75 Ohm unbalanced  
 Signal level: -65 to -25 dBm  
 LNB power: 13/18 V DC (1/-5%),  
 max. 0.5 A, overload protected  
 Switch versions: DiSEqC 1.0, 1.1  
 LNB options: Universal, SatCR  
 (max. 6 users)

**Motor drive options:** DiSEqC 1.2, Go.oX  
 (DiSEqC 1.0)

**System & memory**  
 Main processor: MSTAR MSD7501  
 Flash memory: 4 MB  
 System memory: 64 MB

**Connectors**  
 SAT IN  
 RJ45 - Ethernet  
 USB 2.0 port: 5 W/800 mA (max.)  
 supported  
 HDMI  
 TV SCART (RGB, CVBS, Audio L/R)  
 3.5 mm Audio L/R  
 S/PDIF (coax.)  
 Power adapter (12 V, 1.5 A)

**General Data**  
 Power supply: AC 100 - 240 V - 50/60 Hz  
 Input voltage: DC 12 V, 1.5 A  
 Power consumption: max. 18 W, typ. 5 W  
 Power consumption in standby: max.  
 1.0 W  
 Operating temperature: 0 - 40 °C  
 Storage temperature: -10 - 50 °C  
 Operating humidity range: 10 - 85% R-H,  
 non-condensing  
 Size (W x D x H) in mm: 167 x 146 x 45  
 Weight in kg: 0.36

\*Dolby Digital, Dolby Digital Plus and the double-D symbol are registered trademarks of Dolby Laboratories

SERVICE CENTER			
AT	support_at@strong.tv +379 400 150 (9:00-18:00, Mon-Fri, 9:00-12:00, Sat)	DE	support_de@strong.tv +49 501 49 91 (9:00-18:00, Mon-Fri, 9:00-12:00, Sat)
FR	support_fr@strong.tv +33 32 634401	DK	support_dk@strong.tv +45 32 634401
ES	support_es@strong.tv +34 943 26 10	PL	support_pl@strong.tv +48 22 634 017
IT	support_it@strong.tv +39 02 634 017 (9:00-18:00, Mon-Fri, 9:00-12:00, Sat)	RU	support_ru@strong.tv +7 495 742 2811
UK	support_uk@strong.tv +44 20 326 3401	UA	support_ua@strong.tv +380 44 228 61 00

EAN SRT 7007: 8717185449365

Subject to alterations in consequence of continuous research and development technical specifications, design and appearance of products may change. HDMI, the HDMI logo and High Definition Multimedia Interface are trademarks or registered trademarks of HDMI Licensing LLC in the United States and/or other countries. Other brands and trade names from Dolby Laboratories, Dolby Digital, Dolby Digital Plus and the double-D symbol are trademarks of Dolby Laboratories. All product names are trademarks or registered trademarks of their respective owners.  
 ©STRONG 2022. All rights reserved.

www.strong.tv

Figure 7.1: A detailed diagram showing the receiver's features, connections, and technical specifications.

Feature	Detail
Model Number	SRT 7007
Manufacturer	Strong Digital GmbH

Feature	Detail
Dimensions (W x D x H)	18.7 x 14.6 x 4.5 cm
Weight	380 Grams
Connectivity Technology	USB, HDMI, SCART, Ethernet
USB Ports	1
Audio Output Mode	Surround (Dolby Audio)
Power Consumption (On-state)	5.0 watts
Energy Efficiency Class	A++
Power Supply	12 Volt (suitable for camping)
Batteries Required (Remote)	2 AAA Batteries
Channels Supported	Up to 4000 channels
EPG	8-day Electronic Program Guide
Subtitle Support	Yes

## 8. WARRANTY AND SUPPORT


For warranty information, technical support, or service inquiries, please refer to the official STRONG website or contact your local retailer.

- **Official Website:** [www.strong.tv](http://www.strong.tv)
- **Customer Service:** Refer to the contact information provided in your product packaging or on the official website for regional support.

© 2024 STRONG. All rights reserved.

This manual is for informational purposes only. Specifications are subject to change without notice.

### Related Documents - SRT 7007

	<p><a href="#">STRONG SRT 3030 Digital HD Cable Receiver User Manual</a></p> <p>This user manual provides comprehensive instructions for the STRONG SRT 3030 Digital HD Cable Receiver. It covers setup, operation, features like Timeshift and recording, troubleshooting, and technical specifications. Learn how to connect, tune channels, use the remote control, and access advanced functions for optimal viewing.</p>
---	---



# Digital HD Satellite Receiver

## SRT 7007



**User Manual**  
**Manuale de utilizare**  
**Bedienungsanleitung**  
**Manuale de l'utente**  
**Utilization manual**  
**Prüchführbuch**

**Technická příloha**  
**Manuale de tehnică**  
**Technische beilage**  
**Manuale de tehnică**  
**Technische beilage**



DVB-S2



HDMI



Dolby Digital



Dolby Digital Plus



Dolby Digital Core 3D



Dolby Digital Core 3D



Dolby Digital Core 3D



Dolby Digital Core 3D











































































































[STRONG SRT 7007 Digital HD Satellite Receiver User Manual](#)

Comprehensive user manual for the STRONG SRT 7007 Digital HD Satellite Receiver, covering installation, operation, features, troubleshooting, and technical specifications.

STRONG SRT 8208 Digital Terrestrial HD Receiver User Manual

Comprehensive user manual for the STRONG SRT 8208 Digital Terrestrial HD Receiver, covering setup, operation, connections, troubleshooting, and technical specifications. Learn how to install, configure, and use all features of your receiver.

# STRONG SRT 8215 Digital Terrestrial HD Receiver: Installation and User Guide

Comprehensive guide for installing and operating the STRONG SRT 8215 Digital Terrestrial HD Receiver. Covers setup, connections, channel tuning, features like EPG, recording, timeshift, multimedia playback, troubleshooting, and technical specifications.

STRONG SRT 7030 Digital HD Satellite Receiver User Manual

Comprehensive user manual for the STRONG SRT 7030 Digital HD Satellite Receiver, covering setup, operation, features, troubleshooting, and specifications.

[STRONG SRT 82: Guía de Usuario del Receptor HDMI Terrestre](#)

Manual completo para el receptor STRONG SRT 82, que explica la instalación, operación, características y solución de problemas de este receptor HDMI terrestre DVB-T2.