

Minka Lavery 2922-77-L

Minka Lavery High Rise LED Vanity Bath Light (Model 2922-77-L) Instruction Manual

1. IMPORTANT SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing. Consult a qualified electrician if you are unsure about electrical wiring.

- Read all instructions carefully before beginning installation.
- Ensure all electrical connections comply with local codes and ordinances, as well as the National Electric Code (NEC).
- This fixture is designed for 120-volt electrical systems.
- Do not attempt to alter the LED module. It is a non-removable fixture component.
- This product is suitable for damp indoor locations.
- Proposition 65 Warning: This product may contain chemicals known to the State of California to cause cancer and birth defects or other reproductive harm.

2. PACKAGE CONTENTS

Verify that all components are present before discarding packaging materials.

- High Rise LED Vanity Bath Light Fixture (with integrated LED Module)
- Mounting Hardware (screws, wire nuts, mounting plate)
- Mitered White Glass Shade
- Instruction Manual

3. PRODUCT SPECIFICATIONS

Feature	Detail
Model Number	2922-77-L

Dimensions (L x W x H)	4"L x 24.25"W x 5.5"H
Weight	7.6 pounds
Material	Alloy Steel, Glass
Finish	Chrome
Light Source	Integrated LED Module
Wattage	37 Watts (Total)
Brightness	2094 Lumens
Color Temperature	3000 Kelvin (Warm White)
Voltage	120 Volts
Dimmable	Yes (with compatible dimmer switch)
Certifications	ETL Certified, ADA Compliant
Location Use	Damp Indoor Locations

4. INSTALLATION INSTRUCTIONS

This fixture is designed for wall-mount installation to an existing junction box (junction box not included). Professional installation is recommended.

4.1 Prepare for Installation

- Turn off power:** Locate the circuit breaker or fuse box and turn off the power to the outlet box where you will install the fixture.
- Unpack contents:** Carefully remove all parts from the carton and ensure no damage has occurred during shipping. Keep all packaging until you are sure all parts are present.
- Identify wires:** In your junction box, identify the supply wires: typically black (hot), white (neutral), and bare copper or green (ground).

4.2 Mount the Fixture

- Attach the mounting plate (included) to the junction box using the provided screws. Ensure the plate is securely fastened.
- Make electrical connections:
 - Connect the fixture's bare copper or green ground wire to the supply ground wire using a wire nut.
 - Connect the fixture's white wire to the supply white (neutral) wire using a wire nut.
 - Connect the fixture's black wire to the supply black (hot) wire using a wire nut.
 - Carefully tuck all wires into the junction box.
- Align the fixture base with the mounting plate and secure it with the provided screws.
- Install the mitered white glass shade onto the fixture according to the diagram.



Figure 1: Front view of the Minka Lavery High Rise LED Vanity Bath Light. This image shows the overall design and the integrated LED light source behind the mitered white glass shade.



Figure 2: Angled view of the Minka Lavery High Rise LED Vanity Bath Light, highlighting the chrome finish and the structure of the glass shade.



Figure 3: Close-up view of the Minka Lavery High Rise LED Vanity Bath Light, detailing the mitered white glass shade and the chrome support brackets.

Important: Ensure all connections are tight and secure. Do not overtighten screws to avoid damaging the fixture or wiring.

5. OPERATING INSTRUCTIONS

Once installation is complete and power is restored at the circuit breaker, the fixture is ready for operation.

- **Power On/Off:** Use the wall switch connected to the fixture to turn the light on or off.
- **Dimming Function:** This fixture is dimmable. If connected to a compatible dimmer switch (not included), adjust the dimmer to control the light intensity. The light provides 3000K warm white illumination.
- **Control Method:** The fixture supports control via a push button or dimmer switch.

6. CARE AND MAINTENANCE

Proper care will ensure the longevity and appearance of your Minka Lavery vanity light.

- **Cleaning:** Always turn off the power before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
- **Glass Shade:** The glass shade can be carefully removed for cleaning. Wash with mild soap and water, rinse thoroughly, and dry completely before reattaching.
- **LED Module:** The LED module is integrated and non-removable. Do not attempt to replace individual LEDs.

7. TROUBLESHOOTING

If you experience issues with your vanity light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	- Power is off at the circuit breaker. - Loose or incorrect wiring connections. - Faulty wall switch. - Damaged LED module.	- Check the circuit breaker and ensure power is on. - Turn off power, then check all wiring connections. Re-secure if loose. - Test the wall switch with another device or replace it if faulty. - If the LED module is damaged, contact customer support for assistance.
Light flickers or dims unexpectedly.	- Incompatible dimmer switch. - Loose wiring connection.	- Ensure you are using an LED-compatible dimmer switch. - Turn off power and check wiring connections.

If the problem persists after trying these solutions, contact Minka Lavery customer support.

8. WARRANTY AND CUSTOMER SUPPORT

Manufacturer Warranty: This Minka Lavery product comes with a One Year Limited Warranty. This warranty covers defects in materials and workmanship under normal use.

For warranty claims, technical assistance, or replacement parts, please contact Minka Lavery customer support. Keep your proof of purchase for warranty service.

Contact Information: Please refer to the Minka Lavery official website or your purchase documentation for the most current customer support contact details.

Note: The integrated LED module is designed for long life and is not user-replaceable. Any attempt to modify or replace the LED module will void the warranty.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question