Manuals+

Q & A | Deep Search | Upload

manuals.plus /

- SiriusXM /
- SiriusXM Sound Station Internet Radio GDI-SXTTR2 User Manual

SiriusXM GDI-SXTTR2

SiriusXM Sound Station - Internet Radio

MODEL: GDI-SXTTR2 USER MANUAL

Brand: SiriusXM

Introduction

This manual provides comprehensive instructions for the setup, operation, maintenance, and troubleshooting of your SiriusXM Sound Station Internet Radio, model GDI-SXTTR2. Please read this manual thoroughly before using your device to ensure proper functionality and to maximize your listening experience. The SiriusXM Sound Station allows you to access SiriusXM live news, talk, sports, weather, and music channels, personalized channels, and on-demand shows via your Wi-Fi network. A SiriusXM Streaming Subscription or All Access Subscription Plan is required and sold separately.

What's in the Box:

- SiriusXM Sound Station (GDI-SXTTR2)
- Remote Control
- AC Power Adapter
- Quick Start Guide

Setup

1. Power Connection

Connect the supplied AC power adapter to the DC IN port on the back of the Sound Station and then plug the adapter into a standard electrical outlet. The unit will power on automatically or enter standby mode.

2. Network Connection (Wi-Fi)

The Sound Station requires a Wi-Fi 802.11 b/g/n wireless connection with WEP or WPA security to access SiriusXM content. An optional Ethernet adapter is sold separately if a wired connection is preferred.

- 1. Upon initial power-on, the device will guide you through the network setup process.
- 2. Use the navigation controls (typically a rotary dial and select button) to scan for available Wi-Fi networks.
- 3. Select your home Wi-Fi network from the list.

- 4. Enter your Wi-Fi password using the on-screen keyboard and navigation controls. This process can be tedious due to the rotary dial input method.
- 5. Confirm the connection. The device should indicate a successful connection.



Image: The SiriusXM Sound Station internet radio shown with its remote control. The radio features a digital display, control knobs, and a speaker grille.

3. SiriusXM Account Setup

After connecting to the internet, you will need to log in with your SiriusXM account credentials. Ensure you have an active SiriusXM Streaming or All Access subscription.

- 1. Follow the on-screen prompts to enter your SiriusXM username and password.
- 2. Use the rotary dial and select button to input characters.
- 3. Once logged in, the Sound Station will be ready to stream content.

Operating Instructions

Basic Controls

The Sound Station features intuitive controls for navigation and playback:

- Rotary Dial (Tune/Scroll): Used to scroll through menus, channels, and adjust settings.
- Select Button: Confirms selections.
- Volume Knob: Adjusts audio output level.
- Home Button: Returns to the main menu.
- Back Button: Navigates to the previous screen or menu.
- Number Buttons (0-9): For direct channel entry or preset recall.



Image: A close-up view of the SiriusXM Sound Station's display, showing channel information, album art, and control buttons.

Channel Selection and Presets

- **Browsing Channels:** Use the rotary dial to scroll through the list of available SiriusXM channels. Press the Select button to tune in.
- **Direct Channel Entry:** Use the number buttons on the unit or remote control to directly enter a channel number.
- **Setting Presets:** Tune to your desired channel. Press and hold one of the number buttons (1-10) until the display confirms the preset has been saved.
- Recalling Presets: Briefly press the corresponding number button (1-10) to instantly tune to a saved preset channel.

Playback Features

- Pause, Rewind, Replay: The Sound Station allows you to pause, rewind, and replay live radio content. Use the dedicated playback controls on the unit or remote.
- Start Now Function: On select channels, you can access the "Start Now" function to hear shows from the beginning, even if you tune in late.
- On-Demand Shows: Access a library of on-demand content through the device's menu.

Alarm System

The Sound Station includes an advanced digital alarm system:

- · Access the alarm settings through the main menu.
- Set up to 5 custom alarms with options for weekly, weekends, weekdays, or one-time activation.
- Configure snooze duration and sleep timer settings.

Auxiliary Input

The unit features an integrated auxiliary input jack, allowing you to connect external audio devices (e.g., MP3 players, smartphones) using a 3.5mm audio cable (not included). Select the auxiliary input source from the device's menu to play audio from the connected device.

Maintenance

Cleaning

To maintain the appearance and functionality of your Sound Station:

- Unplug the unit from the power outlet before cleaning.
- Use a soft, dry cloth to wipe the exterior surfaces.
- Do not use liquid cleaners, abrasive cleaners, or solvents, as these may damage the finish.
- Avoid spraying cleaners directly onto the unit.

Firmware Updates

The Sound Station may periodically receive firmware updates to improve performance or add new features. The device will typically prompt you when an update is available. It is generally recommended to install updates, but be aware that some updates may introduce unforeseen issues. Ensure a stable power connection during any update process.

Troubleshooting

If you encounter issues with your SiriusXM Sound Station, refer to the following common problems and solutions:

Problem	Possible Cause / Solution
No Power	Ensure the AC power adapter is securely connected to both the unit and a working electrical outlet. Check if the power outlet is functional by plugging in another device.
No Wi-Fi Connection / Cannot Connect to Network	Verify your Wi-Fi network is active and broadcasting. Double-check the Wi-Fi password entered. Move the Sound Station closer to your Wi-Fi router to improve signal strength. Restart your Wi-Fi router and the Sound Station.

Problem	Possible Cause / Solution
"Playback stopped - Invalid Session (208)" Error	This error may occur if your SiriusXM account is logged in on multiple devices simultaneously. Unplug the power adapter from the Sound Station, wait a few seconds, and plug it back in to force a reboot. Ensure no other devices are actively streaming from your SiriusXM account. If the issue persists after a firmware update, contact SiriusXM customer support.
Poor Sound Quality / Crackling	Ensure the unit is placed on a stable surface and not obstructed. Check your Wi-Fi signal strength; a weak signal can cause audio interruptions. If using the auxiliary input, ensure the cable is fully inserted and undamaged.
Remote Control Not Working	Check and replace the batteries in the remote control. Ensure there are no obstructions between the remote and the Sound Station's IR receiver.

If these solutions do not resolve your issue, please refer to the Support section for further assistance.

Specifications

Feature	Detail
Model Number	GDI-SXTTR2
Product Dimensions	5.25 x 10.75 x 6 inches
Item Weight	3 pounds
Connectivity Technology	Wi-Fi (802.11 b/g/n)
Tuner Technology	Internet Radio
Power Source	AC (Input: 100-240 VAC, 50/60 Hz, 0.2 A)
Special Feature	Alarm
Color	BLACK
Included Components	SiriusXM Sound Station, Remote Control, AC Power Adapter, Quick Start Guide

Warranty and Support

Warranty information for your SiriusXM Sound Station is typically provided with your purchase documentation. Please refer to the warranty card or the original packaging for details regarding coverage and terms. For technical support, customer service, or further assistance with your SiriusXM subscription, please contact

SiriusXM directly. You can often find support contact information on the official SiriusXM website or within your account details.

For product-specific inquiries related to the hardware, you may also refer to Grace Digital's support resources, as they are the manufacturer of this device.

Online Resources:

- · SiriusXM Official Website
- · Grace Digital Official Website

Related Documents - GDI-SXTTR2

