

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Masterplug](#) /

› [Masterplug 60ft Cord Reel User Manual](#)

### Masterplug OMA601114G4SL-US

## Masterplug 60ft Cord Reel User Manual

Model: OMA601114G4SL-US

### PRODUCT OVERVIEW

The Masterplug 60ft Cord Reel is a retractable extension lead designed for convenient power distribution. It features a winding handle, a safety overload circuit breaker, and an integrated power switch. This unit provides four grounded outlets and utilizes a 14AWG cable, rated for 13 amps, making it suitable for various household, DIY, and commercial applications.



Figure 1: Masterplug 60ft Cord Reel, showcasing its compact design and integrated outlets.

## KEY FEATURES

- **60ft Extension Cord:** Provides extended reach for power access in various locations.
- **4 Shuttered Power Outlets:** Offers multiple connection points for appliances, with safety shutters for protection.
- **LED Indicator:** Visually confirms when power is live to the outlets.
- **Integrated Power Switch:** Allows for convenient control of power directly at the reel.
- **Safety Overload Circuit Breaker:** Automatically cuts power in case of an overload, protecting connected devices and the unit. A reset button is provided.
- **Winding Handle & Cord Guide:** Facilitates easy, tangle-free winding and unwinding of the cable.
- **High Visibility 14AWG Cable:** Durable 14-gauge cable with bright coloring for enhanced safety and visibility.
- **Heavy Duty Steel Stand:** Provides stability and durability for the cord reel.



## LOCALIZED POWER SWITCH

Control the power where you are working



## 4X POWER OUTLETS

Safety shuttered power outlets allow you to use safely



## POWER LED INDICATOR

LED indicator shows that power is live



## SAFETY OVERLOAD

Cuts the power in the event of a power overload

Figure 2: Detailed view of the control panel, highlighting the power switch, outlets, LED, and overload protection.



Figure 3: Overview of the cord reel's ergonomic design, including the carry handle and cord guide.

## SETUP

- Unpack the Unit:** Carefully remove the Masterplug Cord Reel from its packaging. Ensure all components, including the reel and any included accessories, are present and undamaged.
- Position the Reel:** Place the cord reel on a stable, flat surface. The heavy-duty steel stand provides stability. Ensure the reel is positioned away from water sources or excessive moisture.
- Unwind the Cable:** To extend the cable, grasp the plug end and pull the cable away from the reel. The integrated cord guide will help prevent tangles. Unwind only the necessary length of cable for your task.
- Connect to Power Source:** Plug the main power cord of the reel into a suitable grounded 120V wall outlet.
- Wall Mounting (Optional):** If wall mounting is desired, use the provided wall mount bracket (if included) and appropriate fasteners to secure it to a sturdy surface. The reel can then be easily attached and detached from the bracket.

## OPERATING INSTRUCTIONS

- Powering On:** After plugging the reel into a wall outlet, press the red "ON-OFF" switch located on the face of the reel to the "ON" position. The power LED indicator will illuminate, confirming that power is live to the outlets.
- Connecting Appliances:** Plug your electrical appliances or power tools into any of the four shuttered outlets on the reel. Ensure that the total current draw of all connected devices does not exceed 13 amps.
- Monitoring Overload:** The safety overload circuit breaker will trip and cut power if the connected load exceeds 13 amps. If this occurs, disconnect some appliances, then press the red "SAFETY OVERLOAD" reset button to restore power.
- Powering Off:** To turn off power to the outlets, press the red "ON-OFF" switch to the "OFF" position.
- Rewinding the Cable:** When finished, disconnect all appliances. Use the winding handle on the side of the reel to neatly retract the cable. The integrated cord guide will assist in smooth, tangle-free winding.

Your browser does not support the video tag.

Video 1: Official Masterplug video demonstrating the features and operation of the cord reel, including winding and power distribution.

## MAINTENANCE

- Regular Inspection:** Periodically inspect the entire length of the cable for any signs of damage, cuts, fraying, or exposed wires. Check the plug, outlets, and casing for cracks or loose connections.
- Cleaning:** Ensure the unit is unplugged from the power source before cleaning. Wipe the reel and cable with a dry or slightly damp cloth. Do not use harsh chemicals or abrasive cleaners.
- Storage:** Store the cord reel in a dry, cool place away from direct sunlight and extreme temperatures. Ensure the cable is fully wound onto the reel to prevent kinks and damage.
- Avoid Overloading:** Always adhere to the 13-amp maximum load capacity to prevent damage to the unit and potential hazards.

## TROUBLESHOOTING

Problem	Possible Cause	Solution
No power to outlets.	Reel not plugged into wall outlet. Power switch is OFF. Safety overload tripped. Wall outlet has no power.	Ensure reel is securely plugged into a live wall outlet. Press the ON-OFF switch to the ON position. Reduce load, then press the red SAFETY OVERLOAD reset button. Test the wall outlet with another device or check your home's circuit breaker.
Cable does not retract smoothly.	Cable is tangled or twisted. Obstruction in the cord guide.	Ensure the cable is free of twists before winding. Check the cord guide for any debris and clear it.
Power LED not illuminated.	No power to the reel. LED malfunction.	Verify the reel is plugged in and the power switch is ON. If power is confirmed but LED is off, the unit may still function, but contact support if concerned.

## SPECIFICATIONS

Feature	Detail
Model Number	OMA601114G4SL-US
Cable Length	60 feet
Wire Gauge	14 AWG
Amperage Rating	13 Amps
Number of Outlets	4 (Grounded)
Voltage	120 Volts
Plug Format	Type B
Product Dimensions	9.75 x 2.5 x 4.5 inches
Item Weight	8.6 pounds
Manufacturer	Luceco plc





Figure 4: Product dimensions for the Masterplug 60ft Cord Reel.


## WARRANTY & SUPPORT

The Masterplug 60ft Cord Reel comes with a **3-year warranty** from the date of purchase, covering defects in materials and workmanship under normal use. For warranty claims, technical support, or any inquiries regarding your product, please contact Masterplug customer service.

Please refer to the official Masterplug website or your product packaging for the most current contact information and detailed warranty terms.

## Related Documents - OMA601114G4SL-US

	<p><a href="#">Masterplug 80ft Large Open Reel OLA80111464SL-US Technical Specification and User Guide</a></p> <p>Technical specifications and user instructions for the Masterplug 80ft Large Open Reel (Model OLA80111464SL-US). Features include 4 surge-protected 120V sockets, a 13A thermal breaker with reset button, an integrated on/off switch, and a power LED indicator. This 80ft green cable reel is designed for home, yard, and light industrial use, offering a maximum load of 1560W.</p>
	<p><a href="#">Masterplug Product Manuals: Extension Leads, Cable Reels, Timers, and Surge Protectors</a></p> <p>Comprehensive user manuals and assembly instructions for a range of Masterplug electrical products, including extension leads, cable reels, weatherproof sockets, countdown timers, immersion heater timers, and surge protectors. This guide provides essential safety information, operating instructions, and technical specifications.</p>
	<p><a href="#">Masterplug Outdoor Power Extension Lead with Cable Tidy CTx13   Safe Garden &amp; DIY Use</a></p> <p>Discover the Masterplug Outdoor Power Extension Lead with Cable Tidy (CTx13). Features a single socket, 13A fused plug, and manufactured to BS1363-2 for safe garden and light DIY power solutions.</p>
	<p><a href="#">Masterplug WBXBFG8BTMS24 Outdoor Weatherproof Power Box with Timer</a></p> <p>The Masterplug WBXBFG8BTMS24 is an IP54 rated outdoor weatherproof power box designed for safe power solutions for garden and light DIY use. It features a 24-hour timer, multiple outlets, and robust construction.</p>
	<p><a href="#">Masterplug Outdoor Power Weatherproof Box (WBX) - Installation and Safety Guide</a></p> <p>Comprehensive guide to the Masterplug Outdoor Power Weatherproof Box (WBX), detailing features, technical specifications, safety warnings, and installation instructions for safe outdoor power solutions.</p>



## [Masterplug Mode 2 EV Charger User Guide: Safety, Operation, and Troubleshooting](#)

Official user guide for the Masterplug Mode 2 EV Charger (EVCM2216xx/G-EU). Provides essential safety instructions, operating procedures, indicator status explanations, fault troubleshooting, technical specifications, and care guidelines for electric and hybrid vehicles.