

## Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [Sea Gull Lighting](#) /

› [Sea Gull Lighting Lonoke 5240703-782 Three-Light Pendant Fixture Instruction Manual](#)

## Sea Gull Lighting 5240703-782

# Sea Gull Lighting Lonoke 5240703-782 Three-Light Pendant Fixture Instruction Manual

Model: 5240703-782

## INTRODUCTION

This instruction manual provides detailed guidance for the safe installation, operation, and maintenance of your Sea Gull Lighting Lonoke Medium Three-Light Hall / Foyer Hanging Modern Light Fixture (Model 5240703-782). Please read all instructions carefully before beginning installation and retain this manual for future reference.

## SAFETY INFORMATION

- **WARNING:** To avoid electric shock, always disconnect power at the main circuit breaker or fuse box before installation or servicing.
- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC). If you are unfamiliar with proper electrical wiring connections, consult a qualified electrician.
- This fixture is designed for indoor use in damp locations. Do not install in areas exposed to direct water spray or submersion.
- Ensure the mounting surface can support the weight of the fixture.
- Use only the specified bulb type and wattage. Refer to the "Specifications" section for details.
- Do not attempt to alter the fixture in any way.

## PACKAGE CONTENTS

Carefully unpack your fixture and inspect for any damage. Keep all packaging materials until you are sure the fixture is in working order.

- A. Fixture Body (Lonoke Medium Three-Light Pendant)
- B. Mounting Hardware (Crossbar, Screws, Wire Nuts)
- C. Canopy
- D. Chain and Loop
- E. Instruction Manual

**Note:** Light bulbs are not included and must be purchased separately.

## SPECIFICATIONS

<b>Model Number</b>	5240703-782
<b>Brand</b>	Sea Gull Lighting
<b>Finish</b>	Heirloom Bronze
<b>Material</b>	Alloy Steel, Glass (Shade)
<b>Dimensions (L x W x H)</b>	17" x 20" x 7.75"
<b>Number of Lights</b>	3
<b>Light Source Type</b>	Torpedo Candelabra (E12 Base)
<b>Max Wattage per Bulb</b>	60 Watts
<b>Voltage</b>	120 Volts
<b>Indoor/Outdoor Usage</b>	Indoor (Damp Location Rated)
<b>Compliance</b>	Title 24 Compliant (with JA8 approved bulbs)

## SETUP AND INSTALLATION

Before you begin, ensure all necessary tools are available (screwdriver, wire strippers, electrical tape, ladder, safety glasses). It is recommended to have a second person assist with installation.

### Step 1: Prepare for Installation

1. **Turn off power** at the circuit breaker or fuse box to the outlet box where the fixture will be installed.
2. Remove any existing fixture from the outlet box.
3. Carefully unpack the new fixture and its components.

### Step 2: Assemble the Fixture

Follow the specific assembly instructions provided in the packaging for connecting the chain to the fixture body and canopy. Adjust the chain length to achieve the desired hanging height.





**Figure 1:** Overview of the Sea Gull Lighting Lonoke Three-Light Pendant Fixture. This image shows the heirloom bronze finish, the open cage design, and the three candelabra-style bulb sockets within the fixture.

### **Step 3: Mount the Fixture**

1. Attach the mounting crossbar to the outlet box using the provided screws.
2. Thread the fixture wires through the center hole of the crossbar and into the outlet box.
3. Connect the fixture's ground wire (usually bare copper or green) to the ground wire from the outlet box (usually bare copper or green) and to the ground screw on the mounting crossbar.
4. Connect the fixture's white wire to the white (neutral) wire from the outlet box using a wire nut.
5. Connect the fixture's black wire to the black (hot) wire from the outlet box using a wire nut.
6. Carefully tuck all wires into the outlet box.

7. Secure the canopy to the mounting crossbar, ensuring it is flush with the ceiling.

#### Step 4: Install Light Bulbs

1. Screw three (3) Torpedo Candelabra (E12 base) bulbs into the sockets. Do not exceed 60 watts per bulb.
2. For Title 24 compliance, use Joint Appendix (JA8) approved light bulbs listed in the California Energy Commission Appliance database.

#### Step 5: Restore Power

Once installation is complete, restore power at the main circuit breaker or fuse box and test the fixture.

### OPERATING INSTRUCTIONS

This fixture operates via a standard wall switch connected to the electrical circuit. Simply toggle the wall switch to turn the light fixture on or off. If connected to a dimmer switch, ensure the bulbs used are dimmable and compatible with the dimmer.

The product specifications mention "Control Method: App". If you intend to use app control, this functionality is typically provided by smart bulbs or a smart switch connected to the fixture, not by the fixture itself. Refer to the instructions for your smart bulbs or smart switch for setup and operation.

### MAINTENANCE

- **Cleaning:** To clean the fixture, ensure power is off. Wipe with a soft, dry cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
- **Bulb Replacement:** Always turn off power before replacing bulbs. Allow bulbs to cool completely before touching. Replace with the same type and wattage as specified in the "Specifications" section.

### TROUBLESHOOTING

Problem	Possible Cause / Solution
Fixture does not light.	<ul style="list-style-type: none"><li>• Power is off at the circuit breaker. <b>Solution:</b> Check the circuit breaker and ensure it is in the ON position.</li><li>• Loose or incorrect wiring connections. <b>Solution:</b> Turn off power, check all wiring connections, and re-secure if necessary.</li><li>• Bulbs are faulty or incorrectly installed. <b>Solution:</b> Ensure bulbs are screwed in tightly and are not burnt out. Replace if needed.</li><li>• Faulty wall switch. <b>Solution:</b> Test the wall switch with another device or consult an electrician.</li></ul>
Flickering lights.	<ul style="list-style-type: none"><li>• Loose bulb connection. <b>Solution:</b> Turn off power, tighten bulbs.</li><li>• Incompatible dimmer switch or bulbs. <b>Solution:</b> Ensure both dimmer and bulbs are compatible.</li></ul>

### WARRANTY AND SUPPORT

The product specifications indicate "Warranty Description: N/a." For specific warranty information, please refer to the documentation included with your purchase or contact Sea Gull Lighting directly.

For technical support or further assistance, please visit the official Sea Gull Lighting website or contact their customer service department. Contact information can typically be found on the manufacturer's website or on the product packaging.

