

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

[manuals.plus](#) /

› [Craftmade](#) /

› [Craftmade CPJM-1PNK Design-A-Fixture Mini Pendant Lighting Instruction Manual](#)

Craftmade CPJM-1PNK

Craftmade CPJM-1PNK Design-A-Fixture Mini Pendant Lighting Instruction Manual

Model: CPJM-1PNK

INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Craftmade CPJM-1PNK Design-A-Fixture Mini Pendant Lighting. Please read all instructions carefully before beginning installation and retain this manual for future reference.

SAFETY INFORMATION

To reduce the risk of fire, electric shock, or personal injury, always follow these basic safety precautions:

- **Disconnect Power:** Always turn off the electrical supply at the main fuse box or circuit breaker before installing, servicing, or cleaning the fixture.
- **Qualified Electrician:** If you are unsure about the installation process, consult a qualified electrician.
- **Indoor Use Only:** This fixture is rated for indoor locations only. Do not install in wet or damp areas.
- **Proper Wiring:** Ensure all electrical connections are made in accordance with local codes and ordinances, as well as the National Electric Code (NEC).
- **Bulb Specifications:** Use only the specified bulb type and wattage (E26 base, maximum 60 watts incandescent or equivalent LED/CFL). Exceeding the maximum wattage may cause overheating.
- **Secure Mounting:** Ensure the fixture is securely mounted to a structurally sound junction box.

PACKAGE CONTENTS

Verify that all components listed below are present and undamaged:

- Pendant Fixture Assembly (CPJM-1PNK)
- Extension Rods (Two 6-inch, Two 12-inch)
- Mounting Hardware (for junction box)

Note: Light bulb(s) and junction box are not included.

INSTALLATION (SETUP)

Follow these steps to install your pendant light:

- 1. Prepare for Installation:** Turn off power at the circuit breaker or fuse box. Ensure the power is completely disconnected before proceeding.
- 2. Assemble Downrod:** Determine the desired hanging height for your pendant. Connect the appropriate combination of 6-inch and 12-inch extension rods to the fixture body and the canopy. Ensure all connections are secure.
- 3. Wiring Connections:** Carefully connect the fixture's electrical wires to the corresponding wires from the junction box. Typically, connect the black fixture wire to the black (live) supply wire, the white fixture wire to the white (neutral) supply wire, and the bare copper or green fixture wire to the green or bare copper (ground) supply wire. Use approved wire connectors and ensure all connections are tight.
- 4. Mount Fixture:** Securely attach the canopy to the existing junction box using the provided mounting hardware. Ensure the fixture is stable and flush against the ceiling.
- 5. Install Bulb:** Insert one E26 base, maximum 60-watt incandescent bulb (or equivalent LED/CFL) into the socket. Do not overtighten.
- 6. Restore Power:** Once installation is complete and all connections are secure, restore power at the circuit breaker or fuse box.





This image displays the Craftmade CPJM-1PNK mini pendant light. It features a polished nickel finish, with a circular canopy at the top, a long slender downrod, and a bell-shaped socket housing at the bottom designed to hold an E26 base bulb. The overall design is sleek and minimalist.

OPERATION

The Craftmade CPJM-1PNK pendant light is operated via a standard wall switch. For dimming functionality, ensure you are using a dimmable E26 bulb and a compatible dimmer switch (not included) installed in your electrical system.

MAINTENANCE

Regular maintenance ensures the longevity and appearance of your fixture.

- **Cleaning:** Disconnect power before cleaning. Wipe the fixture with a soft, dry cloth. Avoid using abrasive cleaners, solvents, or polishes as they may damage the finish.
- **Bulb Replacement:** Ensure power is off and the bulb has cooled completely before attempting to replace it. Unscrew the old bulb and screw in a new E26 base, maximum 60-watt incandescent or equivalent LED/CFL bulb.

TROUBLESHOOTING

If you encounter issues with your pendant light, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not illuminate.	No power to the fixture.	Check circuit breaker or fuse. Ensure wall switch is ON.
	Bulb is faulty or loose.	Replace bulb or tighten it securely.
	Incorrect wiring connection.	Turn off power and recheck wiring connections. Consult an electrician if necessary.
Dimming function does not work.	Non-dimmable bulb used.	Replace with a dimmable E26 bulb.
	Incompatible dimmer switch.	Ensure a compatible dimmer switch is installed.

SPECIFICATIONS

Feature	Detail
Brand	Craftmade
Model Number	CPJM-1PNK
Model Name	One Light Mini Pendant Hardware
Dimensions (L x W x H)	6 x 5.25 x 40 inches
Item Weight	9.75 pounds
Color	Brushed Polished Nickel
Finish	Polished
Material	Alloy Steel
Light Fixture Form	Pendant
Indoor/Outdoor Usage	Indoor
Number of Light Sources	1
Max Wattage	60 watts
Bulb Base	E26
Voltage	120 Volts
Special Feature	Dimmable
Certification	ETL Listed

WARRANTY AND SUPPORT

This Craftmade product is covered by a manufacturer's warranty. For specific warranty details, please refer to the documentation included with your purchase or visit the official Craftmade website. For technical support or

assistance with parts, please contact Craftmade customer service directly.

Craftmade Customer Service: Refer to your product packaging or the Craftmade website for current contact information.