

[manuals.plus](#) /› [HUION](#) /› [HUION Inspiroy Q11K Wireless Graphic Drawing Tablet User Manual](#)

## HUION Q11K

# HUION Inspiroy Q11K Wireless Graphic Drawing Tablet User Manual

Model: Q11K

## 1. INTRODUCTION

Thank you for choosing the HUION Inspiroy Q11K Wireless Graphic Drawing Tablet. This manual provides essential information for setting up, operating, and maintaining your device. The Inspiroy Q11K is designed to enhance your digital creative experience with its advanced features and user-friendly design.

Key features include:

- **8192 Pen Pressure Levels:** For precise and natural drawing.
- **Wireless Connectivity:** Offers a cable-free workspace.
- **8 Customizable Shortcut Keys:** For improved workflow efficiency.
- **Large Active Area:** 11 x 6.87 inches for ample creative space.
- **Long Battery Life:** Over 40 hours of continuous use.
- **Ergonomic Design:** For comfortable extended use.

## 2. WHAT'S IN THE BOX

Please check the package contents to ensure all items are present:

- HUION Inspiroy Q11K Graphics Tablet
- Rechargeable Pen PF150
- Wireless Receiver
- Pen Stand
- 8 Pen Nibs (packed inside the Pen Box)
- Micro USB Cable
- Pen Charging Cable
- Quick Start Guide
- Installation CD

# Accessories



Pen Stand




Pen Box  
(Stylus Pen+8 Pen Nibs+USB Wireless Receiver)



Micro USB Cable



Pen Charge Cable



Installation CD

Image: Package contents including the tablet, pen, cables, pen stand, and nibs.

## 3. SETUP

### 1. Driver Installation:

- Insert the provided Installation CD into your computer's CD-ROM drive. Follow the on-screen instructions to install the tablet driver.
- Alternatively, download the latest driver from the official HUION website ([www.huion.com](http://www.huion.com)) for your specific operating system (Windows 7 or later, macOS 10.11 or later).
- Ensure any previous tablet drivers are uninstalled before installing the HUION driver.

### 2. Connecting the Tablet:

- Wireless Connection:** Plug the Wireless Receiver into an available USB port on your computer. Turn on the tablet using the power switch. The tablet will automatically connect.
- Wired Connection:** Connect the Micro USB Cable from the tablet to an available USB port on your computer.

### 3. Pen Setup:

- The PF150 pen is rechargeable. Connect the Pen Charging Cable to the pen and a USB power source to charge it before first use.
- To replace a nib, use the built-in nib extractor by unscrewing the pen stand.



Image: The tablet connected wirelessly to a computer, highlighting the 2.4GHz wireless connection.

Video: Official HUION guide on how to use the pen tablet, demonstrating basic setup and functionality.

## 4. OPERATING INSTRUCTIONS

### 4.1 Pen Usage

The new rechargeable PF150 pen offers 8192 levels of pressure sensitivity, allowing for precise control over line thickness and opacity. Its ergonomic design provides a comfortable grip for a natural drawing experience.

# Rechargeable Pen PF150

Revolutionary Upgrade

8192 Pen Pressure Sensitivity Levels



Image: The Rechargeable Pen PF150 demonstrating 8192 pressure sensitivity.

## 4.2 Customizable Shortcut Keys

The tablet features 8 customizable shortcut keys. These keys can be programmed to your favorite functions, enhancing efficiency and convenience during your creative process.

## Simply Switch Off to Avoid Accidental Touch



Image: The tablet highlighting its 8 customizable express keys.

### 4.3 Wireless Connectivity

Enjoy a cable-free work experience with the 2.4GHz wireless connectivity, contributing to a tidier desktop environment. The built-in 2500mAh battery provides over 40 hours of continuous battery life.

# Premium Material Inside Out



Image: Close-up of the tablet's side, showing the Micro USB port, power switch, and battery capacity.

## 4.4 Active Area and Ergonomics

The tablet offers a generous 11 x 6.87-inch active drawing area, made with high-end materials for a paper-like finish. Its curvy edges, round corners, and smooth surface are ergonomically designed to provide extra comfort, reducing fatigue during long working hours.

# Professionale e Grande Area Attiva



Image: The tablet displaying its large 11-inch active drawing area dimensions.

Video: A brief overview of the Huion Inspiroy Q11K Graphics Tablet, showcasing its design and features.

## 5. MAINTENANCE

- Cleaning:** Use a soft, dry, lint-free cloth to clean the tablet surface. Avoid using harsh chemicals or abrasive materials.
- Pen Nibs:** Replace pen nibs when they show signs of wear to maintain optimal performance. Extra nibs are provided in the pen stand.
- Battery Care:** Charge the pen and tablet regularly to prolong battery life. Avoid completely draining the battery frequently.

## 6. TROUBLESHOOTING

- **No Pen Response:**
  - Ensure the tablet is powered on and the wireless receiver is properly connected, or the USB cable is securely plugged in.
  - Check if the pen battery is charged.
  - Verify that the driver is correctly installed and running.
- **Driver Issues:**
  - If you experience unexpected behavior, try reinstalling the latest driver from the HUION website.
  - Ensure no other tablet drivers are conflicting with the HUION driver.
- **Connection Problems:**
  - For wireless connection, try a different USB port for the receiver or move closer to the computer to reduce interference.
  - For wired connection, ensure the Micro USB cable is not damaged and is firmly connected.

For further assistance, please visit the official HUION support website or contact customer service.

## 7. SPECIFICATIONS

Feature	Detail
Product Dimensions	15.35 x 8.78 x 0.43 inches
Item Weight	1.94 pounds
Item Model Number	Q11K
Batteries	1 Lithium Ion battery required
Brand	HUION
Connectivity Technology	USB (Wireless 2.4GHz)
Pressure Sensitivity	8192 Levels
Operating System	Windows 7 or later, macOS 10.11 or later
Special Feature	Ergonomic, Programmable Press Key

## 8. WARRANTY AND SUPPORT

For warranty information and technical support, please refer to the warranty card included in your package or visit the official HUION website:

[HUION Support Page](#)

You can also find FAQs, driver downloads, and contact information for customer service on their website.

