

[Manuals.plus](#) /

› [Logitech](#) /

› Logitech M585 Wireless Mouse User Manual

Logitech M585

Logitech M585 Wireless Mouse User Manual

Model: M585 | Brand: Logitech

INTRODUCTION

This manual provides detailed instructions for setting up, operating, and maintaining your Logitech M585 Multi-Device Wireless Mouse. The M585 mouse is designed for enhanced productivity, featuring multi-device connectivity and Logitech FLOW technology for seamless cross-computer control.



Figure 1: Logitech M585 Wireless Mouse, showing its ergonomic design and multi-device indicator lights.

WHAT'S IN THE BOX

- Logitech M585 Wireless Mouse
- 1 AA Battery (pre-installed or included separately)
- USB Unifying Receiver
- User Documentation (this manual)

SETUP

1. Battery Installation

1. Locate the battery compartment on the underside of the mouse.
2. Slide the battery compartment cover off.
3. Insert the included AA battery, ensuring correct polarity (+/-).
4. Replace the battery compartment cover.





Figure 2: Underside of the M585 mouse, showing the battery compartment and ON/OFF switch.

2. Connecting Your Mouse

The M585 mouse offers two connection options: Logitech Unifying Receiver (2.4 GHz wireless) or Bluetooth Low Energy.

Option A: Using the Logitech Unifying Receiver

1. Remove the USB Unifying Receiver from the battery compartment of the mouse.
2. Plug the Unifying Receiver into an available USB port on your computer.
3. Turn on the mouse using the ON/OFF switch on the bottom.
4. The mouse should automatically connect. If not, download and install Logitech Options software from logitech.com/options to complete the pairing process.

Option B: Using Bluetooth Low Energy

1. Turn on the mouse using the ON/OFF switch on the bottom.
2. Press and hold the Easy-Switch button (located below the scroll wheel) for 3 seconds until the LED indicator starts blinking rapidly. This puts the mouse in pairing mode.
3. On your computer, open Bluetooth settings:
 - **Windows:** Go to Start > Settings > Devices > Bluetooth & other devices. Click "Add Bluetooth or other device" and select "Bluetooth".
 - **macOS:** Go to Apple menu > System Preferences > Bluetooth.
4. Select "Logitech M585" from the list of available devices and follow the on-screen prompts to complete pairing.

3. Logitech FLOW Setup (Optional)

Logitech FLOW allows you to seamlessly control multiple computers with a single M585 mouse and copy-paste text, images, and files between them.

1. Ensure both computers are connected to the same network (Wi-Fi or Ethernet).
2. Download and install Logitech Options software on both computers from logitech.com/options.
3. Open Logitech Options on both computers and navigate to the "FLOW" tab.
4. Follow the on-screen instructions to enable and configure FLOW. You can arrange your computer screens virtually to match their physical layout.

OPERATING YOUR MOUSE

Basic Functions

- **Left Click:** Primary selection and activation.
- **Right Click:** Opens context menus.
- **Scroll Wheel:** Scrolls vertically. Pressing the scroll wheel acts as a middle click.

- **Tilt Scroll:** Tilt the scroll wheel left or right for horizontal scrolling (requires Logitech Options software).

Programmable Buttons

The M585 features five programmable buttons, including two thumb buttons and the middle click button. These can be customized using Logitech Options software.



Figure 3: Side view of the M585 mouse, highlighting the two programmable thumb buttons.

- **Thumb Buttons:** By default, these act as Forward/Back buttons in web browsers. Customize them for other functions like copy, paste, or application switching.
- **Middle Click:** Can be assigned to open new tabs, close tabs, or other functions.

Switching Between Devices

Use the Easy-Switch button (labeled 1 and 2) located below the scroll wheel to switch between connected computers. The LED indicator will light up next to the number corresponding to the active device.

- Press the Easy-Switch button once to cycle to the next paired device.
- The LED will briefly illuminate to indicate which channel is active.

MAINTENANCE

Cleaning Your Mouse

To ensure optimal performance, periodically clean your mouse.

- Turn off the mouse before cleaning.
- Use a soft, lint-free cloth slightly dampened with water or an alcohol-based cleaner (avoid harsh chemicals).
- Gently wipe the surface of the mouse.
- Use a cotton swab or compressed air to clean around the scroll wheel and buttons.

Battery Replacement

The M585 mouse has an approximate battery life of 2 years. When the battery is low, the LED indicator on the mouse may blink red. Replace the AA battery as described in the "Battery Installation" section.

TROUBLESHOOTING

Problem	Solution
Mouse not responding	• Ensure the mouse is turned ON. • Check battery level and replace if necessary. • For Unifying Receiver: Try plugging the receiver into a different USB port. • For Bluetooth: Ensure Bluetooth is enabled on your computer and the mouse is paired. Try re-pairing. • Try restarting your computer.
Lagging or erratic cursor movement	• Ensure the mouse is on a clean, non-reflective surface. • Move the mouse closer to the Unifying Receiver or Bluetooth adapter. • Avoid using the mouse near other wireless devices that might cause interference (e.g., Wi-Fi routers, cordless phones). • Clean the optical sensor on the bottom of the mouse.
Logitech FLOW not working	• Ensure both computers are on the same network. • Verify Logitech Options software is installed and running on both computers. • Check FLOW settings in Logitech Options to ensure it's enabled and configured correctly. • Temporarily disable firewalls on both computers to test if they are blocking the connection.
Buttons not programmable	• Ensure Logitech Options software is installed and up to date. • Restart the Logitech Options software or your computer.

SPECIFICATIONS

Feature	Detail
Model Number	910-005012
Connectivity	Bluetooth Low Energy, 2.4 GHz Wireless (Logitech Unifying Receiver)
Sensor Technology	Optical
Number of Buttons	7 (Left/Right-click, Scroll wheel with middle click, Easy-Switch, 2 Thumb buttons)
Scroll Wheel	Precision scroll wheel with tilt function
Battery Type	1 AA battery (included)
Battery Life	Up to 24 months (may vary based on usage)
Wireless Operating Distance	10 meters (33 feet)

Feature	Detail
Dimensions (HxWxD)	4.05 x 3.27 x 4.96 inches (approx.)
Weight	3.52 ounces (with battery)
System Requirements	• Bluetooth: Windows 10 or later, Windows 8, macOS X 10.10 or later, Chrome OS, Android 5.0 or later • Unifying Receiver: Windows 10 or later, Windows 8, Windows 7, macOS X 10.05 or later, Chrome OS • Internet connection for software download



Figure 4: Dimensions of the Logitech M585 Wireless Mouse.

Logitech products are manufactured to the highest quality standards. For detailed warranty information, please refer to the warranty card included with your product or visit the official Logitech website.

For technical support, FAQs, and driver downloads, please visit the Logitech support page:

support.logi.com

You can also find additional resources and community forums on the Logitech website.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page’s manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question