Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

E-SONIC MQ-U350

E-SONIC MQ-U350 8GB USB Voice Recorder Instruction Manual

Introduction

This manual provides detailed instructions for the E-SONIC MQ-U350 8GB USB Voice Recorder. Please read this document thoroughly to ensure proper use, optimal performance, and longevity of your device. Keep this manual for future reference.

Product Overview

The E-SONIC MQ-U350 is a compact, discreet USB digital voice recorder designed for high-quality audio capture. It integrates voice-activated recording (SVOS) and 8GB of internal storage within a standard USB flash drive form factor.

Key Features

- 8GB Internal Storage Capacity
- Super Voice Operated System (SVOS) for automatic recording activation
- Up to 25 days standby time
- Discreet USB Type design
- High-Quality Recording modes (XHQ/HQ)
- Date & Time Stamp for recordings
- 5-level SVOS sensitivity setting
- Hidden Recording On/Off Switch
- Automatic Recording Level Control (ALC)
- High portability



This image displays the front of the E-SONIC MQ-U350 voice recorder's retail packaging. It highlights key features such as 'USB Memory & Mini Digital Voice Recorder', 'MQ-U350', 'Super Voice Operated System (SVOS)', '25 Days' standby time, and 'Date & Time Stamp'. The packaging also indicates 'Made in KOREA'.

Digital Voice Recoreder

➔ 제품특징

* 휴대용저장장치 & 음성녹음기
* 날짜, 시간 설정 가능
* 녹음음질설정(XHQ/HQ)
* 소리감지녹음 레벨 설정 가능(5단계)
* 소리감지녹음 대기시간:약25일
* 최적의 휴대성
* 표시 안나는 녹음 ON/OFF 스위치
* 자동 감도 조절 기능 내장

➔ 제품규격

* 메모리 용량: 8GB/16GB/32GB
* 녹음저장시간(HQ): 약 288/576/1152시간
* 녹음저장시간(XHQ):약144/288/576시간
* 전지사용시간: 약 23~28시간
* 충전시간: 약 2시간
* 크기: 68 x 11 x 21mm
* 중량: 14.7g

➔ Product Feature

* USB Memory & Voice Recorder
* Date and Time Stamp of Recordings
* Recording Quality Setting(XHQ/HQ)
* SVOS level setting: 5 steps
* SVOS Standby time: about 25 days
* Best Portability
* Hidden Recording On/Off Switch
* Automatic Recording Level Control(ALC)

➔ Specifications

* Memory Capacity: 8GB/16GB/32GB
* Recording Time(HQ): About 288/576/1152Hrs
* Recording Time(XHQ):About 144/288/576Hrs
* Hours of Battery Use: About 23~ 28Hrs
* Charging Time: About 2Hrs
* Dimension: 68 x 11 x 21mm
* Weight: 14.7g

➔ 製品特徴

* USB型ボイスレコーダー
* 録音の日時を記録される(PC閲覧のみ)
* 録音音質の設定(XHQ/ HQ)
* 音声感知録音の検出レベル設定(5段階)
* 音声感知録音の待機時間:約25日
* 一回の充電で約28時間連続録音
* 相手に気付かれずに録音
* 自動録音感度調整で安定した録音

➔ 製品規格

* メモリー容量: 8GB/16GB/32GB
* 録音保存時間(HQ): 約288/576/1152時間
* 録音保存時間(XHQ): 約144/288/576時間
* 電池使用時間: 約23~28時間
* 充電時間: 約2時間
* 大きさ: 68 x 11 x 21mm
* 重量: 14.7g

1802K11916

MSIP-REM-ESO-MQ-U350
MADE IN KOREA

This image shows the back of the E-SONIC MQ-U350 voice recorder's retail packaging. It lists 'Product Features' including USB & Voice Recorder, Date and Time Stamp, Recording Quality Setting, SVOS level settings, SVOS Standby Time (about 25 days), Best Portability, Hidden Recording On/Off Switch, and Automatic Recording Level Control (ALC). 'Specifications' are also detailed, covering Memory Capacity (8GB/16GB/32GB), Recording Time, Hours of Battery Use, Charging Time, Dimension, and Weight.



This image presents a side view of the E-SONIC MQ-U350 voice recorder's packaging. It clearly shows memory options (8GB, 16GB, 32GB) and the model number 'MQ-U350'.



This image shows the E-SONIC MQ-U350 voice recorder in its closed state. It appears as a sleek, black USB flash drive with 'USB' and 'MQ-U350' subtly embossed on its surface. A small, textured wheel or switch is visible on one end.



This image displays the E-SONIC MQ-U350 voice recorder with its protective cap removed, exposing the standard USB-A connector. The device maintains its black, minimalist design, with the cap placed beside it.

Initial Setup

Charging the Device

Before first use, fully charge the MQ-U350. Connect the device to a powered USB port on a computer or a compatible USB wall adapter. A full charge typically takes approximately 2 hours. The device may have an indicator light to show charging status (refer to specific product documentation for light behavior).

Date and Time Synchronization

To ensure accurate date and time stamps on your recordings, connect the device to a computer. The device's internal clock will typically synchronize with the computer's system time upon connection, or you may need to use a dedicated utility software (if provided) to set the time. Consult the device's internal files for any specific setup instructions.

Operation

Power On/Off and Recording

The MQ-U350 features a hidden recording on/off switch, typically located on the side or end of the device.

- **To start recording:** Slide the switch to the 'ON' position. The device will begin recording based on its current mode (continuous or SVOS).
- **To stop recording and save:** Slide the switch to the 'OFF' position. The current recording will be saved to the internal 8GB memory.

Voice Activated Recording (SVOS)

The Super Voice Operated System (SVOS) enables the recorder to automatically start recording when sound is detected and pause during periods of silence. This feature helps conserve memory and battery life. The device offers 5 levels of SVOS sensitivity.

To adjust SVOS sensitivity or recording quality (XHQ/HQ), connect the device to a computer. These settings are typically configured via a text file or a simple utility found within the device's storage when connected to a PC.

Accessing Recordings

To listen to or transfer your recorded audio files:

1. Ensure the device's recording switch is in the 'OFF' position.
2. Connect the MQ-U350 to a computer's USB port.
3. The device will appear as a removable storage drive (e.g., "USB Drive" or "MQ-U350") in your computer's file explorer.
4. Open the drive to access your recorded audio files. Files are typically saved in a standard audio format and can be played using common media players.

Maintenance and Care

- Keep the device dry and away from extreme temperatures (both hot and cold).
- Avoid dropping the device or subjecting it to strong impacts.
- Regularly back up important recordings to a computer to prevent data loss.
- Clean the exterior of the device with a soft, dry cloth. Do not use liquid cleaners or abrasive materials.
- When not in use, store the device in a safe place to prevent damage.

Troubleshooting

Device Not Recording

- Ensure the device is sufficiently charged. Connect it to a USB port for charging.
- Verify that the recording switch is firmly in the 'ON' position.
- Check if the 8GB internal memory is full. If so, transfer files to a computer and delete them from the device to free up space.

Device Not Recognized by Computer

- Ensure the device's recording switch is in the 'OFF' position before connecting it to the computer.
- Try connecting the device to a different USB port on your computer.
- Restart your computer and attempt to connect the device again.
- Ensure your computer's operating system is up to date and has necessary USB drivers.

Poor Recording Quality

- Ensure the built-in microphone is not obstructed by clothing, fingers, or other objects.
- Adjust the recording quality settings (XHQ/HQ) if accessible via the device's configuration files when connected to a computer.
- For SVOS recording, adjust the sensitivity levels to match the ambient noise level of your environment. Too high sensitivity may pick up unwanted background noise, while too low may miss quieter sounds.

Technical Specifications

Feature	Detail
Model	MQ-U350
Memory Capacity	8GB
Digital Recording Time	Approx. 100 hours (for 8GB)
Battery Life (Recording)	Approx. 23-28 hours

Battery Life (Standby)	Up to 25 days
Charging Time	Approx. 2 hours
Dimensions	0.59 x 0.2 x 0.2 inches (68 x 11 x 21 mm)
Item Weight	1.76 ounces (14.7g)
Hardware Interface	USB
Microphone Form Factor	Built-In
Microphone Operation Mode	Mono
Compatible Devices	Personal Computer, Laptop, Tablet
UPC	8809196301364

Warranty and Customer Support

For specific warranty information, technical assistance, or customer support, please refer to the manufacturer's official website or contact your authorized retailer. It is recommended to retain your purchase receipt as proof of purchase for any warranty claims.

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B073XQ659P

More documents and user manuals: **https://manuals.plus/**