

Manuals.plus /

- › Access Lighting /
- › Access Lighting Atom Flush Mount LED Light Fixture User Manual

Access Lighting 20726LEDDL-ORB/OPL

Access Lighting Atom Flush Mount LED Light Fixture User Manual

Model: 20726LEDDL-ORB/OPL | Brand: Access Lighting

1. INTRODUCTION

This manual provides essential information for the safe installation, operation, and maintenance of your Access Lighting Atom Flush Mount LED Light Fixture. Please read these instructions thoroughly before beginning installation and retain them for future reference. This fixture is designed for indoor use only and features an Oil Rubbed Bronze finish with an Opal glass shade, providing 30 total watts of LED illumination.



Figure 1: Access Lighting Atom Flush Mount LED Light Fixture (Model 20726LEDDL-ORB/OPL)

2. SAFETY INFORMATION

WARNING: Risk of electric shock. Disconnect power at the circuit breaker or fuse box before installation or servicing. Consult a qualified electrician if you are unsure about wiring procedures.

- All electrical connections must be in accordance with local codes, ordinances, or the National Electric Code (NEC).
- This product is UL Listed, ensuring compliance with safety standards.
- Do not install this fixture in wet locations. It is designed for indoor use only.
- Ensure the mounting surface can support the weight of the fixture.
- Do not attempt to modify the fixture. Any modifications may void the warranty and create a safety hazard.
- Wear safety glasses and gloves during installation.

3. WHAT'S IN THE BOX

Carefully unpack the contents and ensure all items are present and undamaged. If any parts are missing or damaged, do not attempt to assemble or install the fixture. Contact customer support immediately.

- Atom Flush Mount Fixture Body (with integrated LED)
- Opal Glass Shade
- Mounting Hardware Kit (screws, wire nuts, mounting bracket)
- Instruction Manual

4. SETUP (INSTALLATION)

Professional installation is recommended. Ensure power is disconnected at the circuit breaker before proceeding.

1. **Prepare for Installation:** Turn off the main power supply to the junction box at the circuit breaker. Clear the work area and gather necessary tools (screwdriver, wire strippers, electrical tape, safety glasses).
2. **Attach Mounting Bracket:** Secure the mounting bracket to the junction box in the ceiling using the provided screws. Ensure the bracket is firmly attached and level.
3. **Make Electrical Connections:**
 - Connect the bare copper ground wire from the fixture to the ground wire from the junction box (usually bare copper or green) using a wire nut.
 - Connect the white wire from the fixture to the white (neutral) wire from the junction box using a wire nut.
 - Connect the black wire from the fixture to the black (hot) wire from the junction box using a wire nut.
 - Ensure all connections are secure and insulated with electrical tape if necessary.
4. **Mount the Fixture Body:** Carefully push the wired fixture body up towards the ceiling, aligning the screw holes on the fixture with the holes on the mounting bracket. Secure the fixture body to the bracket using the provided mounting screws.
5. **Install the Glass Shade:** Gently place the Opal glass shade onto the fixture body. Depending on the design, it may twist into place or be secured with decorative nuts. Ensure it is seated properly and securely.
6. **Restore Power:** Once installation is complete and all components are secure, restore power at the circuit breaker.



Figure 2: Example of the Atom Flush Mount Fixture installed

5. OPERATING INSTRUCTIONS

The Access Lighting Atom Flush Mount LED Light Fixture is designed for simple operation.

- **Power On/Off:** Operate the fixture using a standard wall switch connected to the electrical circuit.
- **Dimming Function:** This fixture is dimmable. To utilize the dimming feature, ensure you have installed a compatible LED dimmer switch (sold separately) in your wall switch location. Follow the dimmer switch manufacturer's instructions for proper operation.
- **Remote Control:** If your model includes a remote control or is compatible with a specific remote system, refer to the separate remote control instructions for pairing and operation. The fixture supports remote control functionality via a push-button controller.

6. MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your light fixture.

- **Cleaning:** Disconnect power before cleaning. Use a soft, dry, or slightly damp cloth to wipe the exterior surfaces of the fixture. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish or electrical components.
- **LED Light Source:** The LED light source in this fixture is integrated and not user-replaceable. If the LEDs fail, the entire fixture may need to be replaced. Contact customer support for assistance.
- **Glass Shade:** The Opal glass shade can be carefully removed for cleaning if necessary. Wash with mild soap and water, rinse thoroughly, and dry completely before reattaching.

7. TROUBLESHOOTING

If you experience issues with your fixture, refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
Fixture does not light up.	No power to the fixture. Loose wiring connection. Faulty wall switch.	Check circuit breaker and wall switch. Ensure all wire connections are secure. Test the wall switch with another device.
Light flickers or dims inconsistently.	Incompatible dimmer switch. Loose wiring.	Ensure the dimmer switch is compatible with LED fixtures. Check all wiring connections.
Humming noise from fixture.	Incompatible dimmer switch.	Replace with an LED-compatible dimmer switch.

If these steps do not resolve the issue, contact a qualified electrician or Access Lighting customer support.

8. SPECIFICATIONS

Feature	Detail
Model Number	20726LEDDLDP-ORB/OPL
Brand	Access Lighting
Product Dimensions	14"L x 14"W x 4"H
Item Weight	7 Pounds
Finish	Oil Rubbed Bronze
Shade Material	Glass (Opal)
Light Source	Integrated LED
Wattage	30 Watts (Total)
Brightness	2600 Lumens
Voltage	120 Volts
Light Color	Warm White
Control Method	Remote, Push Button (via compatible switch/controller)
Installation Type	Flush Mount
Indoor/Outdoor Usage	Indoor Only
Certifications	Energy Star, UL Listed

9. WARRANTY AND SUPPORT

Manufacturer's Warranty: This Access Lighting fixture is covered by a 1-year manufacturer's warranty from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or unauthorized modifications.

Customer Support: For technical assistance, warranty claims, or to report missing/damaged parts, please contact Access Lighting customer support. Refer to your purchase documentation or the Access Lighting website for current contact information.

Please have your model number (20726LEDDL-ORB/OPL) and proof of purchase available when contacting support.