



Manuals.plus /

- › UpStart Components /
- › UpStart Components Replacement Light Bulb Instruction Manual

UpStart Components ALB-6912W1Z004B-2PK-DL104

Instruction Manual

UPSTART COMPONENTS REPLACEMENT LIGHT BULB

Model: ALB-6912W1Z004B-2PK-DL104

INTRODUCTION

This manual provides essential information for the safe and effective installation and use of your UpStart Components replacement light bulb. This product is designed as a compatible replacement for Kenmore/Sears 72185033010 Microwave and Kenmore/Sears 6912W1Z004B Light Bulbs. Please read all instructions carefully before proceeding with installation.

SPECIFICATIONS

Brand	UpStart Components
Model Number	ALB-6912W1Z004B-2PK-DL104
Wattage	30 watts
Voltage	125 Volts
Bulb Shape Size	E17
Number of Items	2
Material	Glass
Product Dimensions	1 x 2.2 x 2.75 inches
Special Feature	Long Lasting

SAFETY INFORMATION

WARNING: Risk of Electric Shock.

- Always disconnect power to the appliance before attempting to replace the light bulb. Unplug the microwave from the wall outlet or turn off the circuit breaker.
- Allow the old bulb to cool completely before handling, as it may be hot.
- Handle the new bulb by its base to avoid touching the glass, which can reduce bulb life.
- Ensure the replacement bulb matches the voltage and wattage requirements of your appliance.
- If you are unsure about any step, consult a qualified technician.

SETUP & INSTALLATION

Follow these steps to replace the light bulb in your microwave oven:

1. **Disconnect Power:** Before beginning, ensure the microwave oven is completely disconnected from its power source. Unplug the appliance from the wall outlet.
2. **Locate Bulb Access:** Refer to your microwave's specific user manual to locate the light bulb access panel. This is typically found on the bottom, side, or rear of the microwave, often secured by screws.



Image: A single replacement light bulb, showing its clear glass and brass E17 screw-in base. This bulb is ready for installation.

3. **Remove Access Panel:** Using a screwdriver, carefully remove the screws securing the light bulb access panel. Set the screws and panel aside in a safe place.
4. **Remove Old Bulb:** Gently unscrew the old light bulb counter-clockwise until it is free from the socket. Dispose of the old bulb responsibly.



Image: Two identical replacement light bulbs, shown side-by-side. Each bulb features a clear glass casing and a brass E17 screw-in base, highlighting their compact design.

5. **Install New Bulb:** Carefully screw the new UpStart Components light bulb into the socket by turning it clockwise until it is snug. Do not overtighten.



Image: A close-up view of the E17 screw-in base of the light bulb, showing the threaded brass contact and the central electrical contact point. This view emphasizes the bulb's connection mechanism.

6. **Reattach Access Panel:** Replace the access panel and secure it with the screws removed earlier.
7. **Restore Power:** Plug the microwave oven back into the wall outlet.

OPERATING INSTRUCTIONS

After successful installation and power restoration, the light bulb should illuminate when the microwave door is opened or when the internal light function is activated (if applicable to your microwave model). No special operating procedures are required for the bulb itself.

MAINTENANCE

The UpStart Components replacement light bulb is designed for long-lasting performance and requires no specific maintenance. If the bulb's brightness diminishes or it ceases to function, follow the installation steps to replace it with a new one.

TROUBLESHOOTING

- **Bulb Does Not Light:**

- Ensure the microwave is properly plugged in and receiving power.
- Verify that the bulb is screwed in tightly and making proper contact with the socket.
- Check your microwave's circuit breaker or fuse.
- The bulb may be defective. Try installing another new bulb.

- **Bulb Flickers:**

- Ensure the bulb is securely tightened in the socket.
- Check for any loose wiring connections within the microwave's bulb assembly (only if you are qualified to do so).

WARRANTY & SUPPORT

This UpStart Components replacement part is not affiliated with any OEM brands and is not covered under any warranties offered by the original manufacturers. Any warranties for this product are offered solely by UpStart Components. For warranty claims or technical support, please contact UpStart Components directly through their official support channels.

All mentions of brand names or model descriptions are made strictly to illustrate compatibility. All brand names and logos are registered trademarks of their respective owners.