



Manuals.plus /

› UpStart Components /

› UpStart Components Replacement Light Bulb for Amana YAMV1160VAS3 Microwave - Model 8206232A Instruction Manual

UpStart Components 8206232A

UpStart Components Replacement Light Bulb Instruction Manual

For Amana YAMV1160VAS3 Microwave - Compatible with Amana 8206232A Light Bulb

INTRODUCTION

This manual provides instructions for the safe and proper installation, operation, and maintenance of your UpStart Components replacement light bulb. This bulb is designed as a compatible replacement for the Amana 8206232A light bulb used in Amana YAMV1160VAS3 microwave ovens. Please read these instructions carefully before proceeding with installation.

IMPORTANT SAFETY INFORMATION

- **ALWAYS** disconnect power to the microwave oven before attempting any installation or maintenance. Failure to do so can result in electric shock or injury.
- Allow the old bulb to cool completely before removal to prevent burns.
- Handle the new bulb by its base to avoid touching the glass, which can reduce bulb life.
- Ensure the replacement bulb specifications match the original bulb requirements for your appliance.
- Dispose of old bulbs responsibly according to local regulations.

SETUP AND INSTALLATION

Follow these general steps to replace the light bulb in your microwave oven. Refer to your specific microwave oven's user manual for detailed instructions on accessing the bulb compartment, as procedures may vary by model.

Step 1: Prepare for Installation

1. **Disconnect Power:** Unplug the microwave oven from the electrical outlet or turn off the circuit breaker supplying power to the appliance.
2. **Locate Bulb Compartment:** Identify the light bulb compartment. This is typically located behind a cover

panel inside the microwave cavity or on the underside for cooktop lighting.

3. **Allow Cooling:** If the old bulb was recently in use, allow it to cool down completely before touching it.

Step 2: Remove Old Bulb

1. **Access Bulb:** Carefully remove any screws or clips securing the bulb cover. Gently remove the cover.
2. **Unscrew Bulb:** Grasp the old bulb firmly and turn it counter-clockwise to unscrew it from the socket.





Image: The UpStart Components replacement light bulb, showing its clear glass and screw-in base.

Step 3: Install New Bulb

1. **Insert New Bulb:** Carefully insert the new UpStart Components bulb into the socket. Turn it clockwise until it is finger-tight. Do not overtighten.
2. **Replace Cover:** Reattach the bulb cover and secure it with any screws or clips that were removed.



Image: A close-up view of the E17 screw-in base of the replacement light bulb, highlighting the contact point.

Step 4: Test Operation

1. **Reconnect Power:** Plug the microwave oven back into the electrical outlet or restore power at the circuit breaker.
2. **Verify Function:** Test the microwave light function to ensure the new bulb illuminates properly.

OPERATING INSTRUCTIONS

Once installed, the UpStart Components replacement light bulb operates in conjunction with your microwave oven's existing lighting controls. Refer to your microwave oven's user manual for specific instructions on how to activate and control the interior or cooktop lighting.

- The bulb will illuminate when the microwave door is opened (interior light).
- The bulb may illuminate during cooking cycles (interior light).
- If your microwave has a cooktop light, it will operate via the dedicated light button on your microwave's control panel.

MAINTENANCE

The UpStart Components replacement light bulb requires minimal maintenance. Its primary function is to provide illumination for your microwave oven.

- **Cleaning:** If the bulb becomes dusty, ensure the microwave is unplugged and the bulb is cool. Gently wipe the glass with a soft, dry cloth. Do not use liquid cleaners directly on the bulb.
- **Replacement:** The bulb is designed for long-lasting brightness. Replace the bulb only when it burns out. Follow the "Setup and Installation" steps for replacement.

TROUBLESHOOTING

If the replacement light bulb does not function after installation, consider the following:

- **No Power:** Ensure the microwave oven is properly plugged in and receiving power. Check your household circuit breaker.
- **Improper Installation:** Verify that the bulb is screwed in tightly and correctly into the socket.
- **Damaged Bulb:** Although rare, inspect the bulb for any visible damage (e.g., broken filament). If damaged, replace with a new bulb.
- **Socket Issue:** If multiple bulbs fail to work in the same socket, there might be an issue with the microwave's bulb socket or wiring. In this case, professional service may be required.

SPECIFICATIONS

The following are the technical specifications for the UpStart Components Replacement Light Bulb:

Feature	Specification
Brand	UpStart Components
Compatibility	Amana YAMV1160VAS3 Microwave, Amana 8206232A Light Bulb
Wattage	40 Watts
Voltage	130 Volts
Bulb Base	E17
Bulb Shape Size	T22*55mm (0.87"W x 2.17"H)
Material	Glass
Special Feature	Long Lasting

2.17"





Image: Diagram showing the dimensions of the light bulb: 0.87 inches width and 2.17 inches height.

WARRANTY AND SUPPORT

This product is an UpStart Components brand replacement part. Any warranties for this product are offered solely by UpStart Components. This product is not affiliated with any OEM brands and is not covered under any warranties offered by the original manufacturers.

For warranty claims, technical assistance, or customer support, please contact UpStart Components directly. Contact information can typically be found on the product packaging or the UpStart Components official website.