



Manuals.plus /

- › Edvivi /
- › Edvivi Tiered Crystal Chandelier (Model EPJ423CH) Instruction Manual

## Edvivi EPJ423CH

# Edvivi Tiered Crystal Chandelier (Model EPJ423CH) Instruction Manual

Brand: Edvivi

## 1. IMPORTANT SAFETY INFORMATION

Please read this entire manual carefully before assembling, installing, or operating this product. Failure to do so may result in electric shock, fire, or other injuries that could be hazardous or fatal. Keep these instructions for future reference.

- **Electrical Safety:** Always turn off the main power supply at the circuit breaker before beginning any electrical installation. Ensure all wiring connections are secure and comply with local electrical codes. If you are unsure about wiring, consult a qualified electrician.
- **Product Handling:** Handle all components, especially glass and crystal parts, with care to prevent breakage or injury. Wear gloves during installation to protect hands and prevent fingerprints on chrome finishes.
- **Bulb Requirements:** Use only the specified bulb type and wattage. This fixture requires (5) E12 base bulbs, maximum 60 watts each (bulbs not included). Do not exceed the maximum wattage.
- **Mounting:** Ensure the mounting surface can support the weight of the fixture. Securely attach the mounting bracket to a junction box rated for ceiling fan or lighting fixture support.
- **California Proposition 65 Warning:** This product may expose you to chemicals known to the State of California to cause cancer and birth defects or other reproductive harm. Wash hands after handling.

## 2. PACKAGE CONTENTS

Verify that all components are present and undamaged before proceeding with installation. If any parts are missing or damaged, contact Edvivi customer support.

- Chandelier Frame with Chrome Finish

- Ceiling Canopy
- Adjustable Hanging Chain
- Mounting Hardware (screws, wire nuts, mounting bracket)
- Raindrop Crystal Strands/Components
- Instruction Manual

### 3. PRODUCT SPECIFICATIONS

Specification	Detail
Model Number	EPJ423CH
Fixture Dimensions (H x W)	18.5 inches x 16 inches
Ceiling Canopy Dimensions (W x H)	4.7 inches x 0.8 inches
Adjustable Chain Length	39 inches
Maximum Hanging Height	58.5 inches
Number of Lights	5
Bulb Type	E12 Candelabra Base (bulbs not included)
Max Wattage per Bulb	60 Watts
Total Max Wattage	300 Watts
Voltage	110 Volts
Material	Crystal, Glass, Metal
Finish	Chrome Finish
Special Features	Dimmable (with compatible dimmer switch and bulbs)
Certification	UL Listed

#### Dimensional Diagram:



This diagram illustrates the overall dimensions of the chandelier, including the fixture height (18.5 inches), width (16 inches), the 40-inch chain, and the 5.1-inch diameter ceiling canopy, resulting in a total maximum hanging height of 57.5 inches (note: JSON states 58.5 inches max height, diagram shows 57.5 inches. Using JSON's 58.5 inches as primary source for text, diagram for visual reference).

## 4. SETUP AND INSTALLATION

Professional installation is recommended for electrical fixtures. Ensure power is OFF at the circuit breaker before starting.

1. **Prepare for Installation:** Turn off power at the main circuit breaker. Clear the work area.
2. **Mounting Bracket Installation:** Attach the mounting bracket to the ceiling junction box using the provided screws. Ensure it is securely fastened.
3. **Adjust Chain Length:** Determine the desired hanging height. The chain is 39 inches long and can be adjusted by removing links. Feed the electrical wires through the chain and canopy.
4. **Wiring Connections:** Connect the fixture's wires to the house wires according to standard electrical codes (typically black to black, white to white, ground to ground). Use wire nuts to secure connections.
5. **Secure Canopy:** Carefully push the ceiling canopy up to the ceiling, covering the junction box and wiring. Secure it in place with the provided collar ring or screws.
6. **Install Bulbs:** Screw in five (5) E12 base bulbs (not included) into the sockets. Do not overtighten.
7. **Attach Crystals:** Carefully hang the raindrop crystal strands onto the designated hooks on the chandelier frame. Refer to the product images for proper placement.

### Visual Reference for Installation Steps:



Image: Detail of the ceiling canopy, which attaches to the junction box.



Image: View of the chain connecting to the canopy, with electrical wires visible.



Image: Detail of the bulb sockets on the chandelier frame.



Image: Close-up of the decorative raindrop crystals.

## 5. OPERATING INSTRUCTIONS

Once installed, operate the chandelier using a standard wall switch. This fixture is designed to be dimmable when used with a compatible dimmer switch and dimmable E12 bulbs (both sold separately).

- **Power On/Off:** Flip the wall switch connected to the chandelier to turn the lights on or off.
- **Dimming Function:** If a dimmer switch is installed, adjust the dimmer control to achieve the desired light intensity. Ensure that the bulbs used are also dimmable.

## 6. MAINTENANCE

Regular cleaning will help maintain the appearance and functionality of your chandelier.

- **Cleaning:** Keep your Edvivi lighting fixture looking beautiful by cleaning it regularly with a dry, soft cloth or duster.
- **Avoid Harsh Chemicals:** Do not use harsh chemicals, abrasive cleaners, or polishing agents as they may damage the chrome finish and crystal components.
- **Bulb Replacement:** Ensure the power is off at the circuit breaker before replacing any bulbs. Allow bulbs to cool completely before touching them.

## 7. TROUBLESHOOTING

If you encounter issues with your chandelier, refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Lights do not turn on	No power to the fixture, loose wiring, faulty bulbs, tripped circuit breaker.	Check circuit breaker. Ensure wall switch is on. Verify all wire connections are secure. Replace bulbs.
Lights flicker	Loose bulb, incompatible dimmer switch/bulbs, loose wiring.	Tighten bulbs. Ensure dimmer switch and bulbs are compatible. Check wiring connections.
Chandelier hangs unevenly	Improperly installed mounting bracket or chain.	Ensure mounting bracket is level and securely fastened. Re-adjust chain links if necessary.

## 8. WARRANTY AND SUPPORT

This Edvivi chandelier is covered by a manufacturer's warranty. For specific warranty details, claims, or technical support, please contact Edvivi Lighting directly. Keep your purchase receipt as proof of purchase.

For further assistance, please visit the Edvivi Lighting store or contact their customer service department.

## 9. PRODUCT OVERVIEW

The Edvivi Tiered Crystal Chandelier (Model EPJ423CH) is designed to provide elegant illumination with its chrome finish and cascading raindrop crystals. Its versatile design makes it suitable for various indoor settings.



Image: Front view of the Edvivi Tiered Crystal Chandelier.



Image: Chandelier illuminating a dining area with white chairs and dark table.



Image: Chandelier in a dining room with light-colored walls and modern furniture.



Image: Chandelier providing ambient light in a bedroom setting.