

[Manuals.plus](#) /

› [Seneca River Trading](#) /

› Seneca River Trading Halogen Lamp for General Electric Ovens, 35W 130V (Model WB08T10023) - Instruction Manual

Seneca River Trading WB08T10023

Seneca River Trading Halogen Lamp Instruction Manual

Model: WB08T10023 | 35W 130V

1. PRODUCT OVERVIEW

This document provides instructions for the Seneca River Trading Halogen Lamp, a replacement bulb designed for interior oven cavity lighting. It is compatible with various General Electric, Hotpoint, and RCA oven models, replacing part number WB08T10023 and several alternate part numbers. This 35-watt, 130-volt bulb ensures clear visibility inside your oven.



Image 1.1: Front view of the Seneca River Trading Halogen Lamp, showing the clear glass bulb and two metal pins at the base.

2. SAFETY INFORMATION

- **Disconnect Power:** Always disconnect power to the oven at the circuit breaker before attempting any installation or maintenance. Failure to do so can result in electrical shock or injury.
- **Handle with Care:** Halogen bulbs can be fragile. Avoid dropping or subjecting them to impact.
- **Avoid Skin Oils:** Use gloves or a clean, dry cloth when handling the bulb. Oils from your skin can create hot spots on the bulb's surface, leading to premature failure.

- **Hot Surface:** Halogen bulbs operate at high temperatures. Allow the oven and the old bulb to cool completely before removal or installation.

3. INSTALLATION INSTRUCTIONS

Follow these steps to safely replace your oven's interior halogen lamp:

1. **Disconnect Power:** Turn off the electrical power to your oven at the main circuit breaker.
2. **Access Lamp Housing:** Locate the lamp housing inside your oven cavity. This is typically found at the rear or side of the oven. You may need to remove a protective glass cover or metal shield, often secured by screws or clips.
3. **Remove Old Bulb:** Carefully remove the old halogen bulb. For push-in style bulbs, gently pull the bulb straight out from its socket. If the bulb is broken, use pliers to extract the base, ensuring no glass fragments remain.
4. **Insert New Bulb:** Using gloves or a clean cloth, align the two pins of the new Seneca River Trading Halogen Lamp with the holes in the socket. Gently push the bulb firmly into place until it is securely seated. Do not force the bulb.



Image 3.1: Close-up view of the halogen lamp's two-pin base, ready for insertion into a compatible socket.

5. **Reassemble Housing:** Replace any protective covers or shields that were removed, ensuring they are securely fastened.
6. **Restore Power:** Turn the electrical power back on at the circuit breaker.
7. **Test Functionality:** Turn on your oven light to confirm the new bulb is working correctly.



Image 3.2: Side view of the halogen lamp, displaying the '130V 35W' specification printed on its ceramic base.

4. OPERATING INSTRUCTIONS

Once properly installed, the Seneca River Trading Halogen Lamp operates in conjunction with your oven's existing light switch. Simply activate the oven light switch to illuminate the oven interior.

5. MAINTENANCE

The halogen lamp itself requires no routine maintenance. It is designed for a specific operating life and should be replaced when it burns out. To maximize bulb life, always follow the installation guidelines, particularly avoiding contact with the glass surface using bare hands.

6. TROUBLESHOOTING

- **Bulb Does Not Light Up:**
 - Ensure the oven's power is connected and the circuit breaker is on.
 - Verify the bulb is securely seated in its socket.
 - Check if the oven light switch is functional.
 - Inspect the bulb for any visible damage or a broken filament.
- **Bulb Burns Out Quickly:**
 - Confirm that the voltage and wattage of this replacement bulb (130V, 35W) match the requirements of your oven.
 - Ensure the bulb was handled with gloves or a clean cloth during installation to prevent skin oils from causing hot spots.
 - Check for any loose connections in the lamp housing.

7. SPECIFICATIONS

Brand	Seneca River Trading
Model Number	WB08T10023
Light Type	Halogen

Wattage	35 Watts
Voltage	130 Volts
Bulb Base	OEM-style push-in (E26 equivalent for general type, specific for oven)
Bulb Shape Size	T6 1/2 (Tubular)
Light Color	White (Clear)
Operating Life	Approximately 2000 Hours
Material Type	Copper (for contacts)
Replaces Part Numbers	WB08T10023, AP3669150, WB08T10007, 946481, AH230456, EA230456, PS230456, WB8T10007, WB8T10023

8. WARRANTY AND SUPPORT

This product is covered by a **30-day manufacturer's warranty**. For warranty claims or further assistance, please contact Seneca River Trading customer support through your original point of purchase.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question