Saved from manuals.plus.
Open the live page for links to other documents and user manuals.

iDealBed IDEAL4I-QN

iDealBed 4i Custom Adjustable Bed Base User Manual

Model: IDEAL4I-QN (Queen Size)

Introduction

This manual provides detailed instructions for the assembly, operation, and maintenance of your iDealBed 4i Custom Adjustable Bed Base. Please read this manual thoroughly before use to ensure proper function and safety. Keep this manual for future reference.



Image: The iDealBed 4i Adjustable Bed Base in a bedroom, showcasing its adjustable head and foot sections.

Safety Information

Always adhere to the following safety guidelines to prevent injury or damage to the product:

- **Weight Capacity:** Do not exceed the maximum weight capacity of 850 lbs. per unit.
- **Clearance:** Ensure there is adequate clearance around the bed base during operation to prevent obstructions.
- **Children and Pets:** Keep children and pets away from the moving parts of the bed base.
- **Power Cord:** Do not pinch or cut the power cord. Ensure it is routed safely to avoid tripping hazards.
- **Under-Bed Night Light:** Utilize the under-bed night light feature to illuminate the area around the bed, reducing the risk of falls when getting in or out of bed in low light conditions.
- **Professional Installation:** If you are unsure about any assembly steps, consult a qualified professional.

Package Contents

Verify that all components are present before beginning assembly:

- iDealBed 4i Adjustable Bed Base (Queen Size)
- Wireless Back-lit Remote Control
- Adjustable Legs (4", 7", and 11" height options)
- Mattress Retention Bar
- Power Cord and Adapter
- User Manual (this document)

Setup and Assembly

1. Unpacking and Placement

Carefully remove the bed base from its packaging. The base is folded in half. Place the folded base in the desired location. Ensure the area is clear of obstructions.



Image: The adjustable bed base shown in its flat, unfolded state, ready for leg attachment.

2. Unfolding the Base

Carefully unfold the bed base. Ensure the white zip ties, if present, are kept in place until the base is fully positioned to prevent accidental extension. Once unfolded, remove any temporary securing ties.

3. Attaching the Legs

The iDealBed 4i includes 3-in-1 height option legs (4", 7", and 11"). Choose your desired height by screwing the leg segments together. Attach the assembled legs securely to the designated points on the bed frame. Ensure all legs are tightened and the base is level.



Image: A display of the adjustable legs, showing how different heights can be achieved by combining segments.

4. Installing the Mattress Retention Bar

Insert the mattress retention bar into the designated slots at the foot of the bed base. This bar helps keep your mattress from sliding when the base is articulated.

5. Connecting Power

Connect the power cord to the bed base and then plug it into a grounded electrical outlet. Ensure the connection is secure.

6. Remote Pairing (if necessary)

The remote control should be pre-paired. If the remote does not respond, refer to the troubleshooting section for pairing instructions. Insert 2 AAA batteries into the remote control.

Operating Instructions

Wireless Remote Control

The iDealBed 4i features an ergonomic wireless back-lit remote with 18 buttons for intuitive control. The backlight activates when buttons are pressed.



Image: The iDealBed 4i wireless remote control, detailing buttons for head/foot adjustment, massage, pre-sets, and other features.

Articulation Controls:

- **HEAD UP/DOWN:** Adjusts the head section up to 70°.
- **FOOT UP/DOWN:** Adjusts the foot section up to 42°.
- **FLAT:** Returns the bed to a completely flat position.



Image: The adjustable bed base with both head and foot sections raised, illustrating the range of motion.

Pre-Set Positions:

- **ZERO-GRAVITY (ZG):** Elevates the head and foot to a position that may reduce pressure on the back and improve circulation.
- **ANTI-SNORE:** Slightly elevates the head to an angle that may help reduce snoring.
- **TV:** Adjusts the head section to an optimal position for watching television.
- **MEMORY PRE-SETS (M1, M2, M3):** Allows you to save and recall up to three custom positions. To save a position, adjust the bed to your desired setting, then press and hold the desired memory button (M1, M2, or M3) until the remote light flashes.



Image: The adjustable bed base configured into a Zero-Gravity position.

Massage Function:

The bed base features a full-body massage system with adjustable settings.

- **INTENSITY:** Choose from 3 intensity levels.
- **MODES:** Select from 4 modes, including wave, pulse, and constant.
- **TIMER:** Set the massage to run for 10, 20, or 30 minutes.
- **ALL OFF:** Stops the massage function.

Additional Features:

- **DUAL USB CHARGE PORTS:** Located on the side of the bed base, these ports allow you to charge your electronic devices.
- **NIGHTLIGHT:** Activates an under-bed light for visibility in the dark.

Maintenance

To ensure the longevity and optimal performance of your iDealBed 4i Adjustable Bed Base, follow these maintenance guidelines:

- **Cleaning:** Wipe the frame with a damp cloth. Avoid harsh chemicals or abrasive cleaners.
- **Motor Care:** The Leggett & Platt power motors are designed for quiet operation and require no user maintenance. Do not attempt to lubricate or open the motor housing.
- **Cord Inspection:** Periodically inspect the power cord for any signs of damage. If damaged, discontinue use and contact customer support.
- **Tighten Connections:** Occasionally check and tighten all leg and frame connections to ensure stability.

Troubleshooting

If you encounter issues with your iDealBed 4i, refer to the following common solutions:

- **Bed Not Responding to Remote:**
  - Check if the remote batteries (2 AAA) need replacement.
  - Ensure the power cord is securely plugged into both the bed base and the wall outlet.
  - **Remote Pairing:** If the remote loses connection, unplug the bed base from the power outlet for 30 seconds, then plug it back in. Within 10 seconds, press and hold the PAIR button on the remote (often located in the battery compartment or a small button on the control box under the bed) until the bed responds.
- **Motor Noise:**
  - Some motor noise during articulation is normal. If the noise is excessive or unusual, check for any obstructions under the bed.
  - Ensure all legs and frame components are securely tightened. Loose connections can sometimes amplify vibrations.
- **USB Ports Not Charging:**
  - Verify the bed base is powered on and plugged in.
  - Test with a different USB cable or device to rule out external issues.
- **Bed Does Not Articulate:**
  - Check for any objects obstructing the moving parts of the bed base.
  - Ensure the bed is not overloaded beyond its weight capacity.

If these steps do not resolve the issue, please contact iDealBed customer support.

Specifications

Feature	Detail
Model Number	IDEAL4I-QN
Size	Queen
Product Dimensions	80"L x 38"W x 14"H (Note: Width is for one half of a split queen, actual Queen width is 60")
Weight Capacity	850 lbs. per unit
Head Articulation	Up to 70°
Foot Articulation	Up to 42°
Leg Height Options	4", 7", 11" (3-in-1 design)
Motors	Ultra-quiet Leggett & Platt power motors

Feature	Detail
Special Features	Wireless Remote, Massage (3 intensity, 4 modes, timer), Dual USB Charge, Nightlight, Zero-Gravity, Anti-Snore, Memory Pre-Sets
Assembly Required	No (minimal setup)
Included Components	Remote
Power Source	AC Power
Remote Batteries	2 AAA batteries (required)

Warranty and Support

For warranty information or technical assistance, please contact iDealBed customer support. Details regarding specific warranty periods and coverage are typically provided with your purchase documentation or can be obtained directly from the manufacturer.

Customer Support: For any questions or issues not covered in this manual, please visit the iDealBed store on Amazon or contact their customer service directly.

Visit the iDealBed Store

Ask a question about this manual

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. Privacy details.

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

https://manuals.plus/asin/B076BTMS8Z

More documents and user manuals: **https://manuals.plus/**