



[Manuals.plus](#) /

> [Sun Joe](#) /

> Sun Joe SPX7000E 2-in-1 Electric Pressure Washer W/ Built in Wet/Dry Vacuum System User Manual

Sun Joe SPX7000E

Sun Joe SPX7000E 2-in-1 Electric Pressure Washer + Wet/Dry Vacuum System

Model: SPX7000E

Brand: Sun Joe

INTRODUCTION

The Sun Joe SPX7000E is a versatile 2-in-1 electric appliance designed to tackle a wide range of cleaning tasks, both indoors and outdoors. It seamlessly combines the power of a pressure washer with the utility of a high-performance wet/dry vacuum, offering a comprehensive solution for dirt, grime, spills, and debris.

Equipped with a powerful 12-amp pressure washer motor and a 10-amp wet/dry vacuum motor, the SPX7000E provides efficient cleaning for surfaces such as patios, decks, driveways, vehicles, and various indoor areas like garages, basements, and laundry rooms. Its integrated detergent tank and an array of specialized attachments enhance its cleaning capabilities, making it an indispensable tool for maintaining a clean environment.



Image: The Sun Joe SPX7000E unit displayed with all its included accessories, highlighting its dual functionality.

IMPORTANT SAFETY INFORMATION

Before operating the Sun Joe SPX7000E, it is crucial to read and understand all safety warnings and instructions provided in the complete user manual. Failure to follow these instructions may result in electric shock, fire, and/or serious injury.

WARNING: This product can expose you to chemicals including Di(2-ethylhexyl)phthalate (DEHP), which is known to the State of California to cause cancer and birth defects or other reproductive harm. For more information go to www.P65Warnings.ca.gov.

- Always wear appropriate personal protective equipment, including eye protection, when operating the pressure washer.
- Ensure the power cord and plug are in good condition and connected to a properly grounded outlet.
- Do not direct the water spray at people, pets, or electrical devices.
- Keep the work area clear of obstructions and ensure stable footing.

- Unplug the unit from the power source before performing any maintenance or cleaning.

PACKAGE CONTENTS

Carefully remove all items from the packaging and inspect them for any damage. Ensure all components are present before discarding packaging materials.

- Sun Joe SPX7000E 2-in-1 Unit
- High-Pressure Hose
- Spray Wand with Adjustable Nozzle
- Trigger Gun
- Detergent Tank (27 fl oz capacity)
- Wet/Dry Vacuum Hose
- Wet/Dry Floor Brush
- Wet/Dry Bristle Brush
- Crevice Nozzle
- Furniture Brush
- Extension Tubes (2 pieces)
- Washable, Reusable Filters



Image: A detailed view of the 11-piece accessory kit included with the SPX7000E, showing various nozzles, brushes, and hoses.

ASSEMBLY

The Sun Joe SPX7000E requires minimal assembly before first use. Follow these general steps, referring to the detailed diagrams in your complete user manual for precise instructions:

1. Attach the handle assembly to the main unit, securing it with the provided fasteners.
2. Connect the high-pressure hose to the pressure washer outlet on the unit and to the trigger gun.
3. Assemble the spray wand to the trigger gun.
4. Attach the wet/dry vacuum hose to the vacuum inlet on the unit.
5. Securely attach the desired vacuum accessory (e.g., floor brush, crevice nozzle) to the end of the vacuum hose or extension tubes.



Image: A front-side view of the Sun Joe SPX7000E unit, illustrating its compact design and integrated components.

SETUP

Pressure Washer Setup

1. **Water Connection:** Connect a standard garden hose (not included) to the water inlet on the SPX7000E. Ensure the connection is tight to prevent leaks.
2. **Power Connection:** Plug the unit's power cord into a grounded electrical outlet.
3. **Detergent Tank (Optional):** For enhanced cleaning, fill the onboard 27 fl oz detergent tank with a pressure washer-safe detergent.



Image: A close-up view of the detergent tank on the Sun Joe SPX7000E, showing its location and connection point.

Wet/Dry Vacuum Setup

1. Ensure the vacuum hose is securely attached to the vacuum inlet.
 2. Select the appropriate vacuum attachment for your cleaning task (e.g., floor brush for large areas, crevice nozzle for tight spaces).
 3. Verify the collection tank is properly seated and the filter is clean and correctly installed for optimal performance.
-

OPERATING INSTRUCTIONS

Using the Pressure Washer

To operate the pressure washer, ensure the unit is connected to a water source and power. Turn the main switch to the 'Pressure Washer' mode. Squeeze the trigger gun to begin spraying. The adjustable spray wand allows you to quickly switch from an intense jet to a high-power fan spray by twisting the nozzle, adapting to various cleaning needs.



Image: A user operating the Sun Joe SPX7000E in pressure washer mode, cleaning a patio surface.

Using the Wet/Dry Vacuum

To use the wet/dry vacuum function, simply flick the main switch to the 'Vacuum' mode. The powerful 10-amp motor provides strong suction for both dry debris like sawdust and wet spills. Utilize the appropriate attachments for different surfaces and types of messes. The 0.8-gallon collection tank is designed for easy emptying of dirt, debris, and liquids.



Image: A close-up view of the transparent vacuum canister on the Sun Joe SPX7000E, showing its capacity and design.

Product Demonstration Video

Video: An official product video demonstrating the dual functionality of the Sun Joe SPX7000E, showcasing its use as both a pressure washer for outdoor cleaning and a wet/dry vacuum for indoor spills and debris.

MAINTENANCE

Regular maintenance ensures the longevity and optimal performance of your Sun Joe SPX7000E.

- **Emptying Collection Tank:** After vacuuming, especially wet materials, remove the 0.8-gallon collection tank and dispose of dirt, debris, or liquid.
- **Filter Cleaning:** The washable and reusable filters should be cleaned regularly. For dry vacuuming, tap out dust. For wet vacuuming, rinse the filter with water and allow it to air dry completely before reinstallation.
- **Nozzle Cleaning:** If the pressure washer nozzle becomes clogged, use the included needle clean-out tool to clear any debris.

- **Hose and Cord Storage:** Properly coil the high-pressure hose, vacuum hose, and power cord after each use to prevent kinks and damage.
- **Winter Storage:** If storing the unit in an area where temperatures may drop below freezing, ensure all water is drained from the pressure washer pump and hoses to prevent damage.

TROUBLESHOOTING

This section addresses common issues you might encounter with your Sun Joe SPX7000E. For more detailed troubleshooting, refer to the full user manual.

Problem	Possible Cause	Solution
Unit does not start	No power supply; tripped circuit breaker	Check power connection; reset circuit breaker
Low pressure (pressure washer)	Insufficient water supply; clogged nozzle; air in pump	Ensure full water flow; clean nozzle; purge air from system
Low suction (wet/dry vacuum)	Full collection tank; clogged filter; hose obstruction	Empty tank; clean/replace filter; clear hose blockage
Water leaks	Loose connections; damaged O-rings	Tighten connections; inspect and replace O-rings if necessary

SPECIFICATIONS

Detailed technical specifications for the Sun Joe SPX7000E:

Feature	Specification
Model Number	SPX7000E
Power Source	Corded Electric
Pressure Washer Motor	12-amp
Wet/Dry Vacuum Motor	10-amp
Maximum Pressure	1700 PSI (Pound per Square Inch)
Maximum Flow Rate	1.1 GPM (Gallons Per Minute)
Vacuum Tank Volume	0.8 Gallons
Product Dimensions (L x W x H)	14.8" x 18.34" x 30.59"
Item Weight	38.7 pounds (17.6 Kilograms)
Color	Lime, Black
UPC	842470104976



Image: The Sun Joe SPX7000E shown next to a human silhouette, providing a visual reference for its dimensions and height (43 inches / 108 cm).

WARRANTY AND SUPPORT

Sun Joe products are backed by a comprehensive warranty. For specific warranty terms and conditions, please refer to the warranty card included with your product or visit the official Snow Joe + Sun Joe website.

For technical assistance, replacement parts, or general inquiries, please contact Sun Joe customer support. Have your model number (SPX7000E) and purchase date ready when contacting support to expedite service.
