

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

› [GEORGE KOVACS](#) /

› [George Kovacs P1073-657-L Levels LED Pendant Light User Manual](#)

GEORGE KOVACS P1073-657-L

George Kovacs Levels LED Pendant Light User Manual

Model: P1073-657-L

Brand: GEORGE KOVACS

IMPORTANT SAFETY INSTRUCTIONS

Please read and understand all instructions before beginning installation. Failure to do so may result in electric shock, fire, or other injuries that could be hazardous or fatal. This product must be installed in accordance with the applicable installation code by a person familiar with the construction and operation of the product and the hazards involved.

- Always turn off the main power supply at the circuit breaker before installing or servicing the fixture.
- Consult a qualified electrician if you have any electrical questions.
- Wear safety glasses and appropriate protective gear during installation.
- Handle the fixture with care to avoid damage to the glass or electrical components.
- This fixture is rated for dry locations only. Do not install in damp or wet areas.

PACKAGE CONTENTS

Verify that all components listed below are included in your package. If any parts are missing or damaged, contact customer support before proceeding with installation.

- LED Pendant Fixture (1)
- Mounting Plate / Crossbar (1)
- Canopy (1)
- Mounting Screws (2)
- Wire Nuts (3)
- Glass Diffuser (1)
- Fabric Shade (1)



Detailed view of George Kovacs Levels LED Pendant Light components, showing the internal structure and materials.

TOOLS REQUIRED

The following tools are typically required for installation:

- Phillips Head Screwdriver
- Flat Head Screwdriver
- Wire Strippers
- Electrical Tape
- Ladder
- Safety Glasses

SETUP AND INSTALLATION

Follow these steps carefully to install your George Kovacs Levels LED Pendant Light.

Step 1: Prepare for Installation

1. **Turn off power:** Locate the circuit breaker that supplies power to the junction box where you will install the fixture. Turn off the power.
2. **Unpack fixture:** Carefully remove the fixture and all parts from the packaging. Retain the packaging for future reference or if returns are necessary.

Step 2: Install Mounting Plate

1. Attach the mounting plate/crossbar to the junction box using the provided mounting screws. Ensure the plate is securely fastened.

Step 3: Wiring Connections

Connect the electrical wires from the fixture to the wires in the junction box using the provided wire nuts. Ensure all connections are secure.

- Connect the **black** wire from the fixture to the **black** (hot) wire from the junction box.
- Connect the **white** wire from the fixture to the **white** (neutral) wire from the junction box.
- Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box.

Carefully tuck all wires into the junction box.

Step 4: Secure Fixture and Shade

1. Align the canopy of the fixture with the mounting plate and secure it using the canopy screws.
2. Carefully place the fabric shade and glass diffuser onto the fixture according to the design. Ensure they are seated properly and securely.



George Kovacs Levels LED Pendant Light, front view, showcasing the polished nickel frame and honey gold accents with the white fabric shade.

Step 5: Restore Power

1. Once installation is complete, restore power at the circuit breaker.
2. Test the fixture to ensure it is functioning correctly.



Side profile of the George Kovacs Levels LED Pendant Light, illustrating the depth and construction of the fixture.

OPERATING INSTRUCTIONS

This LED pendant light is designed for simple operation.

- **Power On/Off:** Control the light using a standard wall switch connected to the fixture's circuit.
- **Dimming:** This fixture is dimmable. To utilize the dimming feature, ensure you have a compatible LED dimmer switch installed. Follow the dimmer switch manufacturer's instructions for operation.

MAINTENANCE

Proper care will ensure the longevity and appearance of your fixture.

- **Cleaning:** To clean the fixture, turn off the power and allow it to cool. Wipe with a soft, dry, or slightly damp cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish or electrical components.
- **LEDs:** The LED components in this fixture are integrated and not user-replaceable. If the LEDs cease to function, the entire fixture may require replacement.

TROUBLESHOOTING

If you experience issues with your pendant light, refer to the following common problems and solutions:

- **Light does not turn on:**
 - Check that the power supply is on at the circuit breaker.
 - Ensure all wire connections are secure and correctly made.
 - Verify the wall switch is in the 'ON' position.
- **Light flickers or dims improperly:**

- Confirm that the dimmer switch is compatible with LED fixtures.
- Check wire connections for looseness.

If problems persist after checking these points, contact a qualified electrician or customer support.

SPECIFICATIONS

Model Number	P1073-657-L
Dimensions (L x W x H)	32.25 x 32.25 x 8.75 inches
Finish Color	Polished Nickel / Honey Gold
Material	Glass, Alloy Steel, Aluminum, Linen
Lamping Type	Integrated LED
Number of Light Sources	1
Wattage	76 Watts
Lumens	4117
Color Temperature	3000K
CRI	92
Rated Life	30,000 Hours
Voltage	120 Volts
Dimmable	Yes
Moisture Rating	Dry Rated
Control Method	Touch (via compatible wall switch/dimmer)

WARRANTY INFORMATION

GEORGE KOVACS products are manufactured to high standards and are backed by a manufacturer's warranty. For specific warranty terms and conditions, please refer to the documentation included with your purchase or visit the official GEORGE KOVACS website. Keep your proof of purchase for warranty claims.

CUSTOMER SUPPORT

For further assistance, technical support, or to inquire about replacement parts, please contact GEORGE KOVACS customer service.

- **Online:** Visit the official [GEORGE KOVACS Store on Amazon](#) or their corporate website.
- **Phone:** Refer to your product packaging or the brand's official website for contact numbers.