

[Manuals.plus](#) /

› [Nuvo](#) /

› Nuvo 60/6023 Two-Light Flush Mount Installation and Operation Manual

Nuvo 60/6023

Nuvo 60/6023 Two-Light Flush Mount Installation and Operation Manual

1. INTRODUCTION

This manual provides detailed instructions for the safe installation, operation, and maintenance of your Nuvo 60/6023 Two-Light Flush Mount fixture. Please read these instructions thoroughly before beginning installation and retain them for future reference.



Image 1.1: The Nuvo 60/6023 Two-Light Flush Mount fixture, featuring a brushed nickel base and a ribbed clear glass shade.

2. SAFETY INFORMATION

WARNING: Risk of Electric Shock. Always disconnect power at the main circuit breaker or fuse box before beginning installation, servicing, or changing bulbs. Failure to do so may result in serious injury or death.

- Consult a qualified electrician if you are unsure about the installation process or have questions regarding electrical connections.
- Ensure all electrical connections are made in accordance with local electrical codes and ordinances.
- This fixture is rated for indoor, damp location use only. Do not install in areas exposed to direct water spray.
- Use only bulbs of the specified type and wattage. Exceeding the maximum wattage may cause overheating and damage to the fixture or create a fire hazard.
- Do not attempt to modify the fixture. Any modifications may void the warranty and create safety risks.

3. PACKAGE CONTENTS

Carefully unpack your fixture and inspect for any damage. Ensure all components listed below are present. If any parts are missing or damaged, do not attempt to install the fixture. Contact Nuvo customer service for assistance.

- Nuvo 60/6023 Flush Mount Fixture (1)
- Glass Shade (1)
- Mounting Hardware (crossbar, screws, wire nuts) (1 set)
- Instruction Manual (1)



Image 3.1: The product packaging for the Nuvo 60/6023 fixture, indicating '2 Light Flush' and 'Brushed Nickel'.

4. SETUP AND INSTALLATION

Follow these steps for proper installation of your flush mount fixture. It is recommended to have a second person assist during installation.

1. **Turn Off Power:** Locate the circuit breaker or fuse box that controls the power to the desired installation location. Turn off the power completely. Verify power is off using a voltage tester.
2. **Prepare Mounting:** If replacing an existing fixture, carefully remove it. Attach the mounting crossbar to the electrical junction box using the provided screws. Ensure the crossbar is securely fastened.
3. **Make Electrical Connections:** Connect the fixture's wires to the corresponding wires from the junction box using the provided wire nuts.

- Connect the **black** (hot) wire from the fixture to the **black** (hot) wire from the junction box.
- Connect the **white** (neutral) wire from the fixture to the **white** (neutral) wire from the junction box.
- Connect the **ground** wire (bare copper or green) from the fixture to the **ground** wire from the junction box and to the ground screw on the mounting crossbar.

Ensure all connections are tight and secure.

4. **Mount the Fixture:** Carefully tuck the connected wires into the junction box. Align the fixture base with the mounting screws on the crossbar and secure the fixture in place using the decorative nuts or screws provided.
5. **Install Bulbs:** Insert two A19 incandescent bulbs (not included) into the E26 medium base sockets. Do not exceed 60 watts per bulb.
6. **Attach Glass Shade:** Carefully place the glass shade onto the fixture and secure it with the finial or retaining ring, ensuring it is snug but not overtightened.
7. **Restore Power:** Once installation is complete and all components are secure, restore power at the circuit breaker or fuse box. Test the fixture.

5. OPERATING INSTRUCTIONS

The Nuvo 60/6023 Two-Light Flush Mount is designed for simple operation:

- This fixture is controlled by a standard wall switch or a compatible dimmer switch (not included) connected to its electrical circuit.
- To turn the light on or off, operate the wall switch.
- If a dimmer switch is installed, adjust the dimmer to control the light intensity.
- Ensure the correct bulb type (A19 incandescent) and wattage (max 60W per socket) are used for optimal performance and safety.

6. MAINTENANCE

Regular maintenance will help preserve the appearance and functionality of your fixture:

- **Cleaning:** Always turn off power to the fixture before cleaning. Wipe the fixture with a soft, dry cloth. Do not use abrasive cleaners, solvents, or polishes as they may damage the finish.
- **Bulb Replacement:** Turn off power to the fixture before replacing bulbs. Allow bulbs to cool completely before touching. Unscrew old bulbs and replace with new A19 incandescent bulbs (max 60W per socket).
- **Inspection:** Periodically check all connections and mounting hardware to ensure they remain secure.

7. TROUBLESHOOTING

If you encounter issues with your fixture, refer to the following troubleshooting guide:

Problem	Possible Cause	Solution
Light does not turn on.	No power to fixture. Loose wire connection. Defective bulb.	Check circuit breaker/fuse. Verify all wire connections are secure (power off). Replace bulb.
Light flickers.	Loose bulb. Loose wire connection. Incompatible dimmer switch.	Tighten bulb. Check wire connections (power off). Ensure dimmer is compatible with incandescent bulbs.

Problem	Possible Cause	Solution
Bulbs burn out quickly.	Incorrect wattage bulb. Voltage fluctuations.	Ensure bulbs do not exceed 60W. Consult an electrician to check household voltage.

If troubleshooting steps do not resolve the issue, contact Nuvo customer service.

8. SPECIFICATIONS

Brand	Nuvo
Model Number	60/6023
Product Dimensions	1 x 11.25 x 5 inches (Height: 5 inches, Width: 11.25 inches)
Item Weight	34.5 pounds
Number of Lights	2
Bulb Type	A19 Incandescent (Bulbs not included)
Bulb Base	E26 Medium
Max Wattage	60 Watts per socket (120 Watts total)
Voltage	120 Volts
Material	Nickel, Glass
Finish Type	Brushed
Installation Type	Flush Mount
Indoor/Outdoor Usage	Indoor
Safety Rating	cULus Listed, Damp Location Rated
Control Method	Wall Switch / Dimmer (not included)

9. WARRANTY AND SUPPORT

Warranty: This Nuvo fixture comes with a 1-year limited warranty from the date of purchase. This warranty covers defects in materials and workmanship under normal use. It does not cover damage resulting from improper installation, accident, misuse, abuse, or unauthorized modifications.

Customer Support: For technical assistance, warranty claims, or to report missing/damaged parts, please contact Nuvo customer service. Please have your model number (60/6023) and proof of purchase available when contacting support.

For more information, visit the official Nuvo website or refer to the contact information provided with your purchase documentation.

ASK A QUESTION ABOUT THIS MANUAL

Ask about setup, troubleshooting, compatibility, parts, safety, or missing instructions. Manuals+ will review the question

and use this page's manual context to help answer it.

Name

Anonymous

Email

you@example.com

After a successful submission, we securely hash the supplied account or form email before sending it to Microsoft Advertising for conversion attribution. [Privacy details](#).

Question

Example: How do I reset this device or fix this error?

Details

Model number, symptoms, what you tried, or the section of the manual you are using.

Submit question

Open the live page

<https://manuals.plus/asin/B07C8ZNYB2>

More documents and user manuals: **<https://manuals.plus/>**