

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

manuals.plus /

- › [Ganeed](#) /
- › [Ganeed Vintage K9 Clear Crystal Chandelier User Manual](#)

Ganeed GLM-DD-3B

Ganeed Vintage K9 Clear Crystal Chandelier User Manual

Model: GLM-DD-3B

PRODUCT OVERVIEW

The Ganeed Vintage K9 Clear Crystal Chandelier is a sophisticated lighting fixture designed to enhance the ambiance of various indoor spaces. Featuring a black iron frame adorned with K9 clear crystals, this chandelier combines vintage charm with modern elegance. It is suitable for dining rooms, kitchens, living rooms, bedrooms, hallways, and more.



Image: The Ganeed Vintage K9 Clear Crystal Chandelier, showcasing its design and how it appears when installed.

KEY FEATURES

- **Elegant Design:** Features a black iron frame with 5 branches adorned with K9 clear crystals, creating a beautiful and artistic lighting solution.
- **Adjustable Height:** Equipped with a 39-inch steel sling, allowing for height adjustment to suit various ceiling types (slanted, sloped, parallel, low, and high ceilings).
- **Bulb Compatibility:** Uses 3 E12 (US standard) bulbs, max 25 Watts (bulbs not included). Compatible with Incandescent, LED, CFL, and Halogen bulbs.
- **Dimmable Functionality:** Fully dimmable when used with compatible dimmer switch and bulbs (dimmer not included).
- **Versatile Application:** Ideal for dining rooms, kitchen islands, living rooms, bedrooms, bathrooms, foyers, hallways, offices, and restaurants.

PRODUCT SPECIFICATIONS

Attribute	Detail
Brand	Ganeed
Model Number	GLM-DD-3B
Color	Black, 3-light
Material	Iron + K9 Crystal
Product Dimensions	13 (Dia) x 13.4 (L) inches (33cm Dia x 34cm L)
Steel Sling Length	39 inches (100cm), adjustable
Ceiling Cap Diameter	5.5 inches (14cm)
Bulb Type	E12 X 3 (US standard)
Max Wattage	25 Watts per bulb
Voltage	110 Volts
Power Source	Corded Electric
Installation Type	Flush Mount / Monopoint with Canopy
Indoor/Outdoor Usage	Indoor
Item Weight	6.51 pounds (2.96 Kilograms)
Assembly Required	Yes

14cm/5.5inch

100cm/39.7 inch

Adjustable



34cm/13.4 inch

Dia: 33cm/13 in

Image: Detailed dimensions of the chandelier, including diameter, length, and adjustable chain length.

PACKAGE CONTENTS

- Light kit (Chandelier frame with pre-attached wiring)
- K9 Clear Crystal components
- Mounting hardware
- Instruction Manual





Image: A close-up view of the K9 clear crystals and the black iron frame, highlighting the quality of materials.

SETUP AND INSTALLATION

Assembly is required for this chandelier, primarily involving hanging the crystal strings to the main plate and connecting the electrical wiring. A detailed mounting instructional manual is included in every package. For visual guidance, please refer to the official installation video provided by Ganeed Lighting Store.

Important Safety Information:

- Ensure power is turned off at the circuit breaker before beginning installation.
- Consult a qualified electrician if you are unsure about any wiring procedures.
- Handle crystal components with care to prevent damage.

Installation Steps:

1. **Unpack Components:** Carefully remove all parts from the packaging. Verify all components listed in the package contents are present.
2. **Mount Ceiling Canopy:** Secure the ceiling canopy to your junction box according to local electrical codes and the provided manual. Ensure it is firmly attached to support the chandelier's weight.
3. **Adjust Chain Length:** Determine the desired hanging height and adjust the steel chain length accordingly. The chain can be shortened by removing links if necessary.
4. **Wire Connections:** Connect the chandelier's electrical wires to your household wiring. Follow the color-coded instructions in the manual (typically black to black, white to white, and ground to ground). Secure connections with wire nuts.
5. **Attach Chandelier Body:** Carefully lift and attach the chandelier body to the mounted ceiling canopy, ensuring all connections are secure.
6. **Hang Crystals:** Individually attach the K9 crystal components to the designated points on the chandelier frame. Refer to the manual for the correct placement of each crystal string.
7. **Install Bulbs:** Screw in the E12 base bulbs (not included) into the sockets. Do not exceed the maximum wattage of 25 Watts per bulb.
8. **Restore Power:** Once installation is complete and all components are securely in place, restore power at the circuit breaker.

Your browser does not support the video tag.

Video: Official Ganeed installation guide for the 3-Lights Crystal Chandelier, demonstrating the assembly and wiring process.



Image: A detailed view of the chandelier's bulb sockets and the points where crystal elements are attached, illustrating the assembly points.

OPERATING INSTRUCTIONS

Once installed and powered, the Ganeed Crystal Chandelier operates like any standard lighting fixture. It is controlled via a wall switch (not included).

- **Turning On/Off:** Use the wall switch connected to the chandelier to turn the lights on or off.
- **Dimming Function (Optional):** If you have installed compatible dimmable E12 bulbs and a dimmer switch, you can adjust the light intensity by rotating or pressing the dimmer switch. This allows for creating various ambiances.

Different Color Temperatures Gives You Different Ambiences



Image: Comparison showing the chandelier with lights turned on and off, demonstrating its visual impact.

CARE AND MAINTENANCE

Regular cleaning will help maintain the chandelier's sparkle and appearance.

- **Cleaning:** Before cleaning, ensure the power to the chandelier is turned off. Use a soft, dry, or slightly damp cloth to wipe the metal frame. For the crystal components, a soft, lint-free cloth dampened with a mild glass cleaner can be used. Avoid abrasive cleaners or harsh chemicals.
- **Bulb Replacement:** Always turn off the power before replacing bulbs. Allow old bulbs to cool before removal. Replace with E12 base bulbs, not exceeding 25 Watts.
- **Crystal Care:** The K9 crystals are durable, but avoid strong impacts. If any crystal becomes loose, re-secure it carefully. Extra wires are provided for re-attaching crystals if needed.



X001UWWDZCP
Cores Usage X3 Dur - 1 Versata The Colors
11/11





Image: A close-up demonstrating the clarity and quality of the K9 clear crystals used in the chandelier, emphasizing their premium grade.

TROUBLESHOOTING

Problem	Possible Cause	Solution
Chandelier does not light up.	No power, loose wiring, faulty bulb.	Check circuit breaker. Ensure all wire connections are secure. Replace bulbs.
Lights flicker.	Loose bulb, incompatible dimmer, unstable power supply.	Tighten bulbs. Ensure dimmer is compatible with LED/CFL if used. Consult electrician for power issues.
Crystals appear dull.	Dust and dirt accumulation.	Clean crystals regularly with a soft, lint-free cloth and mild cleaner.
Chandelier is unstable/wobbles.	Improper mounting to ceiling.	Ensure ceiling canopy is securely fastened to the junction box and ceiling structure.

WARRANTY AND CUSTOMER SUPPORT

Ganeed provides customer service and support for this product. If you encounter any issues or require replacement parts, please contact Ganeed Lighting Store directly.

- **Warranty:** This product comes with a limited warranty. Please refer to your purchase documentation for specific warranty terms and duration.
- **Returns/Replacements:** You may be eligible to replace or return the chandelier if dissatisfied within 30 days of purchase. Contact customer service for details.
- **Customer Service:** Customer service is available 24/7. For any questions or troubleshooting assistance, please do not hesitate to contact us. We aim to troubleshoot for you within 24 hours.
- **Online Resources:** For additional information and support, visit the official Ganeed Store on Amazon: [Ganeed Store](#)