

[Manuals.plus](#) /

› [Ganeed](#) /

› Ganeed Crystal Chandeliers, Vintage Pendant Lighting Crystal Chandelier Lighting Fixtures with 8 Lights, Ceiling Light Fixture for Living Room Bedroom Restaurant Porch Hallway (Gold) Gold, 8-light

Ganeed GLM-DD-8G

Ganeed Crystal Chandelier Instruction Manual

Brand: Ganeed | **Model:** GLM-DD-8G

1. PRODUCT OVERVIEW

The Ganeed Crystal Chandelier is a vintage-modern lighting fixture designed to enhance the ambiance of various rooms such as living rooms, bedrooms, dining rooms, and hallways. It features a gold-painted iron frame adorned with K9 clear crystals, creating a sparkling and elegant effect. This 8-light fixture is compatible with E12 bulbs (not included) and can be fully dimmable when used with compatible dimmer switches and bulbs.



Figure 1: Ganeed Crystal Chandelier (Gold, 8-light)

2. WHAT'S IN THE BOX

- 1 x Chandelier Unit
- 1 x Accessory Kit (includes mounting hardware)
- 1 x Installation Guidelines (this manual)

Please inspect all components upon unboxing to ensure nothing is missing or damaged. Contact customer service immediately if any issues are found.



Figure 2: Product Packaging

3. SPECIFICATIONS

Feature	Detail
Brand	Ganeed
Model Number	GLM-DD-8G
Color	Gold, 8-light
Material	Crystal + Iron
Style	Antique & Vintage & Modern
Light Fixture Form	Chandelier
Product Dimensions	30.7" (Dia) x 21.6" (H) inches
Steel Sling Length	39 inches (adjustable)
Ceiling Cap Diameter	5.5 inch
Bulb Type	E12 X 8 (US standard), Max 25 Watts (Bulbs NOT Included)
Compatible Bulbs	Incandescent, LED, Energy Saving, Halogen bulbs
Voltage	110 Volts

Installation Type	Pendant light (Flush Mount)
Special Features	Adjustable Height, Suitable for inclined or parallel ceilings, Fully dimmable (with compatible dimmer switch and bulbs)
Item Weight	15.53 pounds (7.06 Kilograms)
Indoor/Outdoor Usage	Indoor use only

Figure 3: Product Dimensions



4. SAFETY INFORMATION

WARNING: To reduce the risk of fire, electric shock, or personal injury, please read and follow all instructions carefully before installation and use. Always consult a qualified electrician if you are unsure about any part of the installation process.

- Ensure the power supply is turned OFF at the circuit breaker before beginning installation.
- All electrical connections must be in accordance with local codes, ordinances, and the National Electric Code (NEC).
- Use only E12 base bulbs with a maximum wattage of 25 Watts per bulb. Exceeding this limit may cause overheating and fire.
- Do not connect the fixture to an ungrounded electrical system.
- Handle crystal components with care to prevent breakage.
- Keep packaging materials away from children.

5. SETUP AND INSTALLATION

Installation of this chandelier requires careful attention to detail. It is recommended to have two people for assembly and installation. Please refer to the video and detailed steps below.

5.1 Assembly Steps

1. **Unpack and Identify Components:** Carefully remove all parts from the packaging. Lay them out on a clean, soft surface to prevent scratches. Identify the main body, crystal branches, ceiling canopy, chain, and accessory kit.
2. **Attach Crystal Branches:** Insert each crystal-adorned branch into its designated slot on the main chandelier body. Ensure they are securely fastened.
3. **Wire Connections (Internal):** Connect all white (or blue) wires from the lamp holders to the main white (or blue) wire. Connect all black (or brown) wires from the lamp holders to the main black (or brown) wire. Use wire nuts provided in the accessory kit. Ensure all connections are tight and secure.
4. **Prepare for Hanging:** Attach the chain to the main body of the chandelier and the ceiling canopy.
5. **Install Mounting Bracket:** Drill holes in the ceiling as per the mounting bracket's specifications. Secure the mounting bracket to the ceiling using appropriate anchors and screws.
6. **Wire Connections (External):** Connect the black (or brown) wire from the chandelier to the fire wire (L) from your household wiring. Connect the white (or blue) wire from the chandelier to the neutral wire (N) from your household wiring. Connect the ground wire (green/yellow) from the chandelier to the household ground wire. Use wire nuts and ensure secure connections.
7. **Secure Canopy:** Carefully lift the chandelier and attach the ceiling canopy to the mounting bracket, securing it with the provided screws or nuts.
8. **Install Bulbs:** Screw in the E12 bulbs (not included) into the lamp holders.

5.2 Installation Video Guide

For a visual guide on the assembly and installation process, please watch the official product video below:

Your browser does not support the video tag.

Video 1: Gold Vintage Crystal Chandelier Light Fixtures with 8 Lights - Assembly and Installation Guide. This video demonstrates the step-by-step process of assembling the chandelier components and connecting the electrical wiring for safe installation.

5.3 Key Assembly Details

Pay close attention to the wiring connections. All white (or blue) wires from the lamp holders should be

connected to the main white (or blue) wire, and all black (or brown) wires from the lamp holders should be connected to the main black (or brown) wire. This ensures proper electrical flow and safety.



Figure 4: Detailed view of crystal branches and lamp holders.

6. OPERATING INSTRUCTIONS

Once installed, the Ganeed Crystal Chandelier operates like any standard light fixture controlled by a wall switch. For dimming functionality, ensure you have installed dimmable E12 bulbs and a compatible dimmer switch (not included). The chandelier is designed for indoor use only.



Figure 5: Chandelier in a living room setting.

7. MAINTENANCE

To maintain the beauty and longevity of your Ganeed Crystal Chandelier, follow these maintenance guidelines:

- **Cleaning:** Turn off the power before cleaning. Use a soft, dry cloth to wipe the metal frame. For crystals, a damp cloth with mild glass cleaner can be used, but avoid spraying directly onto electrical components.
- **Bulb Replacement:** Always turn off the power and allow bulbs to cool before replacing them. Use only E12 base bulbs.
- **Regular Inspection:** Periodically check all connections and components for any signs of wear or damage.

8. TROUBLESHOOTING

If you encounter any issues with your chandelier, please refer to the following common troubleshooting steps:

Problem	Possible Cause	Solution
---------	----------------	----------

Light does not turn on	Loose wiring, faulty bulb, tripped circuit breaker.	Check all wire connections, replace bulbs, reset circuit breaker. Ensure power is off before checking wiring.
Flickering lights	Loose bulb, incompatible dimmer, unstable power supply.	Tighten bulbs, ensure dimmer compatibility, consult electrician for power supply issues.
Crystals appear dull	Dust or residue buildup.	Clean crystals with a soft, damp cloth and mild glass cleaner.

If the problem persists after attempting these solutions, please contact Ganeed customer service.

9. WARRANTY AND SUPPORT

Ganeed provides a **1 Year Warranty** for this product. This warranty covers manufacturing defects and material flaws under normal use. It does not cover damage caused by improper installation, misuse, accidents, or unauthorized modifications.

For any questions, technical assistance, or warranty claims, please contact the Ganeed Lighting Store customer service. They are available 7/24 hours to assist you with replacement parts or any other concerns.

Contact Information:

- **Seller:** Ganeed Lighting Store
- Refer to your purchase documentation for specific contact details or visit the Ganeed store on Amazon.