

Manuals+

[Q & A](#) | [Deep Search](#) | [Upload](#)

Manuals.plus /

- › [Ganeed](#) /
- › Ganeed Crystal Chandelier Instruction Manual

Ganeed GLM-XDD-5G

Ganeed Crystal Chandelier Instruction Manual

Model: GLM-XDD-5G | Brand: Ganeed

1. PRODUCT OVERVIEW

The Ganeed Crystal Chandelier is a vintage-style flush-mounted ceiling light designed to enhance the ambiance of various rooms, including living rooms, dining rooms, bedrooms, and hallways. It features K9 clear crystals and a durable metal frame, providing sparkling illumination.



Figure 1.1: Ganeed Gold 5-light Crystal Chandelier installed in a living room.

Key Features:

- **Elegant Design:** Features K9 clear crystals and a gold-finished iron frame, creating a luxurious and vintage aesthetic.
- **Versatile Lighting:** Equipped with 5 E12 sockets, compatible with incandescent, LED, CFL, and halogen bulbs (max 25W per bulb, bulbs not included).
- **Dimmable Functionality:** Fully dimmable when used with compatible dimmer switch and dimmable bulbs (not included).
- **Wide Application:** Ideal for various indoor spaces such as living rooms, dining rooms, bedrooms, kitchens, hallways, and foyers.

2. SETUP AND INSTALLATION

2.1 Safety Precautions

- Always turn off the main power at the circuit breaker before installation, maintenance, or bulb replacement.
- Ensure proper grounding to avoid electrical shock.
- Consult a qualified electrician if you are unsure about any part of the installation process.
- Wear appropriate safety gear, including gloves and eye protection, during installation.

2.2 Unpacking and Parts List

Carefully unpack all components and inspect for any damage. Keep all packaging materials until installation is complete and the fixture is working correctly. The package includes:

- 1 x Ceiling Light Fixture
- 1 x Accessory Kit (mounting hardware)
- 1 x Installation Guidelines (this manual)



Figure 2.1: Unpacked components of the chandelier, including the main body and crystal branches.

2.3 Assembly Steps

Assembly is required and involves attaching the crystal branches and wiring. For a detailed visual guide, please refer to the installation video provided below.

1. **Prepare the Main Body:** Carefully remove the base cover to access the internal wiring.
2. **Attach Crystal Branches:** Secure each crystal-adorned branch to the main fixture body using the provided nuts and a wrench. Ensure they are firmly tightened.
3. **Connect Internal Wiring:** Connect the wires from each branch to the corresponding wires within the main fixture body. Ensure all connections are secure and properly insulated with wire nuts and electrical tape.
4. **Secure Base Cover:** Reattach the base cover to the main fixture body, ensuring all wires are tucked safely inside.
5. **Mount to Ceiling:** Follow standard flush mount installation procedures to secure the fixture to your ceiling junction box. Connect the fixture's main wires to your household wiring (live to live, neutral to neutral, ground to ground).
6. **Install Bulbs:** Screw in 5 E12 base bulbs (not included) into the sockets.
7. **Attach Central Crystal:** Finally, attach the decorative central crystal to the bottom of the fixture.

Your browser does not support the video tag.

Video 2.1: Detailed installation guide for the Ganeed Crystal Chandelier, demonstrating the assembly of branches and wiring connections.

3. OPERATING INSTRUCTIONS

3.1 Powering On/Off

Once installed, restore power at the circuit breaker. Operate the chandelier using your standard wall switch. Ensure the switch is in the 'ON' position for the light to function.

3.2 Dimmable Functionality

This chandelier is designed to be fully dimmable. To utilize this feature, you must use dimmable E12 bulbs and connect the fixture to a compatible dimmer switch (both sold separately). Adjust the dimmer switch to achieve your desired light intensity.

4. MAINTENANCE

4.1 Cleaning

To maintain the chandelier's appearance and sparkle, regular cleaning is recommended. Always turn off the power and allow the fixture to cool before cleaning.

- **For Crystals:** Gently wipe the crystals with a soft, lint-free cloth dampened with a mild glass cleaner or distilled water. Avoid abrasive cleaners that may scratch the crystal surface.
- **For Metal Frame:** Wipe the metal parts with a dry, soft cloth. Do not use harsh chemicals or abrasive materials, as they may damage the finish.

4.2 Bulb Replacement

Before replacing any bulbs, ensure the power to the fixture is turned off at the circuit breaker. Allow bulbs to cool completely before handling.

- Unscrew the old bulb counter-clockwise.
- Screw in the new E12 base bulb clockwise until snug. Do not overtighten.
- Use bulbs that do not exceed the maximum wattage of 25W per socket.

5. TROUBLESHOOTING

If you encounter issues with your Ganeed Crystal Chandelier, please refer to the following common problems and solutions:

Problem	Possible Cause	Solution
Light does not turn on.	No power, loose wiring, faulty bulb, faulty switch.	Check circuit breaker. Ensure all wiring connections are secure. Replace bulb. Test wall switch.
Light flickers or dims unexpectedly.	Loose bulb, incompatible dimmer/bulb, unstable power supply.	Tighten bulbs. Ensure dimmable bulbs are used with a compatible dimmer. Consult electrician for power supply issues.
Fixture appears crooked or unstable.	Improper mounting, loose mounting hardware.	Ensure mounting bracket is securely attached to the ceiling junction box. Tighten all fixture screws.
Crystals are dull or cloudy.	Dust and dirt accumulation.	Clean crystals regularly with a soft, damp cloth and mild cleaner.

If the problem persists after attempting these solutions, please contact Ganeed customer service for further assistance.

6. SPECIFICATIONS

Attribute	Detail
Brand	Ganeed
Model Number	GLM-XDD-5G
Color	Gold, 5-light
Material	Crystal + Iron
Style	Modern & Vintage & Luxury
Light Fixture Form	Close to Ceiling
Product Dimensions	31.5" (Dia) x 11.8" (H) inches
Ceiling Cap Diameter	6.3 inches

Attribute	Detail
Bulb Type	E12 (Incandescent, LED, CFL, Halogen)
Max Wattage per Bulb	25 Watts
Number of Light Sources	5
Voltage	110 Volts
Installation Type	Flush Mount
Assembly Required	Yes
Item Weight	10.89 pounds (approx. 4.95 kg)

7. WARRANTY AND SUPPORT

Ganeed provides a 1-Year Warranty for this product. If you have any questions, require replacement parts, or need further assistance, please do not hesitate to contact Ganeed customer service. Customer service is available 24/7.

You can also visit the official Ganeed store on Amazon for more information and products: [Ganeed Store](#)